stagetronix

KHROMA LB 1810 V3



Manufacturer	**stagetronix**
Type	**PAR**
DMX modes	**3**
DMX footprint	**8, 26, 72 channels**
Beam angle	**16°**
Heads / cells	**18**
Size (W × H × D)	**900 × 70 × 135 mm**
GDTF fixture type	**5B5A1432-A959-4DEA-BF75-DF…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer · Pixel control

Safety-relevant functions

Strobe

DMX modes

1 Basic	8 ch
26 Channel Mode	26 ch
Pixel Mode	72 ch

1 Basic

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 SLOW > FAST
3	Color Macro1	0	0–10 No Function - Custom 11–34 R:100% G:0-100% B:0% W:0% - Color (wheel slot 1) 35–59 R:100-0% G:100% B:0% W:0% - Color (wheel slot 2) 60–84 R:0% G:100% B:0-100% W:0% - Color (wheel slot 3) 85–109 R:0% G:100-0% B:100% W:0% - Color (wheel slot 4) 110–134 R:0-100% G:0% B:100% W:0% - Color (wheel slot 5) 135–159 R:100% G:0% B:100-0% W:0% - Color (wheel slot 6) 160–184 R:100% G:0-100% B:0-100% W:0% - Color (wheel sl... 185–209 R:100-0% G:100-0% B:100% W:0% - Color (wheel sl... 210–255 RGBW:100% - Color (wheel slot 9)
4	Color Macro1Rate	0	0–254 SLOW 255–255 FAST
5	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
6	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
7	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
8	White	255	0–0 Min 1–254 Min > Max 255–255 Max

26 Channel Mode

26 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 SLOW > FAST
3	Color Macro1	0	0–10 No Function - Custom 11–34 R:100% G:0-100% B:0% W:0% - Color (wheel slot 1) 35–59 R:100-0% G:100% B:0% W:0% - Color (wheel slot 2) 60–84 R:0% G:100% B:0-100% W:0% - Color (wheel slot 3) 85–109 R:0% G:100-0% B:100% W:0% - Color (wheel slot 4) 110–134 R:0-100% G:0% B:100% W:0% - Color (wheel slot 5) 135–159 R:100% G:0% B:100-0% W:0% - Color (wheel slot 6) 160–184 R:100% G:0-100% B:0-100% W:0% - Color (wheel sl... 185–209 R:100-0% G:100-0% B:100% W:0% - Color (wheel sl... 210–255 RGBW:100% - Color (wheel slot 9)
4	Color Macro1Rate	0	0–254 SLOW 255–255 FAST
5	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
6	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
7	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max

26 Channel Mode (continued)

Ch	Function	Default	DMX values
8	White	255	0–0 Min 1–254 Min > Max 255–255 Max
9	Dimmer	0	
10	Dimmer	0	
11	Dimmer	0	
12	Dimmer	0	
13	Dimmer	0	
14	Dimmer	0	
15	Dimmer	0	
16	Dimmer	0	
17	Dimmer	0	
18	Dimmer	0	
19	Dimmer	0	
20	Dimmer	0	
21	Dimmer	0	
22	Dimmer	0	
23	Dimmer	0	
24	Dimmer	0	
25	Dimmer	0	
26	Dimmer	0	

Pixel Mode

72 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	0	
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	0	
9	Red	0	
10	Green	0	
11	Blue	0	
12	White	0	
13	Red	0	
14	Green	0	
15	Blue	0	
16	White	0	
17	Red	0	
18	Green	0	
19	Blue	0	
20	White	0	
21	Red	0	

Pixel Mode (continued)

Ch	Function	Default	DMX values
22	Green	0	
23	Blue	0	
24	White	0	
25	Red	0	
26	Green	0	
27	Blue	0	
28	White	0	
29	Red	0	
30	Green	0	
31	Blue	0	
32	White	0	
33	Red	0	
34	Green	0	
35	Blue	0	
36	White	0	
37	Red	0	
38	Green	0	
39	Blue	0	
40	White	0	
41	Red	0	
42	Green	0	
43	Blue	0	
44	White	0	
45	Red	0	
46	Green	0	
47	Blue	0	
48	White	0	
49	Red	0	
50	Green	0	
51	Blue	0	
52	White	0	
53	Red	0	
54	Green	0	
55	Blue	0	
56	White	0	
57	Red	0	
58	Green	0	
59	Blue	0	
60	White	0	
61	Red	0	
62	Green	0	
63	Blue	0	
64	White	0	
65	Red	0	
66	Green	0	

Pixel Mode (continued)

Ch	Function	Default	DMX values
67	Blue	0	
68	White	0	
69	Red	0	
70	Green	0	
71	Blue	0	
72	White	0	