
ADJ

ElectraPix Par 7



Manufacturer	**ADJ**
Type	**Effect light**
DMX modes	**11**
DMX footprint	**5, 6, 7, 9, 12, 13, 22, 24, 45, 60 channels**
Beam angle	**17°**
Heads / cells	**2**
Size (W × H × D)	**320 × 270 × 65 mm**
GDTF fixture type	**43EBD60F-B3CE-47C6-AD7D-9F…**

Controls

Extra LED colours · RGB colour mixing · Colour temperature · Colour wheel · Effect speed · Strobe · Dimmer · Pixel control

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

5ch	5 ch
42ch	6 ch
6ch	6 ch
7Ch	7 ch
9ch	9 ch
12Ch	12 ch
13ch	13 ch
22ch	22 ch
24ch	24 ch
45ch	45 ch
60ch	60 ch

5ch

5 channels

Ch	Function	Default	DMX values
1	C TO	0	0–0 Off 1–255 2300K to 9900K

5ch (continued)

Ch	Function	Default	DMX values
2	Color Wheel 2	0	0–22 No Function (wheel slot 1) 23–23 2300K (wheel slot 2) 24–24 2400K (wheel slot 3) 25–25 2500K (wheel slot 4) 26–26 2600K (wheel slot 5) 27–27 2700K (wheel slot 6) 28–28 2800K (wheel slot 7) 29–29 2900K (wheel slot 8) 30–30 3000K (wheel slot 9) 31–31 3100K (wheel slot 10) 32–32 3200K (wheel slot 11) 33–33 3300K (wheel slot 12) 34–34 3400K (wheel slot 13) 35–35 3500K (wheel slot 14) 36–36 3600K (wheel slot 15) 37–37 3700K (wheel slot 16) 38–38 3800K (wheel slot 17) 39–39 3900K (wheel slot 18) 40–40 4000K (wheel slot 19) 41–41 4100K (wheel slot 20) 42–42 4200K (wheel slot 21) 43–43 4300K (wheel slot 22) 44–44 4400K (wheel slot 23) 45–45 4500K (wheel slot 24) 46–46 4600K (wheel slot 25) 47–47 4700K (wheel slot 26) 48–48 4800K (wheel slot 27) 49–49 4900K (wheel slot 28) 50–50 5000K (wheel slot 29) 51–51 5100K (wheel slot 30) 52–52 5200K (wheel slot 31) 53–53 5300K (wheel slot 32) 54–54 5400K (wheel slot 33) 55–55 5500K (wheel slot 34) 56–56 5600K (wheel slot 35) 57–57 5700K (wheel slot 36) 58–58 5800K (wheel slot 37) 59–59 5900K (wheel slot 38) 60–60 6000K (wheel slot 39) 61–61 6100K (wheel slot 40) 62–62 6200K (wheel slot 41) 63–63 6300K (wheel slot 42) 64–64 6400K (wheel slot 43) 65–65 6500K (wheel slot 44) 66–66 6600K (wheel slot 45) 67–67 6700K (wheel slot 46) 68–68 6800K (wheel slot 47) 69–69 6900K (wheel slot 48) 70–70 7000K (wheel slot 49) 71–71 7100K (wheel slot 50) 72–72 7200K (wheel slot 51) 73–73 7300K (wheel slot 52) 74–74 7400K (wheel slot 53) 75–75 7500K (wheel slot 54) 76–76 7600K (wheel slot 55) 77–77 7700K (wheel slot 56) 78–78 7800K (wheel slot 57) 79–79 7900K (wheel slot 58) 80–80 8000K (wheel slot 59) 81–81 8100K (wheel slot 60) 82–82 8200K (wheel slot 61) 83–83 8300K (wheel slot 62) 84–84 8400K (wheel slot 63) 85–85 8500K (wheel slot 64)

5ch (continued)

Ch	Function	Default	DMX values
3	Shutter / Strobe	32	0–31 LEDs Off 32–63 LEDs ON 64–95 Strobe Slow to Fast 96–127 LEDs ON 128–159 Pulse Slow to Fast 160–191 Shutter Open 192–223 Rnd Strobe Slow to Fast 224–255 LEDs ON
4	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent
5	Dimmer Fine	0	Fine byte of Dimmer

42ch

6 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

6ch

6 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

6ch (continued)

Ch	Function	Default	DMX values
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

7Ch

7 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

7Ch (continued)

Ch	Function	Default	DMX values
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
7	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent

9ch

9 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
7	Red	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
8	Green	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background

9ch (continued)

Ch	Function	Default	DMX values
9	Blue	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background

12Ch

12 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
7	Red	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
8	Green	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
9	Blue	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
10	C TO	0	0–0 Off 1–255 2300K to 9900K

12Ch (continued)

Ch	Function	Default	DMX values
11	Shutter / Strobe	32	0–31 LEDs Off 32–63 LEDs ON 64–95 Strobe Slow to Fast 96–127 LEDs ON 128–159 Pulse Slow to Fast 160–191 Shutter Open 192–223 Rnd Strobe Slow to Fast 224–255 LEDs ON
12	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent

13ch

13 channels

Ch	Function	Default	DMX values

13ch (continued)

Ch	Function	Default	DMX values
1	Color Wheel	0	0–0 Off (wheel slot 1) 1–4 Color Macro 1 (wheel slot 2) 5–8 Color Macro 2 (wheel slot 3) 9–12 Color Macro 3 (wheel slot 4) 13–16 Color Macro 4 (wheel slot 5) 17–20 Color Macro 5 (wheel slot 6) 21–24 Color Macro 6 (wheel slot 7) 25–28 Color Macro 7 (wheel slot 8) 29–32 Color Macro 8 (wheel slot 9) 33–36 Color Macro 9 (wheel slot 10) 37–40 Color Macro 10 (wheel slot 11) 41–44 Color Macro 11 (wheel slot 12) 45–48 Color Macro 12 (wheel slot 13) 49–52 Color Macro 13 (wheel slot 14) 53–56 Color Macro 14 (wheel slot 15) 57–60 Color Macro 15 (wheel slot 16) 61–64 Color Macro 16 (wheel slot 17) 65–68 Color Macro 17 (wheel slot 18) 69–72 Color Macro 18 (wheel slot 19) 73–76 Color Macro 19 (wheel slot 20) 77–80 Color Macro 20 (wheel slot 21) 81–84 Color Macro 21 (wheel slot 22) 85–88 Color Macro 22 (wheel slot 23) 89–92 Color Macro 23 (wheel slot 24) 93–96 Color Macro 24 (wheel slot 25) 97–100 Color Macro 25 (wheel slot 26) 101–104 Color Macro 26 (wheel slot 27) 105–108 Color Macro 27 (wheel slot 28) 109–112 Color Macro 28 (wheel slot 29) 113–116 Color Macro 29 (wheel slot 30) 117–120 Color Macro 30 (wheel slot 31) 121–124 Color Macro 31 (wheel slot 32) 125–128 Color Macro 32 (wheel slot 33) 129–132 Color Macro 33 (wheel slot 34) 133–136 Color Macro 34 (wheel slot 35) 137–140 Color Macro 35 (wheel slot 36) 141–144 Color Macro 36 (wheel slot 37) 145–148 Color Macro 37 (wheel slot 38) 149–152 Color Macro 38 (wheel slot 39) 153–156 Color Macro 39 (wheel slot 40) 157–160 Color Macro 40 (wheel slot 41) 161–164 Color Macro 41 (wheel slot 42) 165–168 Color Macro 42 (wheel slot 43) 169–172 Color Macro 43 (wheel slot 44) 173–176 Color Macro 44 (wheel slot 45) 177–180 Color Macro 45 (wheel slot 46) 181–184 Color Macro 46 (wheel slot 47) 185–188 Color Macro 47 (wheel slot 48) 189–192 Color Macro 48 (wheel slot 49) 193–196 Color Macro 49 (wheel slot 50) 197–200 Color Macro 50 (wheel slot 51) 201–204 Color Macro 51 (wheel slot 52) 205–208 Color Macro 52 (wheel slot 53) 209–212 Color Macro 53 (wheel slot 54) 213–216 Color Macro 54 (wheel slot 55) 217–220 Color Macro 55 (wheel slot 56) 221–224 Color Macro 56 (wheel slot 57) 225–228 Color Macro 57 (wheel slot 58) 229–232 Color Macro 58 (wheel slot 59) 233–236 Color Macro 59 (wheel slot 60) 237–240 Color Macro 60 (wheel slot 61) 241–244 Color Macro 61 (wheel slot 62) 245–248 Color Macro 62 (wheel slot 63) 249–252 Color Macro 63 (wheel slot 64)

13ch (continued)

Ch	Function	Default	DMX values
2	Color3	0	
3	C TO	0	0–0 Off 1–255 2300K to 9900K

13ch (continued)

Ch	Function	Default	DMX values
4	Color Wheel 2	0	0–22 No Function (wheel slot 1) 23–23 2300K (wheel slot 2) 24–24 2400K (wheel slot 3) 25–25 2500K (wheel slot 4) 26–26 2600K (wheel slot 5) 27–27 2700K (wheel slot 6) 28–28 2800K (wheel slot 7) 29–29 2900K (wheel slot 8) 30–30 3000K (wheel slot 9) 31–31 3100K (wheel slot 10) 32–32 3200K (wheel slot 11) 33–33 3300K (wheel slot 12) 34–34 3400K (wheel slot 13) 35–35 3500K (wheel slot 14) 36–36 3600K (wheel slot 15) 37–37 3700K (wheel slot 16) 38–38 3800K (wheel slot 17) 39–39 3900K (wheel slot 18) 40–40 4000K (wheel slot 19) 41–41 4100K (wheel slot 20) 42–42 4200K (wheel slot 21) 43–43 4300K (wheel slot 22) 44–44 4400K (wheel slot 23) 45–45 4500K (wheel slot 24) 46–46 4600K (wheel slot 25) 47–47 4700K (wheel slot 26) 48–48 4800K (wheel slot 27) 49–49 4900K (wheel slot 28) 50–50 5000K (wheel slot 29) 51–51 5100K (wheel slot 30) 52–52 5200K (wheel slot 31) 53–53 5300K (wheel slot 32) 54–54 5400K (wheel slot 33) 55–55 5500K (wheel slot 34) 56–56 5600K (wheel slot 35) 57–57 5700K (wheel slot 36) 58–58 5800K (wheel slot 37) 59–59 5900K (wheel slot 38) 60–60 6000K (wheel slot 39) 61–61 6100K (wheel slot 40) 62–62 6200K (wheel slot 41) 63–63 6300K (wheel slot 42) 64–64 6400K (wheel slot 43) 65–65 6500K (wheel slot 44) 66–66 6600K (wheel slot 45) 67–67 6700K (wheel slot 46) 68–68 6800K (wheel slot 47) 69–69 6900K (wheel slot 48) 70–70 7000K (wheel slot 49) 71–71 7100K (wheel slot 50) 72–72 7200K (wheel slot 51) 73–73 7300K (wheel slot 52) 74–74 7400K (wheel slot 53) 75–75 7500K (wheel slot 54) 76–76 7600K (wheel slot 55) 77–77 7700K (wheel slot 56) 78–78 7800K (wheel slot 57) 79–79 7900K (wheel slot 58) 80–80 8000K (wheel slot 59) 81–81 8100K (wheel slot 60) 82–82 8200K (wheel slot 61) 83–83 8300K (wheel slot 62) 84–84 8400K (wheel slot 63) 85–85 8500K (wheel slot 64)

13ch (continued)

Ch	Function	Default	DMX values
5	Shutter / Strobe	32	0–31 LEDs Off 32–63 LEDs ON 64–95 Strobe Slow to Fast 96–127 LEDs ON 128–159 Pulse Slow to Fast 160–191 Shutter Open 192–223 Rnd Strobe Slow to Fast 224–255 LEDs ON
6	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent
7	Dimmer Fine	0	Fine byte of Dimmer
8	Effect	0	0–10 Off 11–26 Auto Program 1 27–43 Auto Program 2 44–60 Auto Program 3 61–76 Auto Program 4 77–93 Auto Program 5 94–110 Auto Program 6 111–126 Auto Program 7 127–143 Auto Program 8 144–160 Auto Program 9 161–176 Auto Program 10 177–193 Auto Program 11 194–210 Auto Program 12 211–226 Auto Program 13 227–255 No Function
9	Effect Speed	0	
10	Effects1Fade	0	
11	Effect	0	0–10 Off Background 11–26 Auto Program 1 Background 27–43 Auto Program 2 Background 44–60 Auto Program 3 Background 61–76 Auto Program 4 Background 77–93 Auto Program 5 Background 94–110 Auto Program 6 Background 111–126 Auto Program 7 Background 127–143 Auto Program 8 Background 144–160 Auto Program 9 Background 161–176 Auto Program 10 Background 177–193 Auto Program 11 Background 194–210 Auto Program 12 Background 211–226 Auto Program 13 Background 227–255 No Function Background
12	Effect Speed	0	
13	Effects1Fade	0	

22ch

22 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

22ch (continued)

Ch	Function	Default	DMX values
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

22ch (continued)

Ch	Function	Default	DMX values
7	Color Wheel	0	0–0 Off (wheel slot 1) 1–4 Color Macro 1 (wheel slot 2) 5–8 Color Macro 2 (wheel slot 3) 9–12 Color Macro 3 (wheel slot 4) 13–16 Color Macro 4 (wheel slot 5) 17–20 Color Macro 5 (wheel slot 6) 21–24 Color Macro 6 (wheel slot 7) 25–28 Color Macro 7 (wheel slot 8) 29–32 Color Macro 8 (wheel slot 9) 33–36 Color Macro 9 (wheel slot 10) 37–40 Color Macro 10 (wheel slot 11) 41–44 Color Macro 11 (wheel slot 12) 45–48 Color Macro 12 (wheel slot 13) 49–52 Color Macro 13 (wheel slot 14) 53–56 Color Macro 14 (wheel slot 15) 57–60 Color Macro 15 (wheel slot 16) 61–64 Color Macro 16 (wheel slot 17) 65–68 Color Macro 17 (wheel slot 18) 69–72 Color Macro 18 (wheel slot 19) 73–76 Color Macro 19 (wheel slot 20) 77–80 Color Macro 20 (wheel slot 21) 81–84 Color Macro 21 (wheel slot 22) 85–88 Color Macro 22 (wheel slot 23) 89–92 Color Macro 23 (wheel slot 24) 93–96 Color Macro 24 (wheel slot 25) 97–100 Color Macro 25 (wheel slot 26) 101–104 Color Macro 26 (wheel slot 27) 105–108 Color Macro 27 (wheel slot 28) 109–112 Color Macro 28 (wheel slot 29) 113–116 Color Macro 29 (wheel slot 30) 117–120 Color Macro 30 (wheel slot 31) 121–124 Color Macro 31 (wheel slot 32) 125–128 Color Macro 32 (wheel slot 33) 129–132 Color Macro 33 (wheel slot 34) 133–136 Color Macro 34 (wheel slot 35) 137–140 Color Macro 35 (wheel slot 36) 141–144 Color Macro 36 (wheel slot 37) 145–148 Color Macro 37 (wheel slot 38) 149–152 Color Macro 38 (wheel slot 39) 153–156 Color Macro 39 (wheel slot 40) 157–160 Color Macro 40 (wheel slot 41) 161–164 Color Macro 41 (wheel slot 42) 165–168 Color Macro 42 (wheel slot 43) 169–172 Color Macro 43 (wheel slot 44) 173–176 Color Macro 44 (wheel slot 45) 177–180 Color Macro 45 (wheel slot 46) 181–184 Color Macro 46 (wheel slot 47) 185–188 Color Macro 47 (wheel slot 48) 189–192 Color Macro 48 (wheel slot 49) 193–196 Color Macro 49 (wheel slot 50) 197–200 Color Macro 50 (wheel slot 51) 201–204 Color Macro 51 (wheel slot 52) 205–208 Color Macro 52 (wheel slot 53) 209–212 Color Macro 53 (wheel slot 54) 213–216 Color Macro 54 (wheel slot 55) 217–220 Color Macro 55 (wheel slot 56) 221–224 Color Macro 56 (wheel slot 57) 225–228 Color Macro 57 (wheel slot 58) 229–232 Color Macro 58 (wheel slot 59) 233–236 Color Macro 59 (wheel slot 60) 237–240 Color Macro 60 (wheel slot 61) 241–244 Color Macro 61 (wheel slot 62) 245–248 Color Macro 62 (wheel slot 63) 249–252 Color Macro 63 (wheel slot 64)

22ch (continued)

Ch	Function	Default	DMX values
8	Red	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
9	Green	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
10	Blue	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
11	Color3	0	
12	C TO	0	0–0 Off 1–255 2300K to 9900K

22ch (continued)

Ch	Function	Default	DMX values
13	Color Wheel 2	0	0–22 No Function (wheel slot 1) 23–23 2300K (wheel slot 2) 24–24 2400K (wheel slot 3) 25–25 2500K (wheel slot 4) 26–26 2600K (wheel slot 5) 27–27 2700K (wheel slot 6) 28–28 2800K (wheel slot 7) 29–29 2900K (wheel slot 8) 30–30 3000K (wheel slot 9) 31–31 3100K (wheel slot 10) 32–32 3200K (wheel slot 11) 33–33 3300K (wheel slot 12) 34–34 3400K (wheel slot 13) 35–35 3500K (wheel slot 14) 36–36 3600K (wheel slot 15) 37–37 3700K (wheel slot 16) 38–38 3800K (wheel slot 17) 39–39 3900K (wheel slot 18) 40–40 4000K (wheel slot 19) 41–41 4100K (wheel slot 20) 42–42 4200K (wheel slot 21) 43–43 4300K (wheel slot 22) 44–44 4400K (wheel slot 23) 45–45 4500K (wheel slot 24) 46–46 4600K (wheel slot 25) 47–47 4700K (wheel slot 26) 48–48 4800K (wheel slot 27) 49–49 4900K (wheel slot 28) 50–50 5000K (wheel slot 29) 51–51 5100K (wheel slot 30) 52–52 5200K (wheel slot 31) 53–53 5300K (wheel slot 32) 54–54 5400K (wheel slot 33) 55–55 5500K (wheel slot 34) 56–56 5600K (wheel slot 35) 57–57 5700K (wheel slot 36) 58–58 5800K (wheel slot 37) 59–59 5900K (wheel slot 38) 60–60 6000K (wheel slot 39) 61–61 6100K (wheel slot 40) 62–62 6200K (wheel slot 41) 63–63 6300K (wheel slot 42) 64–64 6400K (wheel slot 43) 65–65 6500K (wheel slot 44) 66–66 6600K (wheel slot 45) 67–67 6700K (wheel slot 46) 68–68 6800K (wheel slot 47) 69–69 6900K (wheel slot 48) 70–70 7000K (wheel slot 49) 71–71 7100K (wheel slot 50) 72–72 7200K (wheel slot 51) 73–73 7300K (wheel slot 52) 74–74 7400K (wheel slot 53) 75–75 7500K (wheel slot 54) 76–76 7600K (wheel slot 55) 77–77 7700K (wheel slot 56) 78–78 7800K (wheel slot 57) 79–79 7900K (wheel slot 58) 80–80 8000K (wheel slot 59) 81–81 8100K (wheel slot 60) 82–82 8200K (wheel slot 61) 83–83 8300K (wheel slot 62) 84–84 8400K (wheel slot 63) 85–85 8500K (wheel slot 64)

22ch (continued)

Ch	Function	Default	DMX values
14	Shutter / Strobe	32	0–31 LEDs Off 32–63 LEDs ON 64–95 Strobe Slow to Fast 96–127 LEDs ON 128–159 Pulse Slow to Fast 160–191 Shutter Open 192–223 Rnd Strobe Slow to Fast 224–255 LEDs ON
15	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent
16	Dimmer Fine	0	Fine byte of Dimmer
17	Effect	0	0–10 Off 11–26 Auto Program 1 27–43 Auto Program 2 44–60 Auto Program 3 61–76 Auto Program 4 77–93 Auto Program 5 94–110 Auto Program 6 111–126 Auto Program 7 127–143 Auto Program 8 144–160 Auto Program 9 161–176 Auto Program 10 177–193 Auto Program 11 194–210 Auto Program 12 211–226 Auto Program 13 227–255 No Function
18	Effect Speed	0	
19	Effects1Fade	0	
20	Effect	0	0–10 Off Background 11–26 Auto Program 1 Background 27–43 Auto Program 2 Background 44–60 Auto Program 3 Background 61–76 Auto Program 4 Background 77–93 Auto Program 5 Background 94–110 Auto Program 6 Background 111–126 Auto Program 7 Background 127–143 Auto Program 8 Background 144–160 Auto Program 9 Background 161–176 Auto Program 10 Background 177–193 Auto Program 11 Background 194–210 Auto Program 12 Background 211–226 Auto Program 13 Background 227–255 No Function Background
21	Effect Speed	0	
22	Effects1Fade	0	

24ch

24 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

24ch (continued)

Ch	Function	Default	DMX values
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

24ch (continued)

Ch	Function	Default	DMX values
7	Color Wheel	0	0–0 Off (wheel slot 1) 1–4 Color Macro 1 (wheel slot 2) 5–8 Color Macro 2 (wheel slot 3) 9–12 Color Macro 3 (wheel slot 4) 13–16 Color Macro 4 (wheel slot 5) 17–20 Color Macro 5 (wheel slot 6) 21–24 Color Macro 6 (wheel slot 7) 25–28 Color Macro 7 (wheel slot 8) 29–32 Color Macro 8 (wheel slot 9) 33–36 Color Macro 9 (wheel slot 10) 37–40 Color Macro 10 (wheel slot 11) 41–44 Color Macro 11 (wheel slot 12) 45–48 Color Macro 12 (wheel slot 13) 49–52 Color Macro 13 (wheel slot 14) 53–56 Color Macro 14 (wheel slot 15) 57–60 Color Macro 15 (wheel slot 16) 61–64 Color Macro 16 (wheel slot 17) 65–68 Color Macro 17 (wheel slot 18) 69–72 Color Macro 18 (wheel slot 19) 73–76 Color Macro 19 (wheel slot 20) 77–80 Color Macro 20 (wheel slot 21) 81–84 Color Macro 21 (wheel slot 22) 85–88 Color Macro 22 (wheel slot 23) 89–92 Color Macro 23 (wheel slot 24) 93–96 Color Macro 24 (wheel slot 25) 97–100 Color Macro 25 (wheel slot 26) 101–104 Color Macro 26 (wheel slot 27) 105–108 Color Macro 27 (wheel slot 28) 109–112 Color Macro 28 (wheel slot 29) 113–116 Color Macro 29 (wheel slot 30) 117–120 Color Macro 30 (wheel slot 31) 121–124 Color Macro 31 (wheel slot 32) 125–128 Color Macro 32 (wheel slot 33) 129–132 Color Macro 33 (wheel slot 34) 133–136 Color Macro 34 (wheel slot 35) 137–140 Color Macro 35 (wheel slot 36) 141–144 Color Macro 36 (wheel slot 37) 145–148 Color Macro 37 (wheel slot 38) 149–152 Color Macro 38 (wheel slot 39) 153–156 Color Macro 39 (wheel slot 40) 157–160 Color Macro 40 (wheel slot 41) 161–164 Color Macro 41 (wheel slot 42) 165–168 Color Macro 42 (wheel slot 43) 169–172 Color Macro 43 (wheel slot 44) 173–176 Color Macro 44 (wheel slot 45) 177–180 Color Macro 45 (wheel slot 46) 181–184 Color Macro 46 (wheel slot 47) 185–188 Color Macro 47 (wheel slot 48) 189–192 Color Macro 48 (wheel slot 49) 193–196 Color Macro 49 (wheel slot 50) 197–200 Color Macro 50 (wheel slot 51) 201–204 Color Macro 51 (wheel slot 52) 205–208 Color Macro 52 (wheel slot 53) 209–212 Color Macro 53 (wheel slot 54) 213–216 Color Macro 54 (wheel slot 55) 217–220 Color Macro 55 (wheel slot 56) 221–224 Color Macro 56 (wheel slot 57) 225–228 Color Macro 57 (wheel slot 58) 229–232 Color Macro 58 (wheel slot 59) 233–236 Color Macro 59 (wheel slot 60) 237–240 Color Macro 60 (wheel slot 61) 241–244 Color Macro 61 (wheel slot 62) 245–248 Color Macro 62 (wheel slot 63) 249–252 Color Macro 63 (wheel slot 64)

24ch (continued)

Ch	Function	Default	DMX values
8	Red	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
9	Green	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
10	Blue	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
11	Color3	0	
12	C TO	0	0–0 Off 1–255 2300K to 9900K

24ch (continued)

Ch	Function	Default	DMX values
13	Color Wheel 2	0	0–22 No Function (wheel slot 1) 23–23 2300K (wheel slot 2) 24–24 2400K (wheel slot 3) 25–25 2500K (wheel slot 4) 26–26 2600K (wheel slot 5) 27–27 2700K (wheel slot 6) 28–28 2800K (wheel slot 7) 29–29 2900K (wheel slot 8) 30–30 3000K (wheel slot 9) 31–31 3100K (wheel slot 10) 32–32 3200K (wheel slot 11) 33–33 3300K (wheel slot 12) 34–34 3400K (wheel slot 13) 35–35 3500K (wheel slot 14) 36–36 3600K (wheel slot 15) 37–37 3700K (wheel slot 16) 38–38 3800K (wheel slot 17) 39–39 3900K (wheel slot 18) 40–40 4000K (wheel slot 19) 41–41 4100K (wheel slot 20) 42–42 4200K (wheel slot 21) 43–43 4300K (wheel slot 22) 44–44 4400K (wheel slot 23) 45–45 4500K (wheel slot 24) 46–46 4600K (wheel slot 25) 47–47 4700K (wheel slot 26) 48–48 4800K (wheel slot 27) 49–49 4900K (wheel slot 28) 50–50 5000K (wheel slot 29) 51–51 5100K (wheel slot 30) 52–52 5200K (wheel slot 31) 53–53 5300K (wheel slot 32) 54–54 5400K (wheel slot 33) 55–55 5500K (wheel slot 34) 56–56 5600K (wheel slot 35) 57–57 5700K (wheel slot 36) 58–58 5800K (wheel slot 37) 59–59 5900K (wheel slot 38) 60–60 6000K (wheel slot 39) 61–61 6100K (wheel slot 40) 62–62 6200K (wheel slot 41) 63–63 6300K (wheel slot 42) 64–64 6400K (wheel slot 43) 65–65 6500K (wheel slot 44) 66–66 6600K (wheel slot 45) 67–67 6700K (wheel slot 46) 68–68 6800K (wheel slot 47) 69–69 6900K (wheel slot 48) 70–70 7000K (wheel slot 49) 71–71 7100K (wheel slot 50) 72–72 7200K (wheel slot 51) 73–73 7300K (wheel slot 52) 74–74 7400K (wheel slot 53) 75–75 7500K (wheel slot 54) 76–76 7600K (wheel slot 55) 77–77 7700K (wheel slot 56) 78–78 7800K (wheel slot 57) 79–79 7900K (wheel slot 58) 80–80 8000K (wheel slot 59) 81–81 8100K (wheel slot 60) 82–82 8200K (wheel slot 61) 83–83 8300K (wheel slot 62) 84–84 8400K (wheel slot 63) 85–85 8500K (wheel slot 64)

24ch (continued)

Ch	Function	Default	DMX values
14	Shutter / Strobe	32	0–31 LEDs Off 32–63 LEDs ON 64–95 Strobe Slow to Fast 96–127 LEDs ON 128–159 Pulse Slow to Fast 160–191 Shutter Open 192–223 Rnd Strobe Slow to Fast 224–255 LEDs ON
15	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent
16	Dimmer Fine	0	Fine byte of Dimmer
17	Effect	0	0–10 Off 11–26 Auto Program 1 27–43 Auto Program 2 44–60 Auto Program 3 61–76 Auto Program 4 77–93 Auto Program 5 94–110 Auto Program 6 111–126 Auto Program 7 127–143 Auto Program 8 144–160 Auto Program 9 161–176 Auto Program 10 177–193 Auto Program 11 194–210 Auto Program 12 211–226 Auto Program 13 227–255 No Function
18	Effect Speed	0	
19	Effects1Fade	0	
20	Effect	0	0–10 Off Background 11–26 Auto Program 1 Background 27–43 Auto Program 2 Background 44–60 Auto Program 3 Background 61–76 Auto Program 4 Background 77–93 Auto Program 5 Background 94–110 Auto Program 6 Background 111–126 Auto Program 7 Background 127–143 Auto Program 8 Background 144–160 Auto Program 9 Background 161–176 Auto Program 10 Background 177–193 Auto Program 11 Background 194–210 Auto Program 12 Background 211–226 Auto Program 13 Background 227–255 No Function Background
21	Effect Speed	0	
22	Effects1Fade	0	

24ch (continued)

Ch	Function	Default	DMX values
23	Dimmer Mode	0	0–20 Default to Unit Setting 21–40 Standard 41–60 Stage 61–80 TV 81–100 Architectural 101–120 Theater 121–140 Stage 2 141–141 0*1 second 142–142 0*2 seconds 143–143 0*3 seconds 144–144 0*4 seconds 145–145 0*5 seconds 146–146 0*6 seconds 147–147 0*7 seconds 148–148 0*8 seconds 149–149 0*9 seconds 150–150 1 second 151–151 1*5 seconds 152–152 2 seconds 153–153 3 seconds 154–154 4 seconds 155–155 5 seconds 156–156 6 seconds 157–157 7 seconds 158–158 8 seconds 159–159 9 seconds 160–160 10 seconds 161–255 Default to Unit Setting
24	Dimmer Curve	0	0–20 Square 21–40 Linear 41–60 Inverted Square 61–80 S Curve 81–255 No function

45ch

45 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

45ch (continued)

Ch	Function	Default	DMX values
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
7	Reserved 7	0	
8	Reserved 8	0	
9	Reserved 9	0	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	Reserved 13	0	
14	Reserved 14	0	
15	Reserved 15	0	
16	Reserved 16	0	
17	Reserved 17	0	
18	Reserved 18	0	
19	Reserved 19	0	
20	Reserved 20	0	
21	Reserved 21	0	
22	Reserved 22	0	
23	Reserved 23	0	
24	Reserved 24	0	
25	Reserved 25	0	
26	Reserved 26	0	
27	Reserved 27	0	
28	Reserved 28	0	
29	Reserved 29	0	
30	Reserved 30	0	
31	Reserved 31	0	
32	Reserved 32	0	
33	Reserved 33	0	
34	Reserved 34	0	
35	Reserved 35	0	
36	Reserved 36	0	
37	Reserved 37	0	
38	Reserved 38	0	
39	Reserved 39	0	
40	Reserved 40	0	
41	Reserved 41	0	
42	Reserved 42	0	

45ch (continued)

Ch	Function	Default	DMX values
43	Red	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
44	Green	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
45	Blue	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background

60ch

60 channels

Ch	Function	Default	DMX values
1	Red	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Color Add RY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
5	Color Add GY	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
6	UV	0	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
7	Reserved 7	0	
8	Reserved 8	0	
9	Reserved 9	0	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	Reserved 13	0	

60ch (continued)

Ch	Function	Default	DMX values
14	Reserved 14	0	
15	Reserved 15	0	
16	Reserved 16	0	
17	Reserved 17	0	
18	Reserved 18	0	
19	Reserved 19	0	
20	Reserved 20	0	
21	Reserved 21	0	
22	Reserved 22	0	
23	Reserved 23	0	
24	Reserved 24	0	
25	Reserved 25	0	
26	Reserved 26	0	
27	Reserved 27	0	
28	Reserved 28	0	
29	Reserved 29	0	
30	Reserved 30	0	
31	Reserved 31	0	
32	Reserved 32	0	
33	Reserved 33	0	
34	Reserved 34	0	
35	Reserved 35	0	
36	Reserved 36	0	
37	Reserved 37	0	
38	Reserved 38	0	
39	Reserved 39	0	
40	Reserved 40	0	
41	Reserved 41	0	
42	Reserved 42	0	

60ch (continued)

Ch	Function	Default	DMX values
43	Color Wheel	0	0–0 Off (wheel slot 1) 1–4 Color Macro 1 (wheel slot 2) 5–8 Color Macro 2 (wheel slot 3) 9–12 Color Macro 3 (wheel slot 4) 13–16 Color Macro 4 (wheel slot 5) 17–20 Color Macro 5 (wheel slot 6) 21–24 Color Macro 6 (wheel slot 7) 25–28 Color Macro 7 (wheel slot 8) 29–32 Color Macro 8 (wheel slot 9) 33–36 Color Macro 9 (wheel slot 10) 37–40 Color Macro 10 (wheel slot 11) 41–44 Color Macro 11 (wheel slot 12) 45–48 Color Macro 12 (wheel slot 13) 49–52 Color Macro 13 (wheel slot 14) 53–56 Color Macro 14 (wheel slot 15) 57–60 Color Macro 15 (wheel slot 16) 61–64 Color Macro 16 (wheel slot 17) 65–68 Color Macro 17 (wheel slot 18) 69–72 Color Macro 18 (wheel slot 19) 73–76 Color Macro 19 (wheel slot 20) 77–80 Color Macro 20 (wheel slot 21) 81–84 Color Macro 21 (wheel slot 22) 85–88 Color Macro 22 (wheel slot 23) 89–92 Color Macro 23 (wheel slot 24) 93–96 Color Macro 24 (wheel slot 25) 97–100 Color Macro 25 (wheel slot 26) 101–104 Color Macro 26 (wheel slot 27) 105–108 Color Macro 27 (wheel slot 28) 109–112 Color Macro 28 (wheel slot 29) 113–116 Color Macro 29 (wheel slot 30) 117–120 Color Macro 30 (wheel slot 31) 121–124 Color Macro 31 (wheel slot 32) 125–128 Color Macro 32 (wheel slot 33) 129–132 Color Macro 33 (wheel slot 34) 133–136 Color Macro 34 (wheel slot 35) 137–140 Color Macro 35 (wheel slot 36) 141–144 Color Macro 36 (wheel slot 37) 145–148 Color Macro 37 (wheel slot 38) 149–152 Color Macro 38 (wheel slot 39) 153–156 Color Macro 39 (wheel slot 40) 157–160 Color Macro 40 (wheel slot 41) 161–164 Color Macro 41 (wheel slot 42) 165–168 Color Macro 42 (wheel slot 43) 169–172 Color Macro 43 (wheel slot 44) 173–176 Color Macro 44 (wheel slot 45) 177–180 Color Macro 45 (wheel slot 46) 181–184 Color Macro 46 (wheel slot 47) 185–188 Color Macro 47 (wheel slot 48) 189–192 Color Macro 48 (wheel slot 49) 193–196 Color Macro 49 (wheel slot 50) 197–200 Color Macro 50 (wheel slot 51) 201–204 Color Macro 51 (wheel slot 52) 205–208 Color Macro 52 (wheel slot 53) 209–212 Color Macro 53 (wheel slot 54) 213–216 Color Macro 54 (wheel slot 55) 217–220 Color Macro 55 (wheel slot 56) 221–224 Color Macro 56 (wheel slot 57) 225–228 Color Macro 57 (wheel slot 58) 229–232 Color Macro 58 (wheel slot 59) 233–236 Color Macro 59 (wheel slot 60) 237–240 Color Macro 60 (wheel slot 61) 241–244 Color Macro 61 (wheel slot 62) 245–248 Color Macro 62 (wheel slot 63) 249–252 Color Macro 63 (wheel slot 64)

60ch (continued)

Ch	Function	Default	DMX values
44	Red	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
45	Green	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
46	Blue	0	0–62 0 % Background 63–126 25 % Background 127–190 50 % Background 191–254 75 % Background 255–255 100 % Background
47	Color3	0	
48	C TO	0	0–0 Off 1–255 2300K to 9900K

60ch (continued)

Ch	Function	Default	DMX values
49	Color Wheel 2	0	0–22 No Function (wheel slot 1) 23–23 2300K (wheel slot 2) 24–24 2400K (wheel slot 3) 25–25 2500K (wheel slot 4) 26–26 2600K (wheel slot 5) 27–27 2700K (wheel slot 6) 28–28 2800K (wheel slot 7) 29–29 2900K (wheel slot 8) 30–30 3000K (wheel slot 9) 31–31 3100K (wheel slot 10) 32–32 3200K (wheel slot 11) 33–33 3300K (wheel slot 12) 34–34 3400K (wheel slot 13) 35–35 3500K (wheel slot 14) 36–36 3600K (wheel slot 15) 37–37 3700K (wheel slot 16) 38–38 3800K (wheel slot 17) 39–39 3900K (wheel slot 18) 40–40 4000K (wheel slot 19) 41–41 4100K (wheel slot 20) 42–42 4200K (wheel slot 21) 43–43 4300K (wheel slot 22) 44–44 4400K (wheel slot 23) 45–45 4500K (wheel slot 24) 46–46 4600K (wheel slot 25) 47–47 4700K (wheel slot 26) 48–48 4800K (wheel slot 27) 49–49 4900K (wheel slot 28) 50–50 5000K (wheel slot 29) 51–51 5100K (wheel slot 30) 52–52 5200K (wheel slot 31) 53–53 5300K (wheel slot 32) 54–54 5400K (wheel slot 33) 55–55 5500K (wheel slot 34) 56–56 5600K (wheel slot 35) 57–57 5700K (wheel slot 36) 58–58 5800K (wheel slot 37) 59–59 5900K (wheel slot 38) 60–60 6000K (wheel slot 39) 61–61 6100K (wheel slot 40) 62–62 6200K (wheel slot 41) 63–63 6300K (wheel slot 42) 64–64 6400K (wheel slot 43) 65–65 6500K (wheel slot 44) 66–66 6600K (wheel slot 45) 67–67 6700K (wheel slot 46) 68–68 6800K (wheel slot 47) 69–69 6900K (wheel slot 48) 70–70 7000K (wheel slot 49) 71–71 7100K (wheel slot 50) 72–72 7200K (wheel slot 51) 73–73 7300K (wheel slot 52) 74–74 7400K (wheel slot 53) 75–75 7500K (wheel slot 54) 76–76 7600K (wheel slot 55) 77–77 7700K (wheel slot 56) 78–78 7800K (wheel slot 57) 79–79 7900K (wheel slot 58) 80–80 8000K (wheel slot 59) 81–81 8100K (wheel slot 60) 82–82 8200K (wheel slot 61) 83–83 8300K (wheel slot 62) 84–84 8400K (wheel slot 63) 85–85 8500K (wheel slot 64)

60ch (continued)

Ch	Function	Default	DMX values
50	Shutter / Strobe	32	0–31 LEDs Off 32–63 LEDs ON 64–95 Strobe Slow to Fast 96–127 LEDs ON 128–159 Pulse Slow to Fast 160–191 Shutter Open 192–223 Rnd Strobe Slow to Fast 224–255 LEDs ON
51	Dimmer	0	0–62 0 percent 63–126 25 percent 127–190 50 percent 191–254 75 percent 255–255 100 percent
52	Dimmer Fine	0	Fine byte of Dimmer
53	Effect	0	0–10 Off 11–26 Auto Program 1 27–43 Auto Program 2 44–60 Auto Program 3 61–76 Auto Program 4 77–93 Auto Program 5 94–110 Auto Program 6 111–126 Auto Program 7 127–143 Auto Program 8 144–160 Auto Program 9 161–176 Auto Program 10 177–193 Auto Program 11 194–210 Auto Program 12 211–226 Auto Program 13 227–255 No Function
54	Effect Speed	0	
55	Effects1Fade	0	
56	Effect	0	0–10 Off Background 11–26 Auto Program 1 Background 27–43 Auto Program 2 Background 44–60 Auto Program 3 Background 61–76 Auto Program 4 Background 77–93 Auto Program 5 Background 94–110 Auto Program 6 Background 111–126 Auto Program 7 Background 127–143 Auto Program 8 Background 144–160 Auto Program 9 Background 161–176 Auto Program 10 Background 177–193 Auto Program 11 Background 194–210 Auto Program 12 Background 211–226 Auto Program 13 Background 227–255 No Function Background
57	Effect Speed	0	
58	Effects1Fade	0	

60ch (continued)

Ch	Function	Default	DMX values
59	Dimmer Mode	0	0–20 Default to Unit Setting 21–40 Standard 41–60 Stage 61–80 TV 81–100 Architectural 101–120 Theater 121–140 Stage 2 141–141 0*1 second 142–142 0*2 seconds 143–143 0*3 seconds 144–144 0*4 seconds 145–145 0*5 seconds 146–146 0*6 seconds 147–147 0*7 seconds 148–148 0*8 seconds 149–149 0*9 seconds 150–150 1 second 151–151 1*5 seconds 152–152 2 seconds 153–153 3 seconds 154–154 4 seconds 155–155 5 seconds 156–156 6 seconds 157–157 7 seconds 158–158 8 seconds 159–159 9 seconds 160–160 10 seconds 161–255 Default to Unit Setting
60	Dimmer Curve	0	0–20 Square 21–40 Linear 41–60 Inverted Square 61–80 S Curve 81–255 No function