BeamZ

KUBE20WH



Manufacturer	**BeamZ**
Type	**Effect light**
DMX modes	**5**
DMX footprint	**2, 6, 8, 11 channels**
Beam angle	**25°**
Size (W × H × D)	**42 × 1035 × 42 mm**
GDTF fixture type	**A6E0C0DF-4948-40FB-89A0-B7…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Effect speed · Strobe · Dimmer

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

2 channels	2 ch
6 channels	6 ch
6 channels 1	6 ch
8 channels 1	8 ch
11 channels 1	11 ch

2 channels

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Color Consistency	0	0–10 Off light 11–20 2000K 21–30 2200K 31–40 2400K 41–50 2600K 51–60 2800K 61–70 3200K 71–80 3600K 81–90 4000K 91–100 4400K 101–110 4800K 111–120 5200K 121–130 5600K 131–140 6000K 141–150 6400K 151–160 6800K 161–170 7200K 171–180 7600K 181–190 8000K 191–200 8400K 201–210 8800K 211–220 9200K 221–230 9600K 231–240 10000K 241–255 No function

6 channels

6 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	0–10 No function 11–255 Slow to fast
3	Blue	0	
4	White	0	
5	Color Add RY	0	
6	UV	0	

6 channels 1

6 channels

Ch	Function	Default	DMX values
1	Color RGBRed	0	
2	Color RGBGreen	0	
3	Color RGBBlue	0	
4	White	0	
5	Color Add RY	0	
6	UV	0	

8 channels 1

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	

8 channels 1 (continued)

Ch	Function	Default	DMX values
2	Shutter / Strobe	0	0–9 Off 10–255 Strobe
3	Color RGBRed	0	
4	Color RGBGreen	0	
5	Color RGBBlue	0	
6	White	0	
7	Color Add RY	0	
8	UV	0	

11 channels 1

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Color RGBRed	0	
3	Color RGBGreen	0	
4	Color RGBBlue	0	
5	White	0	
6	Color Add RY	0	
7	UV	0	
8	Shutter / Strobe	0	0–9 Off 10–255 Strobe
9	Color Consistency	0	0–10 Off light 11–20 2000K 21–30 2200K 31–40 2400K 41–50 2600K 51–60 2800K 61–70 3200K 71–80 3600K 81–90 4000K 91–100 4400K 101–110 4800K 111–120 5200K 121–130 5600K 131–140 6000K 141–150 6400K 151–160 6800K 161–170 7200K 171–180 7600K 181–190 8000K 191–200 8400K 201–210 8800K 211–220 9200K 221–230 9600K 231–240 10000K 241–255 No function
10	Effect	0	0–9 Off light 10–50 Static color mixing 51–100 Jump mode 101–150 Gardient mode 151–200 Mutation pattern 201–215 Color changing voice control 216–245 Color strobe voice control 246–255 Breathing voice control
11	Effect Speed	0	