BETOPPER

# LC500 COB



| | |
|---|---|
| Manufacturer | **BETOPPER** |
| Type | **Blinder** |
| DMX modes | **2** |
| DMX footprint | **12 channels** |
| Beam angle | **25°** |
| Size (W × H × D) | **196 × 352 × 371 mm** |
| GDTF fixture type | **331159AA-3368-46A3-A4FE-5A…** |

## Controls

Extra LED colours · Dimmer

## DMX modes

| | |
|---|---|
| 12 Chan D001 | 12 ch |
| 12 Channel A001 | 12 ch |

## 12 Chan D001

12 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Dimmer | 0 | |
| 2 | Strobe Mode Strobe | 0 | |
| 3 | Function | 0 | 0–50 Dimming Mode<br>51–100 Color Selection<br>101–150 Jump<br>151–200 Gradient<br>201–249 Pulse Change<br>250–255 Voice Control |
| 4 | Function Speed | 0 | |
| 5 | White | 0 | |
| 6 | Color Add RY | 0 | |
| 7 | White | 0 | |
| 8 | Color Add RY | 0 | |
| 9 | White | 0 | |
| 10 | Color Add RY | 0 | |
| 11 | White | 0 | |
| 12 | Color Add RY | 0 | |

## 12 Channel A001

12 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Dimmer | 0 | |
| 2 | White | 0 | |
| 3 | Color Add RY | 0 | |
| 4 | White | 0 | |
| 5 | Color Add RY | 0 | |
| 6 | White | 0 | |
| 7 | Color Add RY | 0 | |
| 8 | White | 0 | |
| 9 | Color Add RY | 0 | |
| 10 | Strobe Mode Strobe | 0 | |
| 11 | Function | 0 | 0–50 Dimming Mode<br>51–100 Color Selection<br>101–150 Jump<br>151–200 Gradient<br>201–249 Pulse Change<br>250–255 Voice Control |
| 12 | Function Speed | 0 | |