Chauvet Professional

Strike V



Manufacturer	**Chauvet Professional**
Type	**Blinder**
DMX modes	**16**
DMX footprint	**29, 30, 72, 96, 120, 144, 192, 222, 240, 288, 314 channels**
Beam angle	**10.4-25°**
Tilt range	**180°**
Heads / cells	**48**
Size (W × H × D)	**407 × 258 × 146 mm**
GDTF fixture type	**9B2DFC2E-BFA6-46E9-B80C-B9…**

Controls

Frost · Colour temperature · Colour wheel · Strobe · Dimmer · Pixel control · Pan and tilt · Movement speed

Safety-relevant functions

Fixture reset · Service functions

DMX modes

Single Mode 29Ch (Basic)	29 ch
Dual-Mov 30Ch (Adv)	30 ch
Cell-Pix 72Ch (RGB-STD)	72 ch
Dot-Pix 72Ch (RGB-STD)	72 ch
Cell-Pix 96Ch (Std)	96 ch
Dot-Pix 96Ch (Std)	96 ch
Cell-Pix 120Ch (RGB-Adv)	120 ch
Dot-Pix 120Ch (RGB-Adv)	120 ch
Cell-Pix 144Ch (Adv)	144 ch
Dot-Pix 144Ch (Adv)	144 ch
Dual- Pix 144Ch (RGB-Std)	144 ch
Dual-Pix 192Ch (Std)	192 ch
Single Mode 222Ch (Standard)	222 ch
Dual -Pix 240Ch (RGB-Adv)	240 ch
Dual Pix 288Ch (Adv)	288 ch
Single Mode 314Ch (Advanced)	314 ch

Single Mode 29Ch (Basic)

29 channels

Ch	Function	Default	DMX values
1	Tilt	127	0–126 Min 127–127 Home 128–254 Home > Max 255–255 Max
2	Tilt Fine	255	Fine byte of Tilt
3	Frost1	0	0–0 Min 1–254 Min > Max 255–255 Max
4	Dimmer	0	
5	Dimmer Fine	0	Fine byte of Dimmer
6	Dimmer	0	
7	Dimmer Fine	0	Fine byte of Dimmer
8	Shutter1Strobe	0	0–9 Disables Duration Control 10–250 7ms - 650ms 251–255 On
9	Shutter / Strobe	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
10	Shutter2Strobe	0	0–9 Disables Duration Control 10–250 7ms - 650ms 251–255 On
11	Shutter / Strobe 2	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
12	Shutter1Strobe Effect	0	0–5 No Effect 6–42 Ramp Up 43–85 Ramp Down 86–128 Ramp Up-Down 129–171 Random 172–214 Lightning 215–255 Spikes
13	Shutter2Strobe Effect	0	0–5 No Effect 6–42 Ramp Up 43–85 Ramp Down 86–128 Ramp Up-Down 129–171 Random 172–214 Lightning 215–255 Spikes

Single Mode 29Ch (Basic) (continued)

Ch	Function	Default	DMX values
14	C TC	0	0–5 No Function 6–13 2800K-2900K 14–20 2900K-3000K 21–27 3000K-3100K 28–34 3100K-3200K 35–41 3200K-3300K 42–48 3300K-3400K 49–55 3400K-3500K 56–62 3500K-3600K 63–69 3600K-3700K 70–76 3700K-3800K 77–83 3800K-3900K 84–90 3900K-4000K 91–97 4000K-4100K 98–104 4100K-4200K 105–111 4200K-4300K 112–118 4300K-4400K 119–125 4400K-4500K 126–132 4500K-4600K 133–139 4600K-4700K 140–146 4700K-4800K 147–153 4800K-4900K 154–160 4900K-5000K 161–167 5000K-5100K 168–174 5100K-5200K 175–181 5200-5300K 182–188 5300K-5400K 189–195 5400K-5500K 196–202 5500K-5600K 203–209 5600K-5700K 210–216 5700K-6000K 217–223 6000K-6500K 224–230 6500K-7000K 231–237 7000-7500K 238–244 7500K-8000K 245–255 8000K
15	Color Macro1	0	
16	Color Macro1Rate	0	0–5 No Function 6–124 Left > Right S > F 125–130 No Function 131–249 Right > Left S > F 250–255 No Function
17	Color Macro2	0	0–2 Snap 3–255 Fade: Short To Long
18	Color Macro3	0	
19	Color Macro3Rate	0	0–5 No Function 6–124 Left > Right S > F 125–130 No Function 131–249 Right > Left S > F 250–255 No Function
20	Color Macro4	0	0–2 Snap 3–255 Fade: Short To Long

Single Mode 29Ch (Basic) (continued)

Ch	Function	Default	DMX values
21	Control1	0	0–5 No Function - #1 6–10 Off 11–15 Dimmer Mode 1 16–20 Dimmer Mode 2 21–25 Dimmer Mode 3 26–30 1000Hz 31–35 2000Hz 36–40 4000Hz 41–45 6000Hz 46–50 25KHz 51–55 64KHz 56–60 Auto Fan Mode 61–65 On Fan Mode 66–70 Silent Fan Mode 71–75 Linear Dimmer Curve 76–80 Square Dimmer Curve 81–85 Inverse Square Dimmer Curve 86–90 S-Curve Dimmer Curve 91–95 No Function - #2 96–100 Dot - Invert Off 101–105 Dot - Invert On 106–110 Cell - Invert Off 111–115 Cell - Invert On 116–120 Tilt Speed 121–125 Tilt Speed Normal 126–130 DMX Loss - Hold Last 131–135 DMX Loss - Blackout 136–140 - No Function - 141–145 Fixture Reset 146–150 Color Calibration Off 151–155 Color Calibration User 156–160 Color Calibration Factory 161–243 Reserved - #3 244–249 Dimmer Mode Override 250–255 No Function - #4
22	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
23	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
24	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
25	White	255	0–0 Min 1–254 Min > Max 255–255 Max
26	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
27	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
28	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
29	White	255	0–0 Min 1–254 Min > Max 255–255 Max

Dual-Mov 30Ch (Adv)

30 channels

Ch	Function	Default	DMX values
1	Tilt	127	0–126 Min 127–127 Home 128–254 Home > Max 255–255 Max
2	Tilt Fine	255	Fine byte of Tilt
3	Position MSpeed	0	0–0 Min 1–254 Min > Max 255–255 Max
4	Frost1	0	0–0 Min 1–254 Min > Max 255–255 Max
5	Dimmer	0	
6	Dimmer Fine	0	Fine byte of Dimmer
7	Dimmer	0	
8	Dimmer Fine	0	Fine byte of Dimmer
9	Shutter1Strobe	0	0–9 Disables Duration Control 10–250 7ms - 650ms 251–255 On
10	Shutter / Strobe	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
11	Shutter2Strobe	0	0–9 Disables Duration Control 10–250 7ms - 650ms 251–255 On
12	Shutter / Strobe 2	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
13	Shutter1Strobe Effect	0	0–5 No Effect 6–42 Ramp Up 43–85 Ramp Down 86–128 Ramp Up-Down 129–171 Random 172–214 Lightning 215–255 Spikes
14	Shutter2Strobe Effect	0	0–5 No Effect 6–42 Ramp Up 43–85 Ramp Down 86–128 Ramp Up-Down 129–171 Random 172–214 Lightning 215–255 Spikes

Dual-Mov 30Ch (Adv) (continued)

Ch	Function	Default	DMX values
15	C TC	0	0–5 No Function 6–13 2800K-2900K 14–20 2900K-3000K 21–27 3000K-3100K 28–34 3100K-3200K 35–41 3200K-3300K 42–48 3300K-3400K 49–55 3400K-3500K 56–62 3500K-3600K 63–69 3600K-3700K 70–76 3700K-3800K 77–83 3800K-3900K 84–90 3900K-4000K 91–97 4000K-4100K 98–104 4100K-4200K 105–111 4200K-4300K 112–118 4300K-4400K 119–125 4400K-4500K 126–132 4500K-4600K 133–139 4600K-4700K 140–146 4700K-4800K 147–153 4800K-4900K 154–160 4900K-5000K 161–167 5000K-5100K 168–174 5100K-5200K 175–181 5200-5300K 182–188 5300K-5400K 189–195 5400K-5500K 196–202 5500K-5600K 203–209 5600K-5700K 210–216 5700K-6000K 217–223 6000K-6500K 224–230 6500K-7000K 231–237 7000-7500K 238–244 7500K-8000K 245–255 8000K
16	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
17	Color Macro1	0	0–0 No Function 1–2 White 2700K (wheel slot 1) 3–4 White 3200K (wheel slot 2) 5–6 White 4200K (wheel slot 3) 7–8 White 5600K (wheel slot 4) 9–10 White 8000K (wheel slot 5) 11–11 Blue (wheel slot 6) 12–48 Green+/Blue (wheel slot 7) 49–49 Cyan (wheel slot 8) 50–86 Green/Blue- (wheel slot 9) 87–87 Green (wheel slot 10) 88–124 Red+/Green (wheel slot 11) 125–125 Yellow (wheel slot 12) 126–162 Red/Green- (wheel slot 13) 163–163 Red (wheel slot 14) 164–200 Red/Blue+ (wheel slot 15) 201–201 Magenta (wheel slot 16) 202–238 Red-/Blue (wheel slot 17) 239–239 Blue (wheel slot 6) 240–247 Color Change F > S 248–255 Color Jump F > S

Dual-Mov 30Ch (Adv) (continued)

Ch	Function	Default	DMX values
18	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
19	Color Macro2	0	0–0 No Function 1–2 White 2700K (wheel slot 1) 3–4 White 3200K (wheel slot 2) 5–6 White 4200K (wheel slot 3) 7–8 White 5600K (wheel slot 4) 9–10 White 8000K (wheel slot 5) 11–11 Blue (wheel slot 6) 12–48 Green+/Blue (wheel slot 7) 49–49 Cyan (wheel slot 8) 50–86 Green/Blue- (wheel slot 9) 87–87 Green (wheel slot 10) 88–124 Red+/Green (wheel slot 11) 125–125 Yellow (wheel slot 12) 126–162 Red/Green- (wheel slot 13) 163–163 Red (wheel slot 14) 164–200 Red/Blue+ (wheel slot 15) 201–201 Magenta (wheel slot 16) 202–238 Red-/Blue (wheel slot 17) 239–239 Blue (wheel slot 6) 240–247 Color Change F > S 248–255 Color Jump F > S
20	Color Macro3	0	
21	Color Macro3Rate	0	0–5 No Function 6–124 Left > Right S > F 125–130 No Function 131–249 Right > Left S > F 250–255 No Function
22	Color Macro4	0	0–2 Snap 3–255 Fade: Short To Long
23	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
24	Color Macro5	0	0–0 No Function 1–2 White 2700K (wheel slot 1) 3–4 White 3200K (wheel slot 2) 5–6 White 4200K (wheel slot 3) 7–8 White 5600K (wheel slot 4) 9–10 White 8000K (wheel slot 5) 11–11 Blue (wheel slot 6) 12–48 Green+/Blue (wheel slot 7) 49–49 Cyan (wheel slot 8) 50–86 Green/Blue- (wheel slot 9) 87–87 Green (wheel slot 10) 88–124 Red+/Green (wheel slot 11) 125–125 Yellow (wheel slot 12) 126–162 Red/Green- (wheel slot 13) 163–163 Red (wheel slot 14) 164–200 Red/Blue+ (wheel slot 15) 201–201 Magenta (wheel slot 16) 202–238 Red-/Blue (wheel slot 17) 239–239 Blue (wheel slot 6) 240–247 Color Change F > S 248–255 Color Jump F > S
25	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max

Dual-Mov 30Ch (Adv) (continued)

Ch	Function	Default	DMX values
26	Color Macro6	0	0–0 No Function 1–2 White 2700K (wheel slot 1) 3–4 White 3200K (wheel slot 2) 5–6 White 4200K (wheel slot 3) 7–8 White 5600K (wheel slot 4) 9–10 White 8000K (wheel slot 5) 11–11 Blue (wheel slot 6) 12–48 Green+/Blue (wheel slot 7) 49–49 Cyan (wheel slot 8) 50–86 Green/Blue- (wheel slot 9) 87–87 Green (wheel slot 10) 88–124 Red+/Green (wheel slot 11) 125–125 Yellow (wheel slot 12) 126–162 Red/Green- (wheel slot 13) 163–163 Red (wheel slot 14) 164–200 Red/Blue+ (wheel slot 15) 201–201 Magenta (wheel slot 16) 202–238 Red-/Blue (wheel slot 17) 239–239 Blue (wheel slot 6) 240–247 Color Change F > S 248–255 Color Jump F > S
27	Color Macro7	0	
28	Color Macro7Rate	0	0–5 No Function 6–124 Left > Right S > F 125–130 No Function 131–249 Right > Left S > F 250–255 No Function
29	Color Macro8	0	0–2 Snap 3–255 Fade: Short To Long

Dual-Mov 30Ch (Adv) (continued)

Ch	Function	Default	DMX values
30	Control1	0	0–5 No Function - #1 6–10 Off 11–15 Dimmer Mode 1 16–20 Dimmer Mode 2 21–25 Dimmer Mode 3 26–30 1000Hz 31–35 2000Hz 36–40 4000Hz 41–45 6000Hz 46–50 25KHz 51–55 64KHz 56–60 Auto Fan Mode 61–65 On Fan Mode 66–70 Silent Fan Mode 71–75 Linear Dimmer Curve 76–80 Square Dimmer Curve 81–85 Inverse Square Dimmer Curve 86–90 S-Curve Dimmer Curve 91–95 No Function - #2 96–100 Dot - Invert Off 101–105 Dot - Invert On 106–110 Cell - Invert Off 111–115 Cell - Invert On 116–120 Tilt Speed 121–125 Tilt Speed Normal 126–130 DMX Loss - Hold Last 131–135 DMX Loss - Blackout 136–140 - No Function - 141–145 Fixture Reset 146–150 Color Calibration Off 151–155 Color Calibration User 156–160 Color Calibration Factory 161–243 Reserved - #3 244–249 Dimmer Mode Override 250–255 No Function - #4

Cell-Pix 72Ch (RGB-STD)

72 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Red	255	
5	Green	255	
6	Blue	255	
7	Red	255	
8	Green	255	
9	Blue	255	
10	Red	255	
11	Green	255	
12	Blue	255	
13	Red	255	
14	Green	255	
15	Blue	255	
16	Red	255	

Cell-Pix 72Ch (RGB-STD) (continued)

Ch	Function	Default	DMX values
17	Green	255	
18	Blue	255	
19	Red	255	
20	Green	255	
21	Blue	255	
22	Red	255	
23	Green	255	
24	Blue	255	
25	Red	255	
26	Green	255	
27	Blue	255	
28	Red	255	
29	Green	255	
30	Blue	255	
31	Red	255	
32	Green	255	
33	Blue	255	
34	Red	255	
35	Green	255	
36	Blue	255	
37	Red	255	
38	Green	255	
39	Blue	255	
40	Red	255	
41	Green	255	
42	Blue	255	
43	Red	255	
44	Green	255	
45	Blue	255	
46	Red	255	
47	Green	255	
48	Blue	255	
49	Red	255	
50	Green	255	
51	Blue	255	
52	Red	255	
53	Green	255	
54	Blue	255	
55	Red	255	
56	Green	255	
57	Blue	255	
58	Red	255	
59	Green	255	
60	Blue	255	
61	Red	255	

Cell-Pix 72Ch (RGB-STD) (continued)

Ch	Function	Default	DMX values
62	Green	255	
63	Blue	255	
64	Red	255	
65	Green	255	
66	Blue	255	
67	Red	255	
68	Green	255	
69	Blue	255	
70	Red	255	
71	Green	255	
72	Blue	255	

Dot-Pix 72Ch (RGB-STD)

72 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Red	255	
5	Green	255	
6	Blue	255	
7	Red	255	
8	Green	255	
9	Blue	255	
10	Red	255	
11	Green	255	
12	Blue	255	
13	Red	255	
14	Green	255	
15	Blue	255	
16	Red	255	
17	Green	255	
18	Blue	255	
19	Red	255	
20	Green	255	
21	Blue	255	
22	Red	255	
23	Green	255	
24	Blue	255	
25	Red	255	
26	Green	255	
27	Blue	255	
28	Red	255	
29	Green	255	
30	Blue	255	

Dot-Pix 72Ch (RGB-STD) (continued)

Ch	Function	Default	DMX values
31	Red	255	
32	Green	255	
33	Blue	255	
34	Red	255	
35	Green	255	
36	Blue	255	
37	Red	255	
38	Green	255	
39	Blue	255	
40	Red	255	
41	Green	255	
42	Blue	255	
43	Red	255	
44	Green	255	
45	Blue	255	
46	Red	255	
47	Green	255	
48	Blue	255	
49	Red	255	
50	Green	255	
51	Blue	255	
52	Red	255	
53	Green	255	
54	Blue	255	
55	Red	255	
56	Green	255	
57	Blue	255	
58	Red	255	
59	Green	255	
60	Blue	255	
61	Red	255	
62	Green	255	
63	Blue	255	
64	Red	255	
65	Green	255	
66	Blue	255	
67	Red	255	
68	Green	255	
69	Blue	255	
70	Red	255	
71	Green	255	
72	Blue	255	

Cell-Pix 96Ch (Std)

96 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	255	
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	255	
13	Red	255	
14	Green	255	
15	Blue	255	
16	White	255	
17	Red	255	
18	Green	255	
19	Blue	255	
20	White	255	
21	Red	255	
22	Green	255	
23	Blue	255	
24	White	255	
25	Red	255	
26	Green	255	
27	Blue	255	
28	White	255	
29	Red	255	
30	Green	255	
31	Blue	255	
32	White	255	
33	Red	255	
34	Green	255	
35	Blue	255	
36	White	255	
37	Red	255	
38	Green	255	
39	Blue	255	
40	White	255	
41	Red	255	
42	Green	255	
43	Blue	255	
44	White	255	
45	Red	255	

Cell-Pix 96Ch (Std) (continued)

Ch	Function	Default	DMX values
46	Green	255	
47	Blue	255	
48	White	255	
49	Red	255	
50	Green	255	
51	Blue	255	
52	White	255	
53	Red	255	
54	Green	255	
55	Blue	255	
56	White	255	
57	Red	255	
58	Green	255	
59	Blue	255	
60	White	255	
61	Red	255	
62	Green	255	
63	Blue	255	
64	White	255	
65	Red	255	
66	Green	255	
67	Blue	255	
68	White	255	
69	Red	255	
70	Green	255	
71	Blue	255	
72	White	255	
73	Red	255	
74	Green	255	
75	Blue	255	
76	White	255	
77	Red	255	
78	Green	255	
79	Blue	255	
80	White	255	
81	Red	255	
82	Green	255	
83	Blue	255	
84	White	255	
85	Red	255	
86	Green	255	
87	Blue	255	
88	White	255	
89	Red	255	
90	Green	255	

Cell-Pix 96Ch (Std) (continued)

Ch	Function	Default	DMX values
91	Blue	255	
92	White	255	
93	Red	255	
94	Green	255	
95	Blue	255	
96	White	255	

Dot-Pix 96Ch (Std)

96 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	255	
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	255	
13	Red	255	
14	Green	255	
15	Blue	255	
16	White	255	
17	Red	255	
18	Green	255	
19	Blue	255	
20	White	255	
21	Red	255	
22	Green	255	
23	Blue	255	
24	White	255	
25	Red	255	
26	Green	255	
27	Blue	255	
28	White	255	
29	Red	255	
30	Green	255	
31	Blue	255	
32	White	255	
33	Red	255	
34	Green	255	
35	Blue	255	

Dot-Pix 96Ch (Std) (continued)

Ch	Function	Default	DMX values
36	White	255	
37	Red	255	
38	Green	255	
39	Blue	255	
40	White	255	
41	Red	255	
42	Green	255	
43	Blue	255	
44	White	255	
45	Red	255	
46	Green	255	
47	Blue	255	
48	White	255	
49	Red	255	
50	Green	255	
51	Blue	255	
52	White	255	
53	Red	255	
54	Green	255	
55	Blue	255	
56	White	255	
57	Red	255	
58	Green	255	
59	Blue	255	
60	White	255	
61	Red	255	
62	Green	255	
63	Blue	255	
64	White	255	
65	Red	255	
66	Green	255	
67	Blue	255	
68	White	255	
69	Red	255	
70	Green	255	
71	Blue	255	
72	White	255	
73	Red	255	
74	Green	255	
75	Blue	255	
76	White	255	
77	Red	255	
78	Green	255	
79	Blue	255	
80	White	255	

Dot-Pix 96Ch (Std) (continued)

Ch	Function	Default	DMX values
81	Red	255	
82	Green	255	
83	Blue	255	
84	White	255	
85	Red	255	
86	Green	255	
87	Blue	255	
88	White	255	
89	Red	255	
90	Green	255	
91	Blue	255	
92	White	255	
93	Red	255	
94	Green	255	
95	Blue	255	
96	White	255	

Cell-Pix 120Ch (RGB-Adv)

120 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Green	255	
5	Blue	255	
6	Dimmer	0	
7	Dimmer Fine	0	Fine byte of Dimmer
8	Red	255	
9	Green	255	
10	Blue	255	
11	Dimmer	0	
12	Dimmer Fine	0	Fine byte of Dimmer
13	Red	255	
14	Green	255	
15	Blue	255	
16	Dimmer	0	
17	Dimmer Fine	0	Fine byte of Dimmer
18	Red	255	
19	Green	255	
20	Blue	255	
21	Dimmer	0	
22	Dimmer Fine	0	Fine byte of Dimmer
23	Red	255	
24	Green	255	
25	Blue	255	

Cell-Pix 120Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
26	Dimmer	0	
27	Dimmer Fine	0	Fine byte of Dimmer
28	Red	255	
29	Green	255	
30	Blue	255	
31	Dimmer	0	
32	Dimmer Fine	0	Fine byte of Dimmer
33	Red	255	
34	Green	255	
35	Blue	255	
36	Dimmer	0	
37	Dimmer Fine	0	Fine byte of Dimmer
38	Red	255	
39	Green	255	
40	Blue	255	
41	Dimmer	0	
42	Dimmer Fine	0	Fine byte of Dimmer
43	Red	255	
44	Green	255	
45	Blue	255	
46	Dimmer	0	
47	Dimmer Fine	0	Fine byte of Dimmer
48	Red	255	
49	Green	255	
50	Blue	255	
51	Dimmer	0	
52	Dimmer Fine	0	Fine byte of Dimmer
53	Red	255	
54	Green	255	
55	Blue	255	
56	Dimmer	0	
57	Dimmer Fine	0	Fine byte of Dimmer
58	Red	255	
59	Green	255	
60	Blue	255	
61	Dimmer	0	
62	Dimmer Fine	0	Fine byte of Dimmer
63	Red	255	
64	Green	255	
65	Blue	255	
66	Dimmer	0	
67	Dimmer Fine	0	Fine byte of Dimmer
68	Red	255	
69	Green	255	
70	Blue	255	

Cell-Pix 120Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
71	Dimmer	0	
72	Dimmer Fine	0	Fine byte of Dimmer
73	Red	255	
74	Green	255	
75	Blue	255	
76	Dimmer	0	
77	Dimmer Fine	0	Fine byte of Dimmer
78	Red	255	
79	Green	255	
80	Blue	255	
81	Dimmer	0	
82	Dimmer Fine	0	Fine byte of Dimmer
83	Red	255	
84	Green	255	
85	Blue	255	
86	Dimmer	0	
87	Dimmer Fine	0	Fine byte of Dimmer
88	Red	255	
89	Green	255	
90	Blue	255	
91	Dimmer	0	
92	Dimmer Fine	0	Fine byte of Dimmer
93	Red	255	
94	Green	255	
95	Blue	255	
96	Dimmer	0	
97	Dimmer Fine	0	Fine byte of Dimmer
98	Red	255	
99	Green	255	
100	Blue	255	
101	Dimmer	0	
102	Dimmer Fine	0	Fine byte of Dimmer
103	Red	255	
104	Green	255	
105	Blue	255	
106	Dimmer	0	
107	Dimmer Fine	0	Fine byte of Dimmer
108	Red	255	
109	Green	255	
110	Blue	255	
111	Dimmer	0	
112	Dimmer Fine	0	Fine byte of Dimmer
113	Red	255	
114	Green	255	
115	Blue	255	

Cell-Pix 120Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
116	Dimmer	0	
117	Dimmer Fine	0	Fine byte of Dimmer
118	Red	255	
119	Green	255	
120	Blue	255	

Dot-Pix 120Ch (RGB-Adv)

120 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Green	255	
5	Blue	255	
6	Dimmer	0	
7	Dimmer Fine	0	Fine byte of Dimmer
8	Red	255	
9	Green	255	
10	Blue	255	
11	Dimmer	0	
12	Dimmer Fine	0	Fine byte of Dimmer
13	Red	255	
14	Green	255	
15	Blue	255	
16	Dimmer	0	
17	Dimmer Fine	0	Fine byte of Dimmer
18	Red	255	
19	Green	255	
20	Blue	255	
21	Dimmer	0	
22	Dimmer Fine	0	Fine byte of Dimmer
23	Red	255	
24	Green	255	
25	Blue	255	
26	Dimmer	0	
27	Dimmer Fine	0	Fine byte of Dimmer
28	Red	255	
29	Green	255	
30	Blue	255	
31	Dimmer	0	
32	Dimmer Fine	0	Fine byte of Dimmer
33	Red	255	
34	Green	255	
35	Blue	255	
36	Dimmer	0	

Dot-Pix 120Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
37	Dimmer Fine	0	Fine byte of Dimmer
38	Red	255	
39	Green	255	
40	Blue	255	
41	Dimmer	0	
42	Dimmer Fine	0	Fine byte of Dimmer
43	Red	255	
44	Green	255	
45	Blue	255	
46	Dimmer	0	
47	Dimmer Fine	0	Fine byte of Dimmer
48	Red	255	
49	Green	255	
50	Blue	255	
51	Dimmer	0	
52	Dimmer Fine	0	Fine byte of Dimmer
53	Red	255	
54	Green	255	
55	Blue	255	
56	Dimmer	0	
57	Dimmer Fine	0	Fine byte of Dimmer
58	Red	255	
59	Green	255	
60	Blue	255	
61	Dimmer	0	
62	Dimmer Fine	0	Fine byte of Dimmer
63	Red	255	
64	Green	255	
65	Blue	255	
66	Dimmer	0	
67	Dimmer Fine	0	Fine byte of Dimmer
68	Red	255	
69	Green	255	
70	Blue	255	
71	Dimmer	0	
72	Dimmer Fine	0	Fine byte of Dimmer
73	Red	255	
74	Green	255	
75	Blue	255	
76	Dimmer	0	
77	Dimmer Fine	0	Fine byte of Dimmer
78	Red	255	
79	Green	255	
80	Blue	255	
81	Dimmer	0	

Dot-Pix 120Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
82	Dimmer Fine	0	Fine byte of Dimmer
83	Red	255	
84	Green	255	
85	Blue	255	
86	Dimmer	0	
87	Dimmer Fine	0	Fine byte of Dimmer
88	Red	255	
89	Green	255	
90	Blue	255	
91	Dimmer	0	
92	Dimmer Fine	0	Fine byte of Dimmer
93	Red	255	
94	Green	255	
95	Blue	255	
96	Dimmer	0	
97	Dimmer Fine	0	Fine byte of Dimmer
98	Red	255	
99	Green	255	
100	Blue	255	
101	Dimmer	0	
102	Dimmer Fine	0	Fine byte of Dimmer
103	Red	255	
104	Green	255	
105	Blue	255	
106	Dimmer	0	
107	Dimmer Fine	0	Fine byte of Dimmer
108	Red	255	
109	Green	255	
110	Blue	255	
111	Dimmer	0	
112	Dimmer Fine	0	Fine byte of Dimmer
113	Red	255	
114	Green	255	
115	Blue	255	
116	Dimmer	0	
117	Dimmer Fine	0	Fine byte of Dimmer
118	Red	255	
119	Green	255	
120	Blue	255	

Cell-Pix 144Ch (Adv)

144 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer

Cell-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
3	Red	255	
4	Green	255	
5	Blue	255	
6	White	255	
7	Dimmer	0	
8	Dimmer Fine	0	Fine byte of Dimmer
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	255	
13	Dimmer	0	
14	Dimmer Fine	0	Fine byte of Dimmer
15	Red	255	
16	Green	255	
17	Blue	255	
18	White	255	
19	Dimmer	0	
20	Dimmer Fine	0	Fine byte of Dimmer
21	Red	255	
22	Green	255	
23	Blue	255	
24	White	255	
25	Dimmer	0	
26	Dimmer Fine	0	Fine byte of Dimmer
27	Red	255	
28	Green	255	
29	Blue	255	
30	White	255	
31	Dimmer	0	
32	Dimmer Fine	0	Fine byte of Dimmer
33	Red	255	
34	Green	255	
35	Blue	255	
36	White	255	
37	Dimmer	0	
38	Dimmer Fine	0	Fine byte of Dimmer
39	Red	255	
40	Green	255	
41	Blue	255	
42	White	255	
43	Dimmer	0	
44	Dimmer Fine	0	Fine byte of Dimmer
45	Red	255	
46	Green	255	
47	Blue	255	

Cell-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
48	White	255	
49	Dimmer	0	
50	Dimmer Fine	0	Fine byte of Dimmer
51	Red	255	
52	Green	255	
53	Blue	255	
54	White	255	
55	Dimmer	0	
56	Dimmer Fine	0	Fine byte of Dimmer
57	Red	255	
58	Green	255	
59	Blue	255	
60	White	255	
61	Dimmer	0	
62	Dimmer Fine	0	Fine byte of Dimmer
63	Red	255	
64	Green	255	
65	Blue	255	
66	White	255	
67	Dimmer	0	
68	Dimmer Fine	0	Fine byte of Dimmer
69	Red	255	
70	Green	255	
71	Blue	255	
72	White	255	
73	Dimmer	0	
74	Dimmer Fine	0	Fine byte of Dimmer
75	Red	255	
76	Green	255	
77	Blue	255	
78	White	255	
79	Dimmer	0	
80	Dimmer Fine	0	Fine byte of Dimmer
81	Red	255	
82	Green	255	
83	Blue	255	
84	White	255	
85	Dimmer	0	
86	Dimmer Fine	0	Fine byte of Dimmer
87	Red	255	
88	Green	255	
89	Blue	255	
90	White	255	
91	Dimmer	0	
92	Dimmer Fine	0	Fine byte of Dimmer

Cell-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
93	Red	255	
94	Green	255	
95	Blue	255	
96	White	255	
97	Dimmer	0	
98	Dimmer Fine	0	Fine byte of Dimmer
99	Red	255	
100	Green	255	
101	Blue	255	
102	White	255	
103	Dimmer	0	
104	Dimmer Fine	0	Fine byte of Dimmer
105	Red	255	
106	Green	255	
107	Blue	255	
108	White	255	
109	Dimmer	0	
110	Dimmer Fine	0	Fine byte of Dimmer
111	Red	255	
112	Green	255	
113	Blue	255	
114	White	255	
115	Dimmer	0	
116	Dimmer Fine	0	Fine byte of Dimmer
117	Red	255	
118	Green	255	
119	Blue	255	
120	White	255	
121	Dimmer	0	
122	Dimmer Fine	0	Fine byte of Dimmer
123	Red	255	
124	Green	255	
125	Blue	255	
126	White	255	
127	Dimmer	0	
128	Dimmer Fine	0	Fine byte of Dimmer
129	Red	255	
130	Green	255	
131	Blue	255	
132	White	255	
133	Dimmer	0	
134	Dimmer Fine	0	Fine byte of Dimmer
135	Red	255	
136	Green	255	
137	Blue	255	

Cell-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
138	White	255	
139	Dimmer	0	
140	Dimmer Fine	0	Fine byte of Dimmer
141	Red	255	
142	Green	255	
143	Blue	255	
144	White	255	

Dot-Pix 144Ch (Adv)

144 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Green	255	
5	Blue	255	
6	White	255	
7	Dimmer	0	
8	Dimmer Fine	0	Fine byte of Dimmer
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	255	
13	Dimmer	0	
14	Dimmer Fine	0	Fine byte of Dimmer
15	Red	255	
16	Green	255	
17	Blue	255	
18	White	255	
19	Dimmer	0	
20	Dimmer Fine	0	Fine byte of Dimmer
21	Red	255	
22	Green	255	
23	Blue	255	
24	White	255	
25	Dimmer	0	
26	Dimmer Fine	0	Fine byte of Dimmer
27	Red	255	
28	Green	255	
29	Blue	255	
30	White	255	
31	Dimmer	0	
32	Dimmer Fine	0	Fine byte of Dimmer
33	Red	255	
34	Green	255	

Dot-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
35	Blue	255	
36	White	255	
37	Dimmer	0	
38	Dimmer Fine	0	Fine byte of Dimmer
39	Red	255	
40	Green	255	
41	Blue	255	
42	White	255	
43	Dimmer	0	
44	Dimmer Fine	0	Fine byte of Dimmer
45	Red	255	
46	Green	255	
47	Blue	255	
48	White	255	
49	Dimmer	0	
50	Dimmer Fine	0	Fine byte of Dimmer
51	Red	255	
52	Green	255	
53	Blue	255	
54	White	255	
55	Dimmer	0	
56	Dimmer Fine	0	Fine byte of Dimmer
57	Red	255	
58	Green	255	
59	Blue	255	
60	White	255	
61	Dimmer	0	
62	Dimmer Fine	0	Fine byte of Dimmer
63	Red	255	
64	Green	255	
65	Blue	255	
66	White	255	
67	Dimmer	0	
68	Dimmer Fine	0	Fine byte of Dimmer
69	Red	255	
70	Green	255	
71	Blue	255	
72	White	255	
73	Dimmer	0	
74	Dimmer Fine	0	Fine byte of Dimmer
75	Red	255	
76	Green	255	
77	Blue	255	
78	White	255	
79	Dimmer	0	

Dot-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
80	Dimmer Fine	0	Fine byte of Dimmer
81	Red	255	
82	Green	255	
83	Blue	255	
84	White	255	
85	Dimmer	0	
86	Dimmer Fine	0	Fine byte of Dimmer
87	Red	255	
88	Green	255	
89	Blue	255	
90	White	255	
91	Dimmer	0	
92	Dimmer Fine	0	Fine byte of Dimmer
93	Red	255	
94	Green	255	
95	Blue	255	
96	White	255	
97	Dimmer	0	
98	Dimmer Fine	0	Fine byte of Dimmer
99	Red	255	
100	Green	255	
101	Blue	255	
102	White	255	
103	Dimmer	0	
104	Dimmer Fine	0	Fine byte of Dimmer
105	Red	255	
106	Green	255	
107	Blue	255	
108	White	255	
109	Dimmer	0	
110	Dimmer Fine	0	Fine byte of Dimmer
111	Red	255	
112	Green	255	
113	Blue	255	
114	White	255	
115	Dimmer	0	
116	Dimmer Fine	0	Fine byte of Dimmer
117	Red	255	
118	Green	255	
119	Blue	255	
120	White	255	
121	Dimmer	0	
122	Dimmer Fine	0	Fine byte of Dimmer
123	Red	255	
124	Green	255	

Dot-Pix 144Ch (Adv) (continued)

Ch	Function	Default	DMX values
125	Blue	255	
126	White	255	
127	Dimmer	0	
128	Dimmer Fine	0	Fine byte of Dimmer
129	Red	255	
130	Green	255	
131	Blue	255	
132	White	255	
133	Dimmer	0	
134	Dimmer Fine	0	Fine byte of Dimmer
135	Red	255	
136	Green	255	
137	Blue	255	
138	White	255	
139	Dimmer	0	
140	Dimmer Fine	0	Fine byte of Dimmer
141	Red	255	
142	Green	255	
143	Blue	255	
144	White	255	

Dual- Pix 144Ch (RGB-Std)

144 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Red	255	
5	Green	255	
6	Blue	255	
7	Red	255	
8	Green	255	
9	Blue	255	
10	Red	255	
11	Green	255	
12	Blue	255	
13	Red	255	
14	Green	255	
15	Blue	255	
16	Red	255	
17	Green	255	
18	Blue	255	
19	Red	255	
20	Green	255	
21	Blue	255	

Dual- Pix 144Ch (RGB-Std) (continued)

Ch	Function	Default	DMX values
22	Red	255	
23	Green	255	
24	Blue	255	
25	Red	255	
26	Green	255	
27	Blue	255	
28	Red	255	
29	Green	255	
30	Blue	255	
31	Red	255	
32	Green	255	
33	Blue	255	
34	Red	255	
35	Green	255	
36	Blue	255	
37	Red	255	
38	Green	255	
39	Blue	255	
40	Red	255	
41	Green	255	
42	Blue	255	
43	Red	255	
44	Green	255	
45	Blue	255	
46	Red	255	
47	Green	255	
48	Blue	255	
49	Red	255	
50	Green	255	
51	Blue	255	
52	Red	255	
53	Green	255	
54	Blue	255	
55	Red	255	
56	Green	255	
57	Blue	255	
58	Red	255	
59	Green	255	
60	Blue	255	
61	Red	255	
62	Green	255	
63	Blue	255	
64	Red	255	
65	Green	255	
66	Blue	255	

Dual- Pix 144Ch (RGB-Std) (continued)

Ch	Function	Default	DMX values
67	Red	255	
68	Green	255	
69	Blue	255	
70	Red	255	
71	Green	255	
72	Blue	255	
73	Red	255	
74	Green	255	
75	Blue	255	
76	Red	255	
77	Green	255	
78	Blue	255	
79	Red	255	
80	Green	255	
81	Blue	255	
82	Red	255	
83	Green	255	
84	Blue	255	
85	Red	255	
86	Green	255	
87	Blue	255	
88	Red	255	
89	Green	255	
90	Blue	255	
91	Red	255	
92	Green	255	
93	Blue	255	
94	Red	255	
95	Green	255	
96	Blue	255	
97	Red	255	
98	Green	255	
99	Blue	255	
100	Red	255	
101	Green	255	
102	Blue	255	
103	Red	255	
104	Green	255	
105	Blue	255	
106	Red	255	
107	Green	255	
108	Blue	255	
109	Red	255	
110	Green	255	
111	Blue	255	

Dual- Pix 144Ch (RGB-Std) (continued)

Ch	Function	Default	DMX values
112	Red	255	
113	Green	255	
114	Blue	255	
115	Red	255	
116	Green	255	
117	Blue	255	
118	Red	255	
119	Green	255	
120	Blue	255	
121	Red	255	
122	Green	255	
123	Blue	255	
124	Red	255	
125	Green	255	
126	Blue	255	
127	Red	255	
128	Green	255	
129	Blue	255	
130	Red	255	
131	Green	255	
132	Blue	255	
133	Red	255	
134	Green	255	
135	Blue	255	
136	Red	255	
137	Green	255	
138	Blue	255	
139	Red	255	
140	Green	255	
141	Blue	255	
142	Red	255	
143	Green	255	
144	Blue	255	

Dual-Pix 192Ch (Std)

192 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	255	

Dual-Pix 192Ch (Std) (continued)

Ch	Function	Default	DMX values
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	255	
13	Red	255	
14	Green	255	
15	Blue	255	
16	White	255	
17	Red	255	
18	Green	255	
19	Blue	255	
20	White	255	
21	Red	255	
22	Green	255	
23	Blue	255	
24	White	255	
25	Red	255	
26	Green	255	
27	Blue	255	
28	White	255	
29	Red	255	
30	Green	255	
31	Blue	255	
32	White	255	
33	Red	255	
34	Green	255	
35	Blue	255	
36	White	255	
37	Red	255	
38	Green	255	
39	Blue	255	
40	White	255	
41	Red	255	
42	Green	255	
43	Blue	255	
44	White	255	
45	Red	255	
46	Green	255	
47	Blue	255	
48	White	255	
49	Red	255	
50	Green	255	
51	Blue	255	
52	White	255	
53	Red	255	

Dual-Pix 192Ch (Std) (continued)

Ch	Function	Default	DMX values
54	Green	255	
55	Blue	255	
56	White	255	
57	Red	255	
58	Green	255	
59	Blue	255	
60	White	255	
61	Red	255	
62	Green	255	
63	Blue	255	
64	White	255	
65	Red	255	
66	Green	255	
67	Blue	255	
68	White	255	
69	Red	255	
70	Green	255	
71	Blue	255	
72	White	255	
73	Red	255	
74	Green	255	
75	Blue	255	
76	White	255	
77	Red	255	
78	Green	255	
79	Blue	255	
80	White	255	
81	Red	255	
82	Green	255	
83	Blue	255	
84	White	255	
85	Red	255	
86	Green	255	
87	Blue	255	
88	White	255	
89	Red	255	
90	Green	255	
91	Blue	255	
92	White	255	
93	Red	255	
94	Green	255	
95	Blue	255	
96	White	255	
97	Red	255	
98	Green	255	

Dual-Pix 192Ch (Std) (continued)

Ch	Function	Default	DMX values
99	Blue	255	
100	White	255	
101	Red	255	
102	Green	255	
103	Blue	255	
104	White	255	
105	Red	255	
106	Green	255	
107	Blue	255	
108	White	255	
109	Red	255	
110	Green	255	
111	Blue	255	
112	White	255	
113	Red	255	
114	Green	255	
115	Blue	255	
116	White	255	
117	Red	255	
118	Green	255	
119	Blue	255	
120	White	255	
121	Red	255	
122	Green	255	
123	Blue	255	
124	White	255	
125	Red	255	
126	Green	255	
127	Blue	255	
128	White	255	
129	Red	255	
130	Green	255	
131	Blue	255	
132	White	255	
133	Red	255	
134	Green	255	
135	Blue	255	
136	White	255	
137	Red	255	
138	Green	255	
139	Blue	255	
140	White	255	
141	Red	255	
142	Green	255	
143	Blue	255	

Dual-Pix 192Ch (Std) (continued)

Ch	Function	Default	DMX values
144	White	255	
145	Red	255	
146	Green	255	
147	Blue	255	
148	White	255	
149	Red	255	
150	Green	255	
151	Blue	255	
152	White	255	
153	Red	255	
154	Green	255	
155	Blue	255	
156	White	255	
157	Red	255	
158	Green	255	
159	Blue	255	
160	White	255	
161	Red	255	
162	Green	255	
163	Blue	255	
164	White	255	
165	Red	255	
166	Green	255	
167	Blue	255	
168	White	255	
169	Red	255	
170	Green	255	
171	Blue	255	
172	White	255	
173	Red	255	
174	Green	255	
175	Blue	255	
176	White	255	
177	Red	255	
178	Green	255	
179	Blue	255	
180	White	255	
181	Red	255	
182	Green	255	
183	Blue	255	
184	White	255	
185	Red	255	
186	Green	255	
187	Blue	255	
188	White	255	

Dual-Pix 192Ch (Std) (continued)

Ch	Function	Default	DMX values
189	Red	255	
190	Green	255	
191	Blue	255	
192	White	255	

Single Mode 222Ch (Standard)

222 channels

Ch	Function	Default	DMX values
1	Tilt	127	
2	Tilt Fine	255	Fine byte of Tilt
3	Position MSpeed	0	
4	Frost1	0	
5	Dimmer	0	
6	Dimmer Fine	0	Fine byte of Dimmer
7	Dimmer	0	
8	Dimmer Fine	0	Fine byte of Dimmer
9	Shutter1Strobe	0	
10	Shutter / Strobe	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
11	Shutter2Strobe	0	
12	Shutter / Strobe 2	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
13	Shutter1Strobe Effect	0	
14	Shutter2Strobe Effect	0	
15	C TC	0	
16	Dimmer	0	
17	Color Macro1	0	
18	Dimmer	0	
19	Color Macro2	0	
20	Color Macro3	0	
21	Color Macro3Rate	0	
22	Color Macro4	0	
23	Dimmer	0	
24	Color Macro5	0	
25	Dimmer	0	
26	Color Macro6	0	
27	Color Macro7	0	
28	Color Macro7Rate	0	
29	Color Macro8	0	
30	Control1	0	
31	Red	255	
32	Green	255	
33	Blue	255	
34	White	255	
35	Red	255	

Single Mode 222Ch (Standard) (continued)

Ch	Function	Default	DMX values
36	Green	255	
37	Blue	255	
38	White	255	
39	Red	255	
40	Green	255	
41	Blue	255	
42	White	255	
43	Red	255	
44	Green	255	
45	Blue	255	
46	White	255	
47	Red	255	
48	Green	255	
49	Blue	255	
50	White	255	
51	Red	255	
52	Green	255	
53	Blue	255	
54	White	255	
55	Red	255	
56	Green	255	
57	Blue	255	
58	White	255	
59	Red	255	
60	Green	255	
61	Blue	255	
62	White	255	
63	Red	255	
64	Green	255	
65	Blue	255	
66	White	255	
67	Red	255	
68	Green	255	
69	Blue	255	
70	White	255	
71	Red	255	
72	Green	255	
73	Blue	255	
74	White	255	
75	Red	255	
76	Green	255	
77	Blue	255	
78	White	255	
79	Red	255	
80	Green	255	

Single Mode 222Ch (Standard) (continued)

Ch	Function	Default	DMX values
81	Blue	255	
82	White	255	
83	Red	255	
84	Green	255	
85	Blue	255	
86	White	255	
87	Red	255	
88	Green	255	
89	Blue	255	
90	White	255	
91	Red	255	
92	Green	255	
93	Blue	255	
94	White	255	
95	Red	255	
96	Green	255	
97	Blue	255	
98	White	255	
99	Red	255	
100	Green	255	
101	Blue	255	
102	White	255	
103	Red	255	
104	Green	255	
105	Blue	255	
106	White	255	
107	Red	255	
108	Green	255	
109	Blue	255	
110	White	255	
111	Red	255	
112	Green	255	
113	Blue	255	
114	White	255	
115	Red	255	
116	Green	255	
117	Blue	255	
118	White	255	
119	Red	255	
120	Green	255	
121	Blue	255	
122	White	255	
123	Red	255	
124	Green	255	
125	Blue	255	

Single Mode 222Ch (Standard) (continued)

Ch	Function	Default	DMX values
126	White	255	
127	Red	255	
128	Green	255	
129	Blue	255	
130	White	255	
131	Red	255	
132	Green	255	
133	Blue	255	
134	White	255	
135	Red	255	
136	Green	255	
137	Blue	255	
138	White	255	
139	Red	255	
140	Green	255	
141	Blue	255	
142	White	255	
143	Red	255	
144	Green	255	
145	Blue	255	
146	White	255	
147	Red	255	
148	Green	255	
149	Blue	255	
150	White	255	
151	Red	255	
152	Green	255	
153	Blue	255	
154	White	255	
155	Red	255	
156	Green	255	
157	Blue	255	
158	White	255	
159	Red	255	
160	Green	255	
161	Blue	255	
162	White	255	
163	Red	255	
164	Green	255	
165	Blue	255	
166	White	255	
167	Red	255	
168	Green	255	
169	Blue	255	
170	White	255	

Single Mode 222Ch (Standard) (continued)

Ch	Function	Default	DMX values
171	Red	255	
172	Green	255	
173	Blue	255	
174	White	255	
175	Red	255	
176	Green	255	
177	Blue	255	
178	White	255	
179	Red	255	
180	Green	255	
181	Blue	255	
182	White	255	
183	Red	255	
184	Green	255	
185	Blue	255	
186	White	255	
187	Red	255	
188	Green	255	
189	Blue	255	
190	White	255	
191	Red	255	
192	Green	255	
193	Blue	255	
194	White	255	
195	Red	255	
196	Green	255	
197	Blue	255	
198	White	255	
199	Red	255	
200	Green	255	
201	Blue	255	
202	White	255	
203	Red	255	
204	Green	255	
205	Blue	255	
206	White	255	
207	Red	255	
208	Green	255	
209	Blue	255	
210	White	255	
211	Red	255	
212	Green	255	
213	Blue	255	
214	White	255	
215	Red	255	

Single Mode 222Ch (Standard) (continued)

Ch	Function	Default	DMX values
216	Green	255	
217	Blue	255	
218	White	255	
219	Red	255	
220	Green	255	
221	Blue	255	
222	White	255	

Dual -Pix 240Ch (RGB-Adv)

240 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Green	255	
5	Blue	255	
6	Dimmer	0	
7	Dimmer Fine	0	Fine byte of Dimmer
8	Red	255	
9	Green	255	
10	Blue	255	
11	Dimmer	0	
12	Dimmer Fine	0	Fine byte of Dimmer
13	Red	255	
14	Green	255	
15	Blue	255	
16	Dimmer	0	
17	Dimmer Fine	0	Fine byte of Dimmer
18	Red	255	
19	Green	255	
20	Blue	255	
21	Dimmer	0	
22	Dimmer Fine	0	Fine byte of Dimmer
23	Red	255	
24	Green	255	
25	Blue	255	
26	Dimmer	0	
27	Dimmer Fine	0	Fine byte of Dimmer
28	Red	255	
29	Green	255	
30	Blue	255	
31	Dimmer	0	
32	Dimmer Fine	0	Fine byte of Dimmer
33	Red	255	
34	Green	255	

Dual -Pix 240Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
35	Blue	255	
36	Dimmer	0	
37	Dimmer Fine	0	Fine byte of Dimmer
38	Red	255	
39	Green	255	
40	Blue	255	
41	Dimmer	0	
42	Dimmer Fine	0	Fine byte of Dimmer
43	Red	255	
44	Green	255	
45	Blue	255	
46	Dimmer	0	
47	Dimmer Fine	0	Fine byte of Dimmer
48	Red	255	
49	Green	255	
50	Blue	255	
51	Dimmer	0	
52	Dimmer Fine	0	Fine byte of Dimmer
53	Red	255	
54	Green	255	
55	Blue	255	
56	Dimmer	0	
57	Dimmer Fine	0	Fine byte of Dimmer
58	Red	255	
59	Green	255	
60	Blue	255	
61	Dimmer	0	
62	Dimmer Fine	0	Fine byte of Dimmer
63	Red	255	
64	Green	255	
65	Blue	255	
66	Dimmer	0	
67	Dimmer Fine	0	Fine byte of Dimmer
68	Red	255	
69	Green	255	
70	Blue	255	
71	Dimmer	0	
72	Dimmer Fine	0	Fine byte of Dimmer
73	Red	255	
74	Green	255	
75	Blue	255	
76	Dimmer	0	
77	Dimmer Fine	0	Fine byte of Dimmer
78	Red	255	
79	Green	255	

Dual -Pix 240Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
80	Blue	255	
81	Dimmer	0	
82	Dimmer Fine	0	Fine byte of Dimmer
83	Red	255	
84	Green	255	
85	Blue	255	
86	Dimmer	0	
87	Dimmer Fine	0	Fine byte of Dimmer
88	Red	255	
89	Green	255	
90	Blue	255	
91	Dimmer	0	
92	Dimmer Fine	0	Fine byte of Dimmer
93	Red	255	
94	Green	255	
95	Blue	255	
96	Dimmer	0	
97	Dimmer Fine	0	Fine byte of Dimmer
98	Red	255	
99	Green	255	
100	Blue	255	
101	Dimmer	0	
102	Dimmer Fine	0	Fine byte of Dimmer
103	Red	255	
104	Green	255	
105	Blue	255	
106	Dimmer	0	
107	Dimmer Fine	0	Fine byte of Dimmer
108	Red	255	
109	Green	255	
110	Blue	255	
111	Dimmer	0	
112	Dimmer Fine	0	Fine byte of Dimmer
113	Red	255	
114	Green	255	
115	Blue	255	
116	Dimmer	0	
117	Dimmer Fine	0	Fine byte of Dimmer
118	Red	255	
119	Green	255	
120	Blue	255	
121	Dimmer	0	
122	Dimmer Fine	0	Fine byte of Dimmer
123	Red	255	
124	Green	255	

Dual -Pix 240Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
125	Blue	255	
126	Dimmer	0	
127	Dimmer Fine	0	Fine byte of Dimmer
128	Red	255	
129	Green	255	
130	Blue	255	
131	Dimmer	0	
132	Dimmer Fine	0	Fine byte of Dimmer
133	Red	255	
134	Green	255	
135	Blue	255	
136	Dimmer	0	
137	Dimmer Fine	0	Fine byte of Dimmer
138	Red	255	
139	Green	255	
140	Blue	255	
141	Dimmer	0	
142	Dimmer Fine	0	Fine byte of Dimmer
143	Red	255	
144	Green	255	
145	Blue	255	
146	Dimmer	0	
147	Dimmer Fine	0	Fine byte of Dimmer
148	Red	255	
149	Green	255	
150	Blue	255	
151	Dimmer	0	
152	Dimmer Fine	0	Fine byte of Dimmer
153	Red	255	
154	Green	255	
155	Blue	255	
156	Dimmer	0	
157	Dimmer Fine	0	Fine byte of Dimmer
158	Red	255	
159	Green	255	
160	Blue	255	
161	Dimmer	0	
162	Dimmer Fine	0	Fine byte of Dimmer
163	Red	255	
164	Green	255	
165	Blue	255	
166	Dimmer	0	
167	Dimmer Fine	0	Fine byte of Dimmer
168	Red	255	
169	Green	255	

Dual -Pix 240Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
170	Blue	255	
171	Dimmer	0	
172	Dimmer Fine	0	Fine byte of Dimmer
173	Red	255	
174	Green	255	
175	Blue	255	
176	Dimmer	0	
177	Dimmer Fine	0	Fine byte of Dimmer
178	Red	255	
179	Green	255	
180	Blue	255	
181	Dimmer	0	
182	Dimmer Fine	0	Fine byte of Dimmer
183	Red	255	
184	Green	255	
185	Blue	255	
186	Dimmer	0	
187	Dimmer Fine	0	Fine byte of Dimmer
188	Red	255	
189	Green	255	
190	Blue	255	
191	Dimmer	0	
192	Dimmer Fine	0	Fine byte of Dimmer
193	Red	255	
194	Green	255	
195	Blue	255	
196	Dimmer	0	
197	Dimmer Fine	0	Fine byte of Dimmer
198	Red	255	
199	Green	255	
200	Blue	255	
201	Dimmer	0	
202	Dimmer Fine	0	Fine byte of Dimmer
203	Red	255	
204	Green	255	
205	Blue	255	
206	Dimmer	0	
207	Dimmer Fine	0	Fine byte of Dimmer
208	Red	255	
209	Green	255	
210	Blue	255	
211	Dimmer	0	
212	Dimmer Fine	0	Fine byte of Dimmer
213	Red	255	
214	Green	255	

Dual -Pix 240Ch (RGB-Adv) (continued)

Ch	Function	Default	DMX values
215	Blue	255	
216	Dimmer	0	
217	Dimmer Fine	0	Fine byte of Dimmer
218	Red	255	
219	Green	255	
220	Blue	255	
221	Dimmer	0	
222	Dimmer Fine	0	Fine byte of Dimmer
223	Red	255	
224	Green	255	
225	Blue	255	
226	Dimmer	0	
227	Dimmer Fine	0	Fine byte of Dimmer
228	Red	255	
229	Green	255	
230	Blue	255	
231	Dimmer	0	
232	Dimmer Fine	0	Fine byte of Dimmer
233	Red	255	
234	Green	255	
235	Blue	255	
236	Dimmer	0	
237	Dimmer Fine	0	Fine byte of Dimmer
238	Red	255	
239	Green	255	
240	Blue	255	

Dual Pix 288Ch (Adv)

288 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Green	255	
5	Blue	255	
6	White	255	
7	Dimmer	0	
8	Dimmer Fine	0	Fine byte of Dimmer
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	255	
13	Dimmer	0	
14	Dimmer Fine	0	Fine byte of Dimmer
15	Red	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
16	Green	255	
17	Blue	255	
18	White	255	
19	Dimmer	0	
20	Dimmer Fine	0	Fine byte of Dimmer
21	Red	255	
22	Green	255	
23	Blue	255	
24	White	255	
25	Dimmer	0	
26	Dimmer Fine	0	Fine byte of Dimmer
27	Red	255	
28	Green	255	
29	Blue	255	
30	White	255	
31	Dimmer	0	
32	Dimmer Fine	0	Fine byte of Dimmer
33	Red	255	
34	Green	255	
35	Blue	255	
36	White	255	
37	Dimmer	0	
38	Dimmer Fine	0	Fine byte of Dimmer
39	Red	255	
40	Green	255	
41	Blue	255	
42	White	255	
43	Dimmer	0	
44	Dimmer Fine	0	Fine byte of Dimmer
45	Red	255	
46	Green	255	
47	Blue	255	
48	White	255	
49	Dimmer	0	
50	Dimmer Fine	0	Fine byte of Dimmer
51	Red	255	
52	Green	255	
53	Blue	255	
54	White	255	
55	Dimmer	0	
56	Dimmer Fine	0	Fine byte of Dimmer
57	Red	255	
58	Green	255	
59	Blue	255	
60	White	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
61	Dimmer	0	
62	Dimmer Fine	0	Fine byte of Dimmer
63	Red	255	
64	Green	255	
65	Blue	255	
66	White	255	
67	Dimmer	0	
68	Dimmer Fine	0	Fine byte of Dimmer
69	Red	255	
70	Green	255	
71	Blue	255	
72	White	255	
73	Dimmer	0	
74	Dimmer Fine	0	Fine byte of Dimmer
75	Red	255	
76	Green	255	
77	Blue	255	
78	White	255	
79	Dimmer	0	
80	Dimmer Fine	0	Fine byte of Dimmer
81	Red	255	
82	Green	255	
83	Blue	255	
84	White	255	
85	Dimmer	0	
86	Dimmer Fine	0	Fine byte of Dimmer
87	Red	255	
88	Green	255	
89	Blue	255	
90	White	255	
91	Dimmer	0	
92	Dimmer Fine	0	Fine byte of Dimmer
93	Red	255	
94	Green	255	
95	Blue	255	
96	White	255	
97	Dimmer	0	
98	Dimmer Fine	0	Fine byte of Dimmer
99	Red	255	
100	Green	255	
101	Blue	255	
102	White	255	
103	Dimmer	0	
104	Dimmer Fine	0	Fine byte of Dimmer
105	Red	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
106	Green	255	
107	Blue	255	
108	White	255	
109	Dimmer	0	
110	Dimmer Fine	0	Fine byte of Dimmer
111	Red	255	
112	Green	255	
113	Blue	255	
114	White	255	
115	Dimmer	0	
116	Dimmer Fine	0	Fine byte of Dimmer
117	Red	255	
118	Green	255	
119	Blue	255	
120	White	255	
121	Dimmer	0	
122	Dimmer Fine	0	Fine byte of Dimmer
123	Red	255	
124	Green	255	
125	Blue	255	
126	White	255	
127	Dimmer	0	
128	Dimmer Fine	0	Fine byte of Dimmer
129	Red	255	
130	Green	255	
131	Blue	255	
132	White	255	
133	Dimmer	0	
134	Dimmer Fine	0	Fine byte of Dimmer
135	Red	255	
136	Green	255	
137	Blue	255	
138	White	255	
139	Dimmer	0	
140	Dimmer Fine	0	Fine byte of Dimmer
141	Red	255	
142	Green	255	
143	Blue	255	
144	White	255	
145	Dimmer	0	
146	Dimmer Fine	0	Fine byte of Dimmer
147	Red	255	
148	Green	255	
149	Blue	255	
150	White	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
151	Dimmer	0	
152	Dimmer Fine	0	Fine byte of Dimmer
153	Red	255	
154	Green	255	
155	Blue	255	
156	White	255	
157	Dimmer	0	
158	Dimmer Fine	0	Fine byte of Dimmer
159	Red	255	
160	Green	255	
161	Blue	255	
162	White	255	
163	Dimmer	0	
164	Dimmer Fine	0	Fine byte of Dimmer
165	Red	255	
166	Green	255	
167	Blue	255	
168	White	255	
169	Dimmer	0	
170	Dimmer Fine	0	Fine byte of Dimmer
171	Red	255	
172	Green	255	
173	Blue	255	
174	White	255	
175	Dimmer	0	
176	Dimmer Fine	0	Fine byte of Dimmer
177	Red	255	
178	Green	255	
179	Blue	255	
180	White	255	
181	Dimmer	0	
182	Dimmer Fine	0	Fine byte of Dimmer
183	Red	255	
184	Green	255	
185	Blue	255	
186	White	255	
187	Dimmer	0	
188	Dimmer Fine	0	Fine byte of Dimmer
189	Red	255	
190	Green	255	
191	Blue	255	
192	White	255	
193	Dimmer	0	
194	Dimmer Fine	0	Fine byte of Dimmer
195	Red	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
196	Green	255	
197	Blue	255	
198	White	255	
199	Dimmer	0	
200	Dimmer Fine	0	Fine byte of Dimmer
201	Red	255	
202	Green	255	
203	Blue	255	
204	White	255	
205	Dimmer	0	
206	Dimmer Fine	0	Fine byte of Dimmer
207	Red	255	
208	Green	255	
209	Blue	255	
210	White	255	
211	Dimmer	0	
212	Dimmer Fine	0	Fine byte of Dimmer
213	Red	255	
214	Green	255	
215	Blue	255	
216	White	255	
217	Dimmer	0	
218	Dimmer Fine	0	Fine byte of Dimmer
219	Red	255	
220	Green	255	
221	Blue	255	
222	White	255	
223	Dimmer	0	
224	Dimmer Fine	0	Fine byte of Dimmer
225	Red	255	
226	Green	255	
227	Blue	255	
228	White	255	
229	Dimmer	0	
230	Dimmer Fine	0	Fine byte of Dimmer
231	Red	255	
232	Green	255	
233	Blue	255	
234	White	255	
235	Dimmer	0	
236	Dimmer Fine	0	Fine byte of Dimmer
237	Red	255	
238	Green	255	
239	Blue	255	
240	White	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
241	Dimmer	0	
242	Dimmer Fine	0	Fine byte of Dimmer
243	Red	255	
244	Green	255	
245	Blue	255	
246	White	255	
247	Dimmer	0	
248	Dimmer Fine	0	Fine byte of Dimmer
249	Red	255	
250	Green	255	
251	Blue	255	
252	White	255	
253	Dimmer	0	
254	Dimmer Fine	0	Fine byte of Dimmer
255	Red	255	
256	Green	255	
257	Blue	255	
258	White	255	
259	Dimmer	0	
260	Dimmer Fine	0	Fine byte of Dimmer
261	Red	255	
262	Green	255	
263	Blue	255	
264	White	255	
265	Dimmer	0	
266	Dimmer Fine	0	Fine byte of Dimmer
267	Red	255	
268	Green	255	
269	Blue	255	
270	White	255	
271	Dimmer	0	
272	Dimmer Fine	0	Fine byte of Dimmer
273	Red	255	
274	Green	255	
275	Blue	255	
276	White	255	
277	Dimmer	0	
278	Dimmer Fine	0	Fine byte of Dimmer
279	Red	255	
280	Green	255	
281	Blue	255	
282	White	255	
283	Dimmer	0	
284	Dimmer Fine	0	Fine byte of Dimmer
285	Red	255	

Dual Pix 288Ch (Adv) (continued)

Ch	Function	Default	DMX values
286	Green	255	
287	Blue	255	
288	White	255	

Single Mode 314Ch (Advanced)

314 channels

Ch	Function	Default	DMX values
1	Tilt	127	
2	Tilt Fine	255	Fine byte of Tilt
3	Position MSpeed	0	
4	Frost1	0	
5	Shutter1Strobe	0	
6	Shutter / Strobe	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
7	Shutter2Strobe	0	
8	Shutter / Strobe 2	0	0–9 Open 10–250 0 289 - 16 67Hz 251–255 Open
9	Shutter1Strobe Effect	0	
10	Shutter2Strobe Effect	0	
11	C TC	0	
12	Dimmer	0	
13	Color Macro1	0	
14	Dimmer	0	
15	Color Macro2	0	
16	Color Macro3	0	
17	Color Macro3Rate	0	
18	Color Macro4	0	
19	Dimmer	0	
20	Color Macro5	0	
21	Dimmer	0	
22	Color Macro6	0	
23	Color Macro7	0	
24	Color Macro7Rate	0	
25	Color Macro8	0	
26	Control1	0	
27	Dimmer	0	
28	Dimmer Fine	0	Fine byte of Dimmer
29	Red	255	
30	Green	255	
31	Blue	255	
32	White	255	
33	Dimmer	0	
34	Dimmer Fine	0	Fine byte of Dimmer
35	Red	255	
36	Green	255	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
37	Blue	255	
38	White	255	
39	Dimmer	0	
40	Dimmer Fine	0	Fine byte of Dimmer
41	Red	255	
42	Green	255	
43	Blue	255	
44	White	255	
45	Dimmer	0	
46	Dimmer Fine	0	Fine byte of Dimmer
47	Red	255	
48	Green	255	
49	Blue	255	
50	White	255	
51	Dimmer	0	
52	Dimmer Fine	0	Fine byte of Dimmer
53	Red	255	
54	Green	255	
55	Blue	255	
56	White	255	
57	Dimmer	0	
58	Dimmer Fine	0	Fine byte of Dimmer
59	Red	255	
60	Green	255	
61	Blue	255	
62	White	255	
63	Dimmer	0	
64	Dimmer Fine	0	Fine byte of Dimmer
65	Red	255	
66	Green	255	
67	Blue	255	
68	White	255	
69	Dimmer	0	
70	Dimmer Fine	0	Fine byte of Dimmer
71	Red	255	
72	Green	255	
73	Blue	255	
74	White	255	
75	Dimmer	0	
76	Dimmer Fine	0	Fine byte of Dimmer
77	Red	255	
78	Green	255	
79	Blue	255	
80	White	255	
81	Dimmer	0	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
82	Dimmer Fine	0	Fine byte of Dimmer
83	Red	255	
84	Green	255	
85	Blue	255	
86	White	255	
87	Dimmer	0	
88	Dimmer Fine	0	Fine byte of Dimmer
89	Red	255	
90	Green	255	
91	Blue	255	
92	White	255	
93	Dimmer	0	
94	Dimmer Fine	0	Fine byte of Dimmer
95	Red	255	
96	Green	255	
97	Blue	255	
98	White	255	
99	Dimmer	0	
100	Dimmer Fine	0	Fine byte of Dimmer
101	Red	255	
102	Green	255	
103	Blue	255	
104	White	255	
105	Dimmer	0	
106	Dimmer Fine	0	Fine byte of Dimmer
107	Red	255	
108	Green	255	
109	Blue	255	
110	White	255	
111	Dimmer	0	
112	Dimmer Fine	0	Fine byte of Dimmer
113	Red	255	
114	Green	255	
115	Blue	255	
116	White	255	
117	Dimmer	0	
118	Dimmer Fine	0	Fine byte of Dimmer
119	Red	255	
120	Green	255	
121	Blue	255	
122	White	255	
123	Dimmer	0	
124	Dimmer Fine	0	Fine byte of Dimmer
125	Red	255	
126	Green	255	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
127	Blue	255	
128	White	255	
129	Dimmer	0	
130	Dimmer Fine	0	Fine byte of Dimmer
131	Red	255	
132	Green	255	
133	Blue	255	
134	White	255	
135	Dimmer	0	
136	Dimmer Fine	0	Fine byte of Dimmer
137	Red	255	
138	Green	255	
139	Blue	255	
140	White	255	
141	Dimmer	0	
142	Dimmer Fine	0	Fine byte of Dimmer
143	Red	255	
144	Green	255	
145	Blue	255	
146	White	255	
147	Dimmer	0	
148	Dimmer Fine	0	Fine byte of Dimmer
149	Red	255	
150	Green	255	
151	Blue	255	
152	White	255	
153	Dimmer	0	
154	Dimmer Fine	0	Fine byte of Dimmer
155	Red	255	
156	Green	255	
157	Blue	255	
158	White	255	
159	Dimmer	0	
160	Dimmer Fine	0	Fine byte of Dimmer
161	Red	255	
162	Green	255	
163	Blue	255	
164	White	255	
165	Dimmer	0	
166	Dimmer Fine	0	Fine byte of Dimmer
167	Red	255	
168	Green	255	
169	Blue	255	
170	White	255	
171	Dimmer	0	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
172	Dimmer Fine	0	Fine byte of Dimmer
173	Red	255	
174	Green	255	
175	Blue	255	
176	White	255	
177	Dimmer	0	
178	Dimmer Fine	0	Fine byte of Dimmer
179	Red	255	
180	Green	255	
181	Blue	255	
182	White	255	
183	Dimmer	0	
184	Dimmer Fine	0	Fine byte of Dimmer
185	Red	255	
186	Green	255	
187	Blue	255	
188	White	255	
189	Dimmer	0	
190	Dimmer Fine	0	Fine byte of Dimmer
191	Red	255	
192	Green	255	
193	Blue	255	
194	White	255	
195	Dimmer	0	
196	Dimmer Fine	0	Fine byte of Dimmer
197	Red	255	
198	Green	255	
199	Blue	255	
200	White	255	
201	Dimmer	0	
202	Dimmer Fine	0	Fine byte of Dimmer
203	Red	255	
204	Green	255	
205	Blue	255	
206	White	255	
207	Dimmer	0	
208	Dimmer Fine	0	Fine byte of Dimmer
209	Red	255	
210	Green	255	
211	Blue	255	
212	White	255	
213	Dimmer	0	
214	Dimmer Fine	0	Fine byte of Dimmer
215	Red	255	
216	Green	255	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
217	Blue	255	
218	White	255	
219	Dimmer	0	
220	Dimmer Fine	0	Fine byte of Dimmer
221	Red	255	
222	Green	255	
223	Blue	255	
224	White	255	
225	Dimmer	0	
226	Dimmer Fine	0	Fine byte of Dimmer
227	Red	255	
228	Green	255	
229	Blue	255	
230	White	255	
231	Dimmer	0	
232	Dimmer Fine	0	Fine byte of Dimmer
233	Red	255	
234	Green	255	
235	Blue	255	
236	White	255	
237	Dimmer	0	
238	Dimmer Fine	0	Fine byte of Dimmer
239	Red	255	
240	Green	255	
241	Blue	255	
242	White	255	
243	Dimmer	0	
244	Dimmer Fine	0	Fine byte of Dimmer
245	Red	255	
246	Green	255	
247	Blue	255	
248	White	255	
249	Dimmer	0	
250	Dimmer Fine	0	Fine byte of Dimmer
251	Red	255	
252	Green	255	
253	Blue	255	
254	White	255	
255	Dimmer	0	
256	Dimmer Fine	0	Fine byte of Dimmer
257	Red	255	
258	Green	255	
259	Blue	255	
260	White	255	
261	Dimmer	0	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
262	Dimmer Fine	0	Fine byte of Dimmer
263	Red	255	
264	Green	255	
265	Blue	255	
266	White	255	
267	Dimmer	0	
268	Dimmer Fine	0	Fine byte of Dimmer
269	Red	255	
270	Green	255	
271	Blue	255	
272	White	255	
273	Dimmer	0	
274	Dimmer Fine	0	Fine byte of Dimmer
275	Red	255	
276	Green	255	
277	Blue	255	
278	White	255	
279	Dimmer	0	
280	Dimmer Fine	0	Fine byte of Dimmer
281	Red	255	
282	Green	255	
283	Blue	255	
284	White	255	
285	Dimmer	0	
286	Dimmer Fine	0	Fine byte of Dimmer
287	Red	255	
288	Green	255	
289	Blue	255	
290	White	255	
291	Dimmer	0	
292	Dimmer Fine	0	Fine byte of Dimmer
293	Red	255	
294	Green	255	
295	Blue	255	
296	White	255	
297	Dimmer	0	
298	Dimmer Fine	0	Fine byte of Dimmer
299	Red	255	
300	Green	255	
301	Blue	255	
302	White	255	
303	Dimmer	0	
304	Dimmer Fine	0	Fine byte of Dimmer
305	Red	255	
306	Green	255	

Single Mode 314Ch (Advanced) (continued)

Ch	Function	Default	DMX values
307	Blue	255	
308	White	255	
309	Dimmer	0	
310	Dimmer Fine	0	Fine byte of Dimmer
311	Red	255	
312	Green	255	
313	Blue	255	
314	White	255	