CKC Lighting

Fresnel 60



Manufacturer	**CKC Lighting**
Type	**Spot**
DMX modes	**4**
DMX footprint	**1, 2, 3, 4 channels**
Beam angle	**32°**
Size (W × H × D)	**240 × 240 × 35 mm**
GDTF fixture type	**2BC0E1E3-D29E-4175-A553-0F…**

Controls

Strobe · Dimmer

DMX modes

1CH	1 ch
2CH	2 ch
3CH	3 ch
4CH	4 ch

1CH

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 0% 255–255 100%

2CH

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 0% 255–255 100%
2	Shutter / Strobe	50	0–31 Shutter Closed (1) 32–63 Shutter Open (1) 64–77 Strobe slow 78–92 Strobe mid 93–95 Strobe fast 96–127 Shutter Open (2) 128–140 Pulse slow 141–156 Pulse mid 157–159 Pulse fast 160–191 Shutter Open (3) 192–204 Random · Str Rnd slow 1–8.35 Hz 205–220 Random · Str Rnd mid 8.97–18.2 Hz 221–223 Random · Str Rnd fast 18.8–20 Hz 224–255 Shutter Open (4)

3CH

3 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 0% 255–255 100%
2	Shutter / Strobe	50	0–31 Shutter Closed (1) 32–63 Shutter Open (1) 64–77 Strobe slow 78–92 Strobe mid 93–95 Strobe fast 96–127 Shutter Open (2) 128–140 Pulse slow 141–156 Pulse mid 157–159 Pulse fast 160–191 Shutter Open (3) 192–204 Random · Str Rnd slow 1–8.35 Hz 205–220 Random · Str Rnd mid 8.97–18.2 Hz 221–223 Random · Str Rnd fast 18.8–20 Hz 224–255 Shutter Open (4)
3	Dimmer Mode	0	0–20 Standard 21–40 Stage 41–60 TV 61–80 Architectural 81–100 Theatre 101–255 Default to Unit Setting

4CH

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 0% 255–255 100%
2	Dimmer Fine	0	Fine byte of Dimmer

4CH (continued)

Ch	Function	Default	DMX values
3	Shutter / Strobe	50	0–31 Shutter Closed (1) 32–63 Shutter Open (1) 64–77 Strobe slow 78–92 Strobe mid 93–95 Strobe fast 96–127 Shutter Open (2) 128–140 Pulse slow 141–156 Pulse mid 157–159 Pulse fast 160–191 Shutter Open (3) 192–204 Random · Str Rnd slow 1–8.35 Hz 205–220 Random · Str Rnd mid 8.97–18.2 Hz 221–223 Random · Str Rnd fast 18.8–20 Hz 224–255 Shutter Open (4)
4	Dimmer Mode	0	0–20 Standard 21–40 Stage 41–60 TV 61–80 Architectural 81–100 Theatre 101–255 Default to Unit Setting