Elation

Fuze Wash 575



Manufacturer	**Elation**
Type	**Moving head**
DMX modes	**2**
DMX footprint	**9, 11 channels**
Beam angle	**11-40°**
Pan range	**540°**
Tilt range	**270°**
Size (W × H × D)	**235 × 238 × 228 mm**
GDTF fixture type	**06B941A1-1ECD-416B-BFCC-00…**

Controls

Zoom · Strobe · Dimmer · Pan and tilt

Safety-relevant functions

Strobe

DMX modes

9CH 8bit	9 ch
11CH 16bit	11 ch

9CH 8bit

9 channels

Ch	Function	Default	DMX values
1	Pan	127	
2	Tilt	128	
3	Dimmer	0	0–62 0% (wheel slot 1) 63–126 25% 127–190 50% 191–254 75% 255–255 100%
4	Dimmer Fine	0	Fine byte of Dimmer
5	Shutter / Strobe	50	0–31 Closed 32–63 Open 64–94 Strobe Min 95–95 Strobe Max 96–127 Open 128–158 Strobe Pulse Min 159–159 Strobe Pulse Max 160–191 Open 192–222 Random Strobe Min 223–223 Random Strobe Max 224–255 Open
6	Zoom	0	
7	Dimmer Mode	0	0–20 Standard 21–40 Stage 41–60 TV 61–80 Architectural 81–100 Theatre 101–255 Default to unit setting
8	Pan Tilt Mode	0	0–225 Speed maximum to minimum 226–235 Blackout by movement 236–255 No Function
9	Function	0	0–79 Normal 80–84 All Motor Reset 85–89 Enable Auto Scene 90–99 Save New Auto Scene 100–119 Internal Programs 1 120–139 Internal Programs 2 140–159 Internal Programs 3 160–179 Internal Programs 4 180–199 Internal Programs 5 200–219 Internal Programs 6 220–239 Internal Programs 7 240–255 No Function

11CH 16bit

11 channels

Ch	Function	Default	DMX values
1	Pan	127	
2	Pan Fine	255	Fine byte of Pan
3	Tilt	128	
4	Tilt Fine	0	Fine byte of Tilt
5	Dimmer	0	0–62 0% (wheel slot 1) 63–126 25% 127–190 50% 191–254 75% 255–255 100%
6	Dimmer Fine	0	Fine byte of Dimmer

11CH 16bit (continued)

Ch	Function	Default	DMX values
7	Shutter / Strobe	50	0–31 Closed 32–63 Open 64–94 Strobe Min 95–95 Strobe Max 96–127 Open 128–158 Strobe Pulse Min 159–159 Strobe Pulse Max 160–191 Open 192–222 Random Strobe Min 223–223 Random Strobe Max 224–255 Open
8	Zoom	0	
9	Dimmer Mode	0	0–20 Standard 21–40 Stage 41–60 TV 61–80 Architectural 81–100 Theatre 101–255 Default to unit setting
10	Pan Tilt Mode	0	0–225 Speed maximum to minimum 226–235 Blackout by movement 236–255 No Function
11	Function	0	0–79 Normal 80–84 All Motor Reset 85–89 Enable Auto Scene 90–99 Save New Auto Scene 100–119 Internal Programs 1 120–139 Internal Programs 2 140–159 Internal Programs 3 160–179 Internal Programs 4 180–199 Internal Programs 5 200–219 Internal Programs 6 220–239 Internal Programs 7 240–255 No Function