Eurolite

LED SLS-98 Strobe SMD



Manufacturer	**Eurolite**
Type	**Strobe**
DMX modes	**2**
DMX footprint	**4, 9 channels**
Beam angle	**120°**
Size (W × H × D)	**215 × 120 × 245 mm**
GDTF fixture type	**A795C24D-4D5A-5FE9-BEDE-E…**

Controls

Colour wheel · Strobe · Dimmer · Effect control

Safety-relevant functions

Built-in effect programmes

DMX modes

4CH	4 ch
9CH	9 ch

4CH

4 channels

Ch	Function	Default	DMX values
1	Color Macro1	0	0–9 No function 10–19 SMD1 (White) 20–29 SMD2 (White) 30–39 SMD3 (White) 40–49 SMD4 (White) 50–59 SMD5 (White) 60–69 SMD1 + SMD2 (White) 70–79 SMD1 + SMD3 (White) 80–89 SMD1 + SMD4 (White) 90–99 SMD1 + SMD5 (White) 100–109 SMD2 + SMD3 (White) 110–119 SMD2 + SMD4 (White) 120–129 SMD2 + SMD5 (White) 130–139 SMD3 + SMD4 (White) 140–149 SMD3 + SMD5 (White) 150–159 SMD4 + SMD5 (White) 160–169 SMD1 + SMD2 + SMD3 (White) 170–179 SMD1 + SMD2 + SMD4 (White) 180–189 SMD1 + SMD2 + SMD5 (White) 190–199 SMD1 + SMD3 + SMD4 (White) 200–209 SMD1 + SMD3 + SMD5 (White) 210–219 SMD2 + SMD3 + SMD4 (White) 220–229 SMD2 + SMD3 + SMD5 (White) 230–239 SMD3 + SMD4 + SMD5 (White) 240–249 SMD1 + SMD2 + SMD3 + SMD4 (White) 250–255 SMD1 + SMD2 + SMD3 + SMD4 + SMD5 (White)
2	Shutter / Strobe	0	0–9 No function 10–255 Strobe1 · Increasing speed 0.1–20 Hz
3	Effect	0	0–9 No function 10–199 Auto program 200–255 Sound program
4	Effect Speed	0	

9CH

9 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer	0	
3	Dimmer	0	
4	Dimmer	0	
5	Dimmer	0	
6	Dimmer	0	
7	Shutter / Strobe	0	0–9 No function 10–255 Strobe1 · Increasing speed 0.1–20 Hz
8	Effect	0	0–9 No function 10–199 Auto program 200–255 Sound program
9	Effect Speed	0	