Litecraft

Wash X21



Manufacturer	**Litecraft**
Type	**PAR**
DMX modes	**3**
DMX footprint	**4, 6, 11 channels**
Beam angle	**43°**
Size (W × H × D)	**456 × 200 × 140 mm**
GDTF fixture type	**740C57AF-FF34-4F1B-8F6A-FA…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer

Safety-relevant functions

Strobe

DMX modes

4 Channels	4 ch
6 Channels	6 ch
11 channel	11 ch

4 Channels

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

6 Channels

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Red	255	
3	Green	255	
4	Blue	255	
5	White	0	
6	Shutter / Strobe	0	0–10 no Function 11–129 Slow Strobe 130–254 Medium Strobe 255–255 Fast Strobe

11 channel

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Red	255	
3	Green	255	
4	Blue	255	
5	White	0	
6	Shutter / Strobe	0	0–10 no Function 11–129 Slow Strobe 130–254 Medium Strobe 255–255 Fast Strobe
7	Color Effects1	0	0–10 no Function 11–30 R=100/G=0-100/B=0 31–50 R=100-0/G=100/B=0 51–70 R=0/G=0-100/B=0-100 71–90 R=0/G=100-0/B=100 91–110 R=0-100/G=0/B=100 111–130 R=100/G=0/B=100-0 131–150 R=100/G=0-100/B=0-100 151–170 R=100-0/G=0-100/B=100 171–200 R=100/G=100/B=100/W=100 201–205 Color 1 206–210 Color 2 211–215 Color 3 216–220 Color 4 221–225 Color 5 226–230 Color 6 231–235 Color 7 236–240 Color 8 241–245 Color 9 246–250 Color 10 251–255 Color 11

11 channel (continued)

Ch	Function	Default	DMX values
8	Custom Color	0	0–5 No Function 6–29 3000K 30–53 4000K 54–77 4200K 78–101 5000K 102–125 5600K 126–149 6000K 150–173 7000K 174–197 8000K 198–221 9000K 222–245 10000K 246–255 No Function
9	Color Macro1	0	0–10 No Function 11–60 Programm Auto 1 61–110 Programm Auto 2 111–160 Programm Auto 3 161–210 Programm Auto 4 211–255 Programm Auto 5 (1-4)
10	Color Macro1Rate	0	0–254 slow 255–255 fast
11	Dimmer Mode	0	0–51 Modus from Setting 52–101 Off 102–152 Dimmer 1 (fast) 153–203 Dimmer 2 (medium) 204–255 Dimmer 3 (slow)