Lotus Light

ST 100 AQUA 2



Manufacturer	**Lotus Light**
Type	**Strobe**
DMX modes	**2**
DMX footprint	**4, 16 channels**
Size (W × H × D)	**1000 × 130 × 85 mm**
GDTF fixture type	**7D89C28A-8DE5-406B-A22B-1F…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer · Pixel control

DMX modes

4 Channel	4 ch
16 Channel	16 ch

4 Channel

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

16 Channel

16 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 closed 255–255 open
2	Shutter / Strobe	0	0–5 Open 6–6 min Strobe 7–249 Strobe3 · Slow > Fast 0.58–19.9 Hz 250–250 max Strobe 251–255 Open
3	Red	255	
4	Green	255	
5	Blue	255	
6	Color Macro1	0	
7	Color Macro1Rate	0	
8	Shutter / Strobe	0	0–4 Open 5–5 Min Strobe 6–254 StrobeFrequency 1 · Slow > Fast 0.777–19.9 Hz 255–255 Max Strobe
9	White	0	
10	Strobe Mode Effect	0	0–5 Strobe 6–42 Ramp Up 43–85 Ramp Down 86–128 Sin 129–171 Bursts 172–214 Bursts Slow 215–255 Bursts Fast
11	Strobe Duration	0	
12	Shutter / Strobe	0	0–4 Open 5–5 Min Strobe 6–254 StrobeFrequency 1 · Slow > Fast 0.777–19.9 Hz 255–255 Max Strobe
13	Color Macro1	0	
14	Color Macro1Rate	0	
15	Dimmer Mode	0	
16	Dimmer Curve	0	