MARK

MBAR 354



Manufacturer	**MARK**
Type	**LED bar**
DMX modes	**3**
DMX footprint	**3, 7, 13 channels**
Beam angle	**35°**
Heads / cells	**3**
Size (W × H × D)	**1050 × 80 × 105 mm**
GDTF fixture type	**E9946408-2B88-466A-9565-000…**

Controls

RGB colour mixing · Colour wheel · Strobe · Dimmer · Pixel control

Safety-relevant functions

Strobe

DMX modes

3CH	3 ch
7CH	7 ch
13CH	13 ch

3CH

3 channels

Ch	Function	Default	DMX values
1	Red	255	0–0 Min 1–254 Min to Max 255–255 Max
2	Green	255	0–0 Min 1–254 Min to Max 255–255 Max
3	Blue	255	0–0 Min 1–254 Min to Max 255–255 Max

7CH

7 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min to Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min to Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min to Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min to Max 255–255 Max
5	Shutter / Strobe	0	0–9 Open 10–254 Strobe Min 255–255 Strobe Max
6	Color Macro1	0	0–9 Open 10–33 All Macro 34–57 Gradual Color Change 58–81 Pulse Color Change 82–105 Jump Color Change 106–129 Macro 1 130–153 Macro 2 154–177 Macro 3 178–201 Jump RGB Change 202–225 Jump CMY Change 226–249 Macro 4 250–255 Sound Mode
7	Color Macro1Rate	0	0–254 Slow 255–255 Fast

13CH

13 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Red	255	
5	Green	255	
6	Blue	255	
7	Red	255	
8	Green	255	

13CH (continued)

Ch	Function	Default	DMX values
9	Blue	255	
10	No Feature	0	
11	Shutter / Strobe	0	0–9 Open 10–254 Strobe Min 255–255 Strobe Max
12	Color Effects1	0	0–9 Open 10–33 All Macro 34–57 Gradual Color Change 58–81 Pulse Color Change 82–105 Jump Color Change 106–129 Macro 1 130–153 Macro 2 154–177 Macro 3 178–201 Jump RGB Change 202–225 Jump CMY Change 226–249 Macro 4 250–255 Sound Mode
13	Color Macro1Rate	0	0–0 Min 1–254 Min > Max 255–255 Max