PRstage

Dimmer Pack 4



Manufacturer	**PRstage**
Type	**Dimmer pack**
DMX modes	**5**
DMX footprint	**4, 5, 8 channels**
Size (W × H × D)	**250 × 203 × 96 mm**
GDTF fixture type	**FA7BD9E6-121C-43EC-86B1-20…**

Controls

Effect speed · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

Mode 1 - 4CH DM4	4 ch
Mode 2 - 4CH DM4-MFP	4 ch
Mode 4 - SW4	4 ch
Mode 5 - SW4-M	5 ch
Mode 3 - DM4-MFP	8 ch

Mode 1 - 4CH DM4

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer	0	0–254 Closed 255–255 Open
3	Dimmer	0	0–254 Closed 255–255 Open
4	Dimmer	0	0–254 Closed 255–255 Open

Mode 2 - 4CH DM4-MFP

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Effects1Fade	0	0–0 Fade Off 1–7 Without Invesion 8–255 With Inversion
3	Effect	0	0–15 Effects Off 16–45 Bubble Jump 46–75 Flowing Water 76–105 Pass Field 106–135 Swing 136–165 Waves 166–195 Chase 196–254 Ripples 255–255 Starling
4	Effect Speed	127	

Mode 4 - SW4

4 channels

Ch	Function	Default	DMX values
1	Control1	0	0–127 Socket 1 Off (wheel slot 1) 128–255 Socket 1 On (wheel slot 2)
2	Control1	0	0–127 Socket 2 Off (wheel slot 1) 128–255 Socket 2 On (wheel slot 2)
3	Control1	0	0–127 Socket 3 Off (wheel slot 1) 128–255 Socket 3 On (wheel slot 2)
4	Control1	0	0–127 Socket 4 Off (wheel slot 1) 128–255 Socket 4 On (wheel slot 2)

Mode 5 - SW4-M

5 channels

Ch	Function	Default	DMX values
1	Control1	100	0–63 Fixed parameters sockets 64–127 Allow to change parameters sockets 128–191 All socket On (wheel slot 2) 192–255 All socket Off (wheel slot 1)
2	Control1	0	0–127 Socket 1 Off (wheel slot 1) 128–255 Socket 1 On (wheel slot 2)
3	Control1	0	0–127 Socket 2 Off (wheel slot 1) 128–255 Socket 2 On (wheel slot 2)
4	Control1	0	0–127 Socket 3 Off (wheel slot 1) 128–255 Socket 3 On (wheel slot 2)

Mode 5 - SW4-M (continued)

Ch	Function	Default	DMX values
5	Control1	0	0–127 Socket 4 Off (wheel slot 1) 128–255 Socket 4 On (wheel slot 2)

Mode 3 - DM4-MFP

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Effects1Fade	0	0–0 Fade Off 1–7 Without Invesion 8–255 With Inversion
3	Effect	0	0–15 Effects Off 16–45 Bubble Jump 46–75 Flowing Water 76–105 Pass Field 106–135 Swing 136–165 Waves 166–195 Chase 196–254 Ripples 255–255 Starling
4	Effect Speed	127	
5	Dimmer	0	0–254 Closed 255–255 Open
6	Dimmer	0	0–254 Closed 255–255 Open
7	Dimmer	0	0–254 Closed 255–255 Open
8	Dimmer	0	0–254 Closed 255–255 Open