Terbly

OVAL9D



Manufacturer	**Terbly**
Type	**Effect light**
DMX modes	**6**
DMX footprint	**4, 5, 6, 8 channels**
Beam angle	**10°**
Size (W × H × D)	**268 × 292 × 232 mm**
GDTF fixture type	**8B857665-F2D2-483E-83CA-E5…**

Controls

Extra LED colours · RGB colour mixing · Effect speed · Strobe · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

36Channel	4 ch
4Channel	4 ch
5Channel	5 ch
Pixel	5 ch
6Channel	6 ch
8Channel	8 ch

36Channel

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

4Channel

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

5Channel

5 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Dimmer	0	0–254 Closed 255–255 Open

Pixel

5 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Dimmer	0	0–254 Closed 255–255 Open

6Channel

6 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

6Channel (continued)

Ch	Function	Default	DMX values
5	Shutter / Strobe	63	0–31 Closed 32–63 Open 64–94 min Strobe 95–95 max Strobe 96–127 Open 2 128–158 min Pulse 159–159 max Pulse 160–191 Open 3 192–222 Random · min Rnd 1–24.2 Hz 223–223 Random · maxRnd 25 Hz 224–255 Open 4
6	Dimmer	0	0–254 Closed 255–255 Open

8Channel

8 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	
5	Shutter / Strobe	63	0–31 Closed 32–63 Open 64–94 min Strobe 95–95 max Strobe 96–127 Open 2 128–158 min Pulse 159–159 max Pulse 160–191 Open 3 192–222 Random · min Rnd 1–24.2 Hz 223–223 Random · maxRnd 25 Hz 224–255 Open 4
6	Dimmer	0	0–254 Closed 255–255 Open
7	Effect	0	0–10 No function 11–40 Chase 1 41–70 Chase 2 71–100 Chase 3 101–130 Chase 4 131–160 Chase 5 161–190 Chase 6 191–220 Chase 7 221–255 Chase 8
8	Effect Speed	0	