ACME

ACME COCKTAIL (AM1 RGBW)



Manufacturer	**ACME**
Type	**Moving head**
DMX modes	**2**
DMX footprint	**13, 15 channels**
Beam angle	**10-40°**
Pan range	**540°**
Tilt range	**200°**
Size (W × H × D)	**185 × 271 × 185 mm**
GDTF fixture type	**54B34FAD-F766-4117-8DF0-4B…**

Controls

Zoom · Extra LED colours · RGB colour mixing · Colour temperature · Strobe · Dimmer · Pan and tilt

Safety-relevant functions

Fixture reset · Strobe

DMX modes

Mode 1 13 DMX	13 ch
Mode 2 15 DMX	15 ch

Mode 1 13 DMX

13 channels

Ch	Function	Default	DMX values
1	Pan	127	
2	Tilt	127	
3	P TSpeed	0	
4	Zoom	127	
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	0	
9	C TO	0	
10	Shutter / Strobe	63	0–31 Closed 32–63 Open 64–94 min Strobe 95–95 max Strobe 96–127 Open 2 128–158 max Pulse Open 159–159 min Pulse Open 160–191 Open 3 192–223 Strobe Ran 224–255 Open 4
11	Dimmer	0	
12	Dimmer Fine	0	Fine byte of Dimmer
13	Function	0	0–69 No Feature 1 70–79 Black out Pan Tilt Move Enable 80–89 Black out Pan Tilt Move Disable 90–139 No Feature 2 140–149 PT Reset 150–169 No Feature 2 170–179 Zoom Reset 180–199 No Feature 4 200–209 All Reset 218–255 No Feature 5

Mode 2 15 DMX

15 channels

Ch	Function	Default	DMX values
1	Pan	127	
2	Pan Fine	255	Fine byte of Pan
3	Tilt	127	
4	Tilt Fine	255	Fine byte of Tilt
5	P TSpeed	0	
6	Zoom	127	
7	Red	255	
8	Green	255	
9	Blue	255	
10	White	0	
11	C TO	0	

Mode 2 15 DMX (continued)

Ch	Function	Default	DMX values
12	Shutter / Strobe	63	0–31 Closed 32–63 Open 64–94 min Strobe 95–95 max Strobe 96–127 Open 2 128–158 max Pulse Open 159–159 min Pulse Open 160–191 Open 3 192–223 Strobe Ran 224–255 Open 4
13	Dimmer	0	
14	Dimmer Fine	0	Fine byte of Dimmer
15	Function	0	0–69 No Feature 1 70–79 Black out Pan Tilt Move Enable 80–89 Black out Pan Tilt Move Disable 90–139 No Feature 2 140–149 PT Reset 150–169 No Feature 2 170–179 Zoom Reset 180–199 No Feature 4 200–209 All Reset 218–255 No Feature 5