ADJ

Entour Faze



Manufacturer	**ADJ**
Type	**Hazer**
DMX modes	**3**
DMX footprint	**1, 2, 4 channels**
Size (W × H × D)	**530 × 380 × 380 mm**
GDTF fixture type	**CBDB82A6-73C1-4907-9485-5E…**

Controls

Fan · Haze or smoke output

Safety-relevant functions

Haze or smoke output

DMX modes

1 Channel Mode	1 ch
2 Channel Mode	2 ch
4 Channel Mode	4 ch

1 Channel Mode

1 channel

Ch	Function	Default	DMX values
1	Haze	0	0–0 No Output Volume 1–255 100 percent output

2 Channel Mode

2 channels

Ch	Function	Default	DMX values
1	Haze	0	0–0 No Output Volume 1–255 100 percent output
2	Fan	0	0–127 0 percent Speed 128–255 1 to 100 percent Speed

4 Channel Mode

4 channels

Ch	Function	Default	DMX values
1	Haze	0	0–0 No Output Volume 1–255 100 percent Output Volume
2	Fan	0	0–127 0 percent Speed 128–255 1 to 100 percent Speed
3	Duration	0	0–9 0 seconds 10–255 10-255 Seconds
4	Interval	0	0–9 0 Seconds 10–255 9-250 Seconds