ADJ

MDF2



Manufacturer	**ADJ**
Type	**PAR**
DMX modes	**3**
DMX footprint	**5, 7, 10 channels**
Beam angle	**25°**
Size (W × H × D)	**600 × 72 × 600 mm**
GDTF fixture type	**20E54693-C552-479B-9776-502…**

Controls

RGB colour mixing · Colour wheel · Dimmer

DMX modes

Mode 5CH	5 ch
Mode 7CH	7 ch
Mode 10CH	10 ch

Mode 5CH

5 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	Dimmer	0	0–254 Closed 255–255 Open
5	Dimmer Fine	0	Fine byte of Dimmer

Mode 7CH

7 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	Color Macro1	0	1–7 R02 Bastard Amber (wheel slot 1) 8–15 R04 Medium Amber (wheel slot 2) 16–23 R09 Pale Amber Gold (wheel slot 3) 24–31 R316 Gallo Gold (wheel slot 4) 32–39 R21 Golden Amber (wheel slot 5) 40–47 R26 Light Red (wheel slot 6) 48–55 R27 Medium Red (wheel slot 7) 56–63 R36 Medium Pink (wheel slot 8) 64–71 R339 Broadway Pink (wheel slot 9) 72–79 R344 Follies Pink (wheel slot 10) 80–87 R52 Light Lavender (wheel slot 11) 88–95 R54 Special Lavender (wheel slot 12) 96–103 R57 Lavender (wheel slot 13) 104–111 R59 Indigo (wheel slot 14) 112–119 R361 Hemsley Blue (wheel slot 15) 120–127 R362 Tipton Blue (wheel slot 16) 128–135 R64 Light Steel Blue (wheel slot 17) 136–143 R67 Light Sky Blue (wheel slot 18) 144–151 R68 Sky Blue (wheel slot 19) 152–159 R69 Brilliant Blue (wheel slot 20) 160–167 R76 Light Green Blue (wheel slot 21) 168–175 R79 Bright Blue (wheel slot 22) 176–183 R80 Primary Blue (wheel slot 23) 184–191 R382 Congo Blue (wheel slot 24) 192–199 R87 Pale Yellow Green (wheel slot 25) 200–207 R89 Moss Green (wheel slot 26) 208–215 R91 Primary Green (wheel slot 27) 216–223 L200 Double CTB (wheel slot 28) 224–231 L201 Full CTB (wheel slot 29) 232–239 L202 Half CTB (wheel slot 30) 240–247 L119 Dark Blue (wheel slot 31) 248–255 White (wheel slot 32)
5	Strobe Mode Strobe	0	0–31 Off 32–63 On 64–95 Variable_slow_to_fast 96–127 On 128–159 Pulse_slow_to_fast 160–191 On 192–223 Random_slow_to_fast 224–255 On
6	Dimmer	0	0–254 Closed 255–255 Open
7	Dimmer Fine	0	Fine byte of Dimmer

Mode 10CH

10 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	Color Macro1	0	1–7 R02 Bastard Amber (wheel slot 1) 8–15 R04 Medium Amber (wheel slot 2) 16–23 R09 Pale Amber Gold (wheel slot 3) 24–31 R316 Gallo Gold (wheel slot 4) 32–39 R21 Golden Amber (wheel slot 5) 40–47 R26 Light Red (wheel slot 6) 48–55 R27 Medium Red (wheel slot 7) 56–63 R36 Medium Pink (wheel slot 8) 64–71 R339 Broadway Pink (wheel slot 9) 72–79 R344 Follies Pink (wheel slot 10) 80–87 R52 Light Lavender (wheel slot 11) 88–95 R54 Special Lavender (wheel slot 12) 96–103 R57 Lavender (wheel slot 13) 104–111 R59 Indigo (wheel slot 14) 112–119 R361 Hemsley Blue (wheel slot 15) 120–127 R362 Tipton Blue (wheel slot 16) 128–135 R64 Light Steel Blue (wheel slot 17) 136–143 R67 Light Sky Blue (wheel slot 18) 144–151 R68 Sky Blue (wheel slot 19) 152–159 R69 Brilliant Blue (wheel slot 20) 160–167 R76 Light Green Blue (wheel slot 21) 168–175 R79 Bright Blue (wheel slot 22) 176–183 R80 Primary Blue (wheel slot 23) 184–191 R382 Congo Blue (wheel slot 24) 192–199 R87 Pale Yellow Green (wheel slot 25) 200–207 R89 Moss Green (wheel slot 26) 208–215 R91 Primary Green (wheel slot 27) 216–223 L200 Double CTB (wheel slot 28) 224–231 L201 Full CTB (wheel slot 29) 232–239 L202 Half CTB (wheel slot 30) 240–247 L119 Dark Blue (wheel slot 31) 248–255 White (wheel slot 32)
5	Strobe Mode Strobe	0	0–31 Off 32–63 On 64–95 Variable_slow_to_fast 96–127 On 128–159 Pulse_slow_to_fast 160–191 On 192–223 Random_slow_to_fast 224–255 On
6	Dimmer	0	0–254 Closed 255–255 Open
7	Dimmer Fine	0	Fine byte of Dimmer
8	Dimmer Mode	0	
9	Color Effects1	0	0–10 Maintain 11–60 Random_change 61–110 Color_jump 111–160 Color_gradient 161–210 Color_pulse 211–255 Sound_control
10	Color Mix MSpeed	0	