AML Lighting

AL-005BIP Thunder Strobe 60



Manufacturer	**AML Lighting**
Type	**Strobe**
DMX modes	**6**
DMX footprint	**4, 8, 12, 15 channels**
Beam angle	**25°**
Heads / cells	**2**
Size (W × H × D)	**510 × 230 × 198 mm**
GDTF fixture type	**35F60C95-A57F-4CC0-A0E5-83…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer · Pixel control

Safety-relevant functions

Built-in effect programmes

DMX modes

4CH RGBW	4 ch
4CH Strobe	4 ch
244CH	8 ch
44CH	8 ch
12CH	12 ch
15CH	15 ch

4CH RGBW

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

4CH Strobe

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Duration	0	
3	Strobe Rate	0	
4	Shutter / Strobe	0	0–5 Shutter1 1 6–255 Shutter1Strobe 2

244CH

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Duration	0	
3	Strobe Rate	0	
4	Shutter / Strobe	0	0–5 Shutter1 1 6–255 Shutter1Strobe 2
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	0	

44CH

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Duration	0	
3	Strobe Rate	0	
4	Shutter / Strobe	0	0–5 Shutter1 1 6–255 Shutter1Strobe 2
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	0	

12CH

12 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Strobe Duration	0	
3	Strobe Rate	0	

12CH (continued)

Ch	Function	Default	DMX values
4	Shutter / Strobe	0	0–5 Shutter1 1 6–255 Shutter1Strobe 2
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	0	
9	Effect	0	
10	Effect 2	0	
11	Color Macro1	0	
12	Color Macro1Rate	0	

15CH

15 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–5 Shutter1 1 6–255 Shutter1Strobe 2
3	Red	255	
4	Green	255	
5	Blue	255	
6	White	0	
7	Dimmer	0	
8	Shutter / Strobe	0	0–5 Shutter1 1 6–255 Shutter1Strobe 2
9	Red	255	
10	Green	255	
11	Blue	255	
12	White	0	
13	Color Macro1	0	
14	Color Macro1Rate	0	
15	Control1	0	0–51 Menu Set 52–101 Mode Off 102–152 Mode 1 153–203 Mode 2 204–255 Mode 3