Antari

CH-1 Cinema Haze Machine



Manufacturer	**Antari**
Type	**Hazer**
DMX modes	**3**
DMX footprint	**1, 3, 5 channels**
Size (W × H × D)	**579 × 311 × 164 mm**
GDTF fixture type	**CF10FBEC-6664-4A09-9CE8-54…**

Controls

Fan · Haze or smoke output

Safety-relevant functions

Haze or smoke output

DMX modes

1 Channel Mode	1 ch
3 Channel Mode	3 ch
5 Channel Mode	5 ch

1 Channel Mode

1 channel

Ch	Function	Default	DMX values
1	Haze	0	0–4 No Output 5–255 Output Level

3 Channel Mode

3 channels

Ch	Function	Default	DMX values
1	Haze	0	0–4 No Output 5–255 Output Level
2	Fan	0	0–4 No Fan Level 5–255 Fan Level
3	Heater	0	0–127 Heater Off 128–255 Heater On

5 Channel Mode

5 channels

Ch	Function	Default	DMX values
1	Haze	0	0–4 No Output 5–255 Output Level
2	Fan	0	0–4 Fan Off 5–255 Fan Level
3	Heater	0	0–127 Heater Off 128–255 Heater On
4	Operation Mode	0	0–127 DMX 128–192 Timer 1 193–255 Timer 2
5	Cleaning	0	0–127 Off 128–255 On