Antari

M-7 RGBA



Manufacturer	**Antari**
Type	**Smoke machine**
DMX modes	**1**
DMX footprint	**9 channels**
Beam angle	**25°**
Size (W × H × D)	**193 × 446 × 405 mm**
GDTF fixture type	**C6F7EFBD-D7D6-4277-AC29-88…**

Controls

Haze or smoke output · Extra LED colours · RGB colour mixing · Dimmer

Safety-relevant functions

Haze or smoke output

DMX modes

9ch	9 ch

9ch

9 channels

Ch	Function	Default	DMX values
1	Fog	0	0–254 0% 255–255 100%
2	Red	255	
3	Green	255	
4	Blue	255	
5	Color Add RY	255	
6	Chase	0	0–0 No Chase 1–15 Chase 1 16–31 Chase 2 32–47 Chase 3 48–63 Chase 4 64–79 Chase 5 80–95 Chase 6 96–111 Chase 7 112–127 Chase 8 128–143 Chase 9 144–159 Chase 10 160–175 Chase 11 176–191 Chase 12 192–207 Chase 13 208–223 Chase 14 224–255 Chase 15
7	Chase Speed	0	
8	Dimmer	0	
9	Shutter1Strobe	0	