Antari

m-9 RGBAW



Manufacturer	**Antari**
Type	**Smoke machine**
DMX modes	**1**
DMX footprint	**25 channels**
Beam angle	**25°**
Size (W × H × D)	**393 × 420 × 321 mm**
GDTF fixture type	**64B6A5CC-CA68-4F26-8FA2-32…**

Controls

Haze or smoke output · Extra LED colours · RGB colour mixing · Dimmer

Safety-relevant functions

Haze or smoke output · Built-in effect programmes

DMX modes

25 Channel Mode — 25 ch

25 Channel Mode

25 channels

Ch	Function	Default	DMX values
1	Fog	0	0–4 Fog Off 5–255 Fog On
2	Color RGBRed	0	
3	Color RGBGreen	0	
4	Color RGBBlue	0	
5	Color Add RY	0	
6	White	0	
7	Color RGBRed	0	
8	Color RGBGreen	0	
9	Color RGBBlue	0	
10	Color Add RY	0	
11	White	0	
12	Color RGBRed	0	
13	Color Add GC	0	
14	Color RGBBlue	0	
15	Color Add RY	0	
16	White	0	
17	Color RGBRed	0	
18	Color RGBGreen	0	
19	Color RGBBlue	0	
20	Color Add RY	0	
21	White	0	
22	Effect	0	0–30 Chase 1 31–60 Chase 2 61–90 Chase 3 91–120 Chase 4 121–150 Chase 5 151–180 Chase 6 181–210 Chase 7 211–255 Chase 8
23	Intensity MSpeed	0	
24	Dimmer	0	
25	Shutter1Strobe	0	