Anzhee

Profile 100 ZOOM RGBAL



Manufacturer	**Anzhee**
Type	**Profile spot**
DMX modes	**2**
DMX footprint	**6, 12 channels**
Beam angle	**19°**
Size (W × H × D)	**270 × 608 × 430 mm**
GDTF fixture type	**959D08FF-807A-577B-9F2A-21…**

Controls

Extra LED colours · RGB colour mixing · Colour temperature · Colour wheel · Strobe · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

6CH	6 ch
12CH	12 ch

6CH

6 channels

Ch	Function	Default	DMX values
1	H SBHue	0	
2	H SBSaturation	0	
3	Dimmer	0	
4	Dimmer Fine	0	Fine byte of Dimmer
5	C TC	0	0–0 CCT off (assumed) 1–255 CCT 1800K-10000K (table p11)
6	Shutter / Strobe	0	0–0 Strobe off (assumed) 1–255 Strobe frequency slow -> fast 1–20 Hz

12CH

12 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	Color Add RY	0	
5	Color Add GY	0	
6	Color Macro1	0	0–0 No macro (assumed) 1–255 Colour macros (not listed in the manual)
7	C TC	0	0–0 CCT off (assumed) 1–255 CCT 1800K-10000K (table p11)
8	Effect	0	0–9 Auto modes off (printed «Нет функции») 10–127 Dimmer smoothing 128–134 Auto modes off (printed «Нет функции») 135–255 Auto modes
9	Shutter / Strobe	0	0–9 Strobe off (printed «Нет функции») 10–255 Strobe slow -> fast 1–20 Hz
10	Dimmer Curve	0	0–63 Dimmer curve 1 64–127 Dimmer curve 2 128–191 Dimmer curve 3 192–255 Dimmer curve 4
11	Dimmer	0	
12	Dimmer Fine	0	Fine byte of Dimmer

Fixture model: gdtf-anzhee-profile-100-zoom-rgbal-2611110701
Original HitLight geometry, scripted locally by the HitLight fixture agent from the manufacturer manual's published dimension drawing and pr…
Creator: HitLight