Arena Luci

Stage X F Motor zoom



Manufacturer	**Arena Luci**
Type	**Spot**
DMX modes	**4**
DMX footprint	**1, 2, 3, 4 channels**
Beam angle	**10-71°**
Size (W × H × D)	**231 × 273 × 106 mm**
GDTF fixture type	**2159E679-025A-4FF8-B5B1-ED…**

Controls

Zoom · Strobe · Dimmer

DMX modes

Mode 1	1 ch
Mode 3	2 ch
Mode 2	3 ch
Mode 4	4 ch

Mode 1

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open

Mode 3

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Zoom	0	0–254 Narrow 255–255 Wide

Mode 2

3 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer Fine	0	Fine byte of Dimmer
3	Shutter / Strobe	9	0–9 Open 10–254 Strobe · Slow 0.5–14.9 Hz 255–255 Strobe · Fast 15 Hz

Mode 4

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer Fine	0	Fine byte of Dimmer
3	Shutter / Strobe	9	0–9 Open 10–254 Strobe · Slow 0.5–14.9 Hz 255–255 Strobe · Fast 15 Hz
4	Zoom	0	0–254 Narrow 255–255 Wide