Ayrton

Arcaline 2 3G 1M



Manufacturer	**Ayrton**
Type	**PAR**
DMX modes	**6**
DMX footprint	**4, 5, 7, 8, 9, 11 channels**
Beam angle	**10°**
Heads / cells	**2**
Size (W × H × D)	**1002 × 134 × 134 mm**
GDTF fixture type	**AAE1A082-1829-41A2-914C-2F…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Dimmer · Pixel control

DMX modes

Mode 1	4 ch
Mode 2	5 ch
Mode 3	7 ch
Mode 4	8 ch
Mode 5	9 ch
Mode 6	11 ch

Mode 1

4 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	255	

Mode 2

5 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	255	
5	Dimmer	0	0–254 Closed 255–255 Open

Mode 3

7 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	255	
5	Shutter1Strobe	0	0–15 LED ON 16–242 Shutter1Strobe 1 243–255 LED ON 1
6	Color Macro1	0	
7	Dimmer	0	0–254 Closed 255–255 Open

Mode 4

8 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	255	
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	255	

Mode 5

9 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	

Mode 5 (continued)

Ch	Function	Default	DMX values
4	White	255	
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	255	
9	Dimmer	0	0–254 Closed 255–255 Open

Mode 6

11 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	255	
5	Red	0	
6	Green	0	
7	Blue	0	
8	White	255	
9	Shutter1Strobe	0	0–15 LED ON 16–242 Shutter1Strobe 1 243–255 LED ON 1
10	Color Macro1	0	
11	Dimmer	0	0–254 Closed 255–255 Open