BeamZ

# BBP59



| | |
|---|---|
| Manufacturer | **BeamZ** |
| Type | **PAR** |
| DMX modes | **2** |
| DMX footprint | **6, 12 channels** |
| Beam angle | **25°** |
| Size (W × H × D) | **100 × 150 × 100 mm** |
| GDTF fixture type | **809522ED-E34A-43EB-9B29-46…** |

## Controls

Extra LED colours · RGB colour mixing · Colour wheel · Effect speed · Dimmer

## DMX modes

| | |
|---|---|
| 6 channel mode | 6 ch |
| 12 channel mode | 12 ch |

## 6 channel mode

6 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Red | 0 | |
| 2 | Green | 0 | |
| 3 | Blue | 0 | |
| 4 | White | 0 | |
| 5 | Color Add RY | 0 | |
| 6 | UV | 0 | |

## 12 channel mode

12 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Dimmer | 0 | |
| 2 | Red | 0 | |
| 3 | Green | 0 | |
| 4 | Blue | 0 | |
| 5 | White | 0 | |
| 6 | Color Add RY | 0 | |
| 7 | UV | 0 | |
| 8 | Shutter1Strobe | 0 | 0–4 no function<br>5–255 strobe slow to fast |
| 9 | Color Macro1 | 0 | 0–7 no fuction<br>8–127 40 preset colors<br>128–255 64 preset colors |
| 10 | Playmode | 0 | 0–19 no fucntion<br>20–127 18 chases<br>128–159 63 color fade<br>160–191 63 color jump<br>192–223 63 color pulse<br>224–255 sound control |
| 11 | Effect Speed | 0 | |
| 12 | Dimmer Curve | 0 | 0–5 control panel<br>6–55 dimmer curve 0<br>56–105 dimmer curve 1<br>106–155 dimmer curve 2<br>156–205 dimmer curve 3<br>206–255 dimmer curve 4 |