BeamZ

Blaze 1200



Manufacturer	**BeamZ**
Type	**Smoke machine**
DMX modes	**1**
DMX footprint	**8 channels**
Beam angle	**25°**
Size (W × H × D)	**410 × 210 × 270 mm**
GDTF fixture type	**45266794-A35F-416E-971F-1D…**

Controls

Haze or smoke output · Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer

Safety-relevant functions

Haze or smoke output

DMX modes

Standard	8 ch

Standard

8 channels

Ch	Function	Default	DMX values
1	Fog	0	0–254 No Fog 255–255 Max Fog
2	Dimmer	0	0–254 Closed 255–255 Open
3	Red	255	
4	Green	255	
5	Blue	255	
6	Color Add RY	255	
7	Shutter / Strobe	0	0–0 Open 1–254 Strobe Frequency · min 1–19.9 Hz 255–255 Strobe Frequency · max 20 Hz
8	Color Macro1	0	