BOS Lighting

Fresnel 200 Bi Color



Manufacturer	**BOS Lighting**
Type	**Spot**
DMX modes	**4**
DMX footprint	**1, 2, 4, 7 channels**
Beam angle	**25°**
Size (W × H × D)	**596 × 597 × 597 mm**
GDTF fixture type	**EB1326EC-EC0A-418C-A9CD-41…**

Controls

Extra LED colours · Colour temperature · Strobe · Dimmer

Safety-relevant functions

Strobe

DMX modes

1ch	1 ch
2ch	2 ch
4ch	4 ch
7ch	7 ch

1ch

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open

2ch

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	C TC	255	0–254 2200 K 255–255 5200 K

4ch

4 channels

Ch	Function	Default	DMX values
1	Color Add WW	0	
2	Color Add CW	0	
3	C TC	255	0–254 2200 K 255–255 5200 K
4	Dimmer	0	0–254 Closed 255–255 Open

7ch

7 channels

Ch	Function	Default	DMX values
1	Color Add WW	0	
2	Color Add CW	0	
3	C TC	255	0–254 2200 K 255–255 5200 K
4	Shutter / Strobe	0	0–10 No function 11–254 slow 255–255 fast
5	Dimmer Curve	0	
6	Dimmer	0	0–254 Closed 255–255 Open
7	Dimmer Fine	0	Fine byte of Dimmer