Cameo

Steam Wizard 2000



Manufacturer	**Cameo**
Type	**Smoke machine**
DMX modes	**1**
DMX footprint	**4 channels**
Beam angle	**25°**
Size (W × H × D)	**421 × 191 × 309 mm**
GDTF fixture type	**83E36086-BD3A-4D1D-8F5C-B9…**

Controls

Haze or smoke output · Colour wheel · Strobe · Dimmer

Safety-relevant functions

Haze or smoke output

DMX modes

4 Chan Mode — 4 ch

4 Chan Mode

4 channels

Ch	Function	Default	DMX values
1	Fog	0	0–0 No Fog 1–252 min Fog 253–255 max Fog
2	Dimmer	0	0–24 0% 25–50 10% 51–62 20% 63–75 25% 76–101 30% 102–126 40% 127–152 50% 153–177 60% 178–190 70% 191–203 75% 204–228 80% 229–254 90% 255–255 100%
3	Shutter / Strobe	0	0–5 Open 6–128 Strobe · Str Slow 1–15.2 Hz 129–252 Strobe · Str Medium 15.3–29.7 Hz 253–255 Strobe · Str Fast 29.8–30 Hz
4	Color Wheel	90	0–5 Color Off (wheel slot 1) 6–13 Red (wheel slot 2) 14–21 Green (wheel slot 3) 22–29 Blue (wheel slot 4) 30–37 Amber (wheel slot 5) 38–45 Red-Green (wheel slot 6) 46–53 Red-Blue (wheel slot 7) 54–61 Red-Amber (wheel slot 8) 62–69 Green-Blue (wheel slot 9) 70–77 Green-Amber (wheel slot 10) 78–85 Blue-Amber (wheel slot 11) 86–93 Red-Green-Blue (wheel slot 12) 94–101 Red-Green-Amber (wheel slot 13) 102–109 Red-Green-Blue-Amber (wheel slot 14) 110–117 Green-Blue-Amber (wheel slot 15) 118–125 Red-Green-Blue-Amber (wheel slot 16) 126–127 Color Jumping Stop (wheel slot 17) 128–191 Color Jumping Slow -> Fast (wheel slot 18) 192–255 Color Fading Slow -> Fast (wheel slot 19)