Chauvet Professional

COLORado 1 Quad Zoom



Manufacturer	**Chauvet Professional**
Type	**Effect light**
DMX modes	**12**
DMX footprint	**3, 4, 5, 6, 7, 10, 12, 17, 25 channels**
Beam angle	**13-45°**
Heads / cells	**2**
Size (W × H × D)	**236 × 318 × 194 mm**
GDTF fixture type	**252B6D62-AE3C-4ED3-81CD-74…**

Controls

Zoom · Extra LED colours · Hue and saturation · RGB colour mixing · Colour wheel · Effect speed · Strobe · Dimmer · Pixel control

Safety-relevant functions

Fixture reset · Built-in effect programmes

DMX modes

ARC 1	3 ch
HSV	3 ch
AR1 D	4 ch
ARC 2	4 ch
AR2 D	5 ch
AR2 S	6 ch
AR2 Z	7 ch
C1Q	10 ch
TOUR	12 ch
STD Y	17 ch
TR16	17 ch
Full	25 ch

ARC 1

3 channels

Ch	Function	Default	DMX values
1	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
2	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max

HSV

3 channels

Ch	Function	Default	DMX values
1	H SBHue	0	0–0 Min 1–254 Min > Max 255–255 Max
2	H SBSaturation	0	0–0 Min 1–254 Min > Max 255–255 Max
3	H SBBrightness	0	0–0 Min 1–254 Min > Max 255–255 Max

AR1 D

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max

ARC 2

4 channels

Ch	Function	Default	DMX values
1	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
2	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
4	White	255	0–0 Min 1–254 Min > Max 255–255 Max

AR2 D

5 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
5	White	255	0–0 Min 1–254 Min > Max 255–255 Max

AR2 S

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
5	White	255	0–0 Min 1–254 Min > Max 255–255 Max
6	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 0-20Hz - Strobe

AR2 Z

7 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max

AR2 Z (continued)

Ch	Function	Default	DMX values
5	White	255	0–0 Min 1–254 Min > Max 255–255 Max
6	Zoom	127	0–0 Narrow 1–254 Narrow > Wide 255–255 Wide
7	Zoom Mode	0	0–200 No Func - Custom 201–220 Zoom Reset - Reset 221–255 No Func - Custom

C1Q

10 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
5	White	255	0–0 Min 1–254 Min > Max 255–255 Max
6	Color Macro1	0	0–10 No Func - Custom 11–30 R:100% G:0-100% B:0 - Color (wheel slot 1) 31–50 R:100%-0 G:100% B:0 - Color (wheel slot 2) 51–70 R:0 G:100% B:0-100% - Color (wheel slot 3) 71–90 R:0 G:100%-0 B:100% - Color (wheel slot 4) 91–110 R:0-100% G:0 B:100% - Color (wheel slot 5) 111–130 R:100% G:0 B:100%-0 - Color (wheel slot 6) 131–150 R:100% G:0-100% B:0-100% - Color (wheel slot 7) 151–170 R:100%-0 G:0-100%-0 B:100% - Color (wheel slot 8) 171–200 RGBW:100% - Color (wheel slot 9) 201–205 White 1 - Color (wheel slot 10) 206–210 White 2 - Color (wheel slot 11) 211–215 White 3 - Color (wheel slot 12) 216–220 White 4 - Color (wheel slot 13) 221–225 White 5 - Color (wheel slot 14) 226–230 White 6 - Color (wheel slot 15) 231–235 White 7 - Color (wheel slot 16) 236–240 White 8 - Color (wheel slot 17) 241–245 White 9 - Color (wheel slot 18) 246–250 White 10 - Color (wheel slot 19) 251–255 White 11 - Color (wheel slot 20)
7	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 0-20Hz - Strobe

C1Q (continued)

Ch	Function	Default	DMX values
8	Effect	0	0–40 No Func - Custom 41–50 Auto 1 - Macro 51–60 Auto 2 - Macro 61–70 Auto 3 - Macro 71–80 Auto 4 - Macro 81–90 Auto 5 - Macro 91–100 Auto 6 - Macro 101–110 Auto 7 - Macro 111–120 Auto 8 - Macro 121–130 Auto 9 - Macro 131–140 Auto 10 - Macro 141–150 Custom 1 - Macro 151–160 Custom 2 - Macro 161–170 Custom 3 - Macro 171–180 Custom 4 - Macro 181–190 Custom 5 - Macro 191–200 Custom 6 - Macro 201–210 Custom 7 - Macro 211–220 Custom 8 - Macro 221–230 Custom 9 - Macro 231–255 Custom 10 - Macro
9	Effect Speed	0	0–0 Min 1–254 Min > Max 255–255 Max
10	Intensity MSpeed	0	0–9 Preset Dim Spd Fr Disp Menu - Speed 10–29 Linear Dimmer - Speed 30–69 Nonlinear Dim Curve 1 (Fastest) - Speed 70–129 Nonlinear Dim Curve 2 - Speed 130–189 Nonlinear Dim Curve 3 - Speed 190–255 Nonlinear Dim Curve 4 (Slowest) - Speed

TOUR

12 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Red	255	0–0 Min 1–254 Min > Max 255–255 Max
3	Green	255	0–0 Min 1–254 Min > Max 255–255 Max
4	Blue	255	0–0 Min 1–254 Min > Max 255–255 Max
5	White	255	0–0 Min 1–254 Min > Max 255–255 Max

TOUR (continued)

Ch	Function	Default	DMX values
6	Color Macro1	0	0–10 No Func - Custom 11–30 R:100% G:0-100% B:0 - Color (wheel slot 1) 31–50 R:100%-0 G:100% B:0 - Color (wheel slot 2) 51–70 R:0 G:100% B:0-100% - Color (wheel slot 3) 71–90 R:0 G:100%-0 B:100% - Color (wheel slot 4) 91–110 R:0-100% G:0 B:100% - Color (wheel slot 5) 111–130 R:100% G:0 B:100%-0 - Color (wheel slot 6) 131–150 R:100% G:0-100% B:0-100% - Color (wheel slot 7) 151–170 R:100%-0 G:0-100%-0 B:100% - Color (wheel slot 8) 171–200 RGBW:100% - Color (wheel slot 9) 201–205 White 1 - Color (wheel slot 10) 206–210 White 2 - Color (wheel slot 11) 211–215 White 3 - Color (wheel slot 12) 216–220 White 4 - Color (wheel slot 13) 221–225 White 5 - Color (wheel slot 14) 226–230 White 6 - Color (wheel slot 15) 231–235 White 7 - Color (wheel slot 16) 236–240 White 8 - Color (wheel slot 17) 241–245 White 9 - Color (wheel slot 18) 246–250 White 10 - Color (wheel slot 19) 251–255 White 11 - Color (wheel slot 20)
7	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 0-20Hz - Strobe
8	Effect	0	0–40 No Func - Custom 41–50 Auto 1 - Macro 51–60 Auto 2 - Macro 61–70 Auto 3 - Macro 71–80 Auto 4 - Macro 81–90 Auto 5 - Macro 91–100 Auto 6 - Macro 101–110 Auto 7 - Macro 111–120 Auto 8 - Macro 121–130 Auto 9 - Macro 131–140 Auto 10 - Macro 141–150 Custom 1 - Macro 151–160 Custom 2 - Macro 161–170 Custom 3 - Macro 171–180 Custom 4 - Macro 181–190 Custom 5 - Macro 191–200 Custom 6 - Macro 201–210 Custom 7 - Macro 211–220 Custom 8 - Macro 221–230 Custom 9 - Macro 231–255 Custom 10 - Macro
9	Effect Speed	0	0–0 Min 1–254 Min > Max 255–255 Max
10	Intensity MSpeed	0	0–9 Preset Dim Spd Fr Disp Menu - Speed 10–29 Linear Dimmer - Speed 30–69 Nonlinear Dim Curve 1 (Fastest) - Speed 70–129 Nonlinear Dim Curve 2 - Speed 130–189 Nonlinear Dim Curve 3 - Speed 190–255 Nonlinear Dim Curve 4 (Slowest) - Speed
11	Zoom	127	0–0 Narrow 1–254 Narrow > Wide 255–255 Wide
12	Zoom Mode	0	0–200 No Func - Custom 201–220 Zoom Reset - Reset 221–255 No Func - Custom

STD Y

17 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Red Fine	255	Fine byte of Red
5	Green	255	
6	Green Fine	255	Fine byte of Green
7	Blue	255	
8	Blue Fine	255	Fine byte of Blue
9	White	255	
10	White Fine	255	Fine byte of White
11	Color Macro1	0	0–10 No Func - Custom 11–30 R:100% G:0-100% B:0 - Color (wheel slot 1) 31–50 R:100%-0 G:100% B:0 - Color (wheel slot 2) 51–70 R:0 G:100% B:0-100% - Color (wheel slot 3) 71–90 R:0 G:100%-0 B:100% - Color (wheel slot 4) 91–110 R:0-100% G:0 B:100% - Color (wheel slot 5) 111–130 R:100% G:0 B:100%-0 - Color (wheel slot 6) 131–150 R:100% G:0-100% B:0-100% - Color (wheel slot 7) 151–170 R:100%-0 G:0-100%-0 B:100% - Color (wheel slot 8) 171–200 RGBW:100% - Color (wheel slot 9) 201–205 White 1 - Color (wheel slot 10) 206–210 White 2 - Color (wheel slot 11) 211–215 White 3 - Color (wheel slot 12) 216–220 White 4 - Color (wheel slot 13) 221–225 White 5 - Color (wheel slot 14) 226–230 White 6 - Color (wheel slot 15) 231–235 White 7 - Color (wheel slot 16) 236–240 White 8 - Color (wheel slot 17) 241–245 White 9 - Color (wheel slot 18) 246–250 White 10 - Color (wheel slot 19) 251–255 White 11 - Color (wheel slot 20)
12	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 0-20Hz - Strobe
13	Effect	0	0–40 No Func - Custom 41–50 Auto 1 - Macro 51–60 Auto 2 - Macro 61–70 Auto 3 - Macro 71–80 Auto 4 - Macro 81–90 Auto 5 - Macro 91–100 Auto 6 - Macro 101–110 Auto 7 - Macro 111–120 Auto 8 - Macro 121–130 Auto 9 - Macro 131–140 Auto 10 - Macro 141–150 Custom 1 - Macro 151–160 Custom 2 - Macro 161–170 Custom 3 - Macro 171–180 Custom 4 - Macro 181–190 Custom 5 - Macro 191–200 Custom 6 - Macro 201–210 Custom 7 - Macro 211–220 Custom 8 - Macro 221–230 Custom 9 - Macro 231–255 Custom 10 - Macro
14	Effect Speed	0	0–0 Min 1–254 Min > Max 255–255 Max

STD Y (continued)

Ch	Function	Default	DMX values
15	Intensity MSpeed	0	0–9 Preset Dim Spd Fr Disp Menu - Speed 10–29 Linear Dimmer - Speed 30–69 Nonlinear Dim Curve 1 (Fastest) - Speed 70–129 Nonlinear Dim Curve 2 - Speed 130–189 Nonlinear Dim Curve 3 - Speed 190–255 Nonlinear Dim Curve 4 (Slowest) - Speed
16	Zoom	127	0–0 Narrow 1–254 Narrow > Wide 255–255 Wide
17	Zoom Mode	0	0–200 No Func - Custom 201–220 Zoom Reset - Reset 221–255 No Func - Custom

TR16

17 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Red Fine	255	Fine byte of Red
5	Green	255	
6	Green Fine	255	Fine byte of Green
7	Blue	255	
8	Blue Fine	255	Fine byte of Blue
9	White	255	
10	White Fine	255	Fine byte of White
11	Color Macro1	0	0–10 No Func - Custom 11–30 R:100% G:0-100% B:0 - Color (wheel slot 1) 31–50 R:100%-0 G:100% B:0 - Color (wheel slot 2) 51–70 R:0 G:100% B:0-100% - Color (wheel slot 3) 71–90 R:0 G:100%-0 B:100% - Color (wheel slot 4) 91–110 R:0-100% G:0 B:100% - Color (wheel slot 5) 111–130 R:100% G:0 B:100%-0 - Color (wheel slot 6) 131–150 R:100% G:0-100% B:0-100% - Color (wheel slot 7) 151–170 R:100%-0 G:0-100%-0 B:100% - Color (wheel slot 8) 171–200 RGBW:100% - Color (wheel slot 9) 201–205 White 1 - Color (wheel slot 10) 206–210 White 2 - Color (wheel slot 11) 211–215 White 3 - Color (wheel slot 12) 216–220 White 4 - Color (wheel slot 13) 221–225 White 5 - Color (wheel slot 14) 226–230 White 6 - Color (wheel slot 15) 231–235 White 7 - Color (wheel slot 16) 236–240 White 8 - Color (wheel slot 17) 241–245 White 9 - Color (wheel slot 18) 246–250 White 10 - Color (wheel slot 19) 251–255 White 11 - Color (wheel slot 20)
12	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 0-20Hz - Strobe

TR16 (continued)

Ch	Function	Default	DMX values
13	Effect	0	0–40 No Func - Custom 41–50 Auto 1 - Macro 51–60 Auto 2 - Macro 61–70 Auto 3 - Macro 71–80 Auto 4 - Macro 81–90 Auto 5 - Macro 91–100 Auto 6 - Macro 101–110 Auto 7 - Macro 111–120 Auto 8 - Macro 121–130 Auto 9 - Macro 131–140 Auto 10 - Macro 141–150 Custom 1 - Macro 151–160 Custom 2 - Macro 161–170 Custom 3 - Macro 171–180 Custom 4 - Macro 181–190 Custom 5 - Macro 191–200 Custom 6 - Macro 201–210 Custom 7 - Macro 211–220 Custom 8 - Macro 221–230 Custom 9 - Macro 231–255 Custom 10 - Macro
14	Effect Speed	0	0–0 Min 1–254 Min > Max 255–255 Max
15	Intensity MSpeed	0	0–9 Preset Dim Spd Fr Disp Menu - Speed 10–29 Linear Dimmer - Speed 30–69 Nonlinear Dim Curve 1 (Fastest) - Speed 70–129 Nonlinear Dim Curve 2 - Speed 130–189 Nonlinear Dim Curve 3 - Speed 190–255 Nonlinear Dim Curve 4 (Slowest) - Speed
16	Zoom	127	0–0 Narrow 1–254 Narrow > Wide 255–255 Wide
17	Zoom Mode	0	0–200 No Func - Custom 201–220 Zoom Reset - Reset 221–255 No Func - Custom

Full

25 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Red	255	
4	Red Fine	255	Fine byte of Red
5	Green	255	
6	Green Fine	255	Fine byte of Green
7	Blue	255	
8	Blue Fine	255	Fine byte of Blue
9	White	255	
10	White Fine	255	Fine byte of White
11	Red	255	
12	Red Fine	255	Fine byte of Red
13	Green	255	
14	Green Fine	255	Fine byte of Green

Full (continued)

Ch	Function	Default	DMX values
15	Blue	255	
16	Blue Fine	255	Fine byte of Blue
17	White	255	
18	White Fine	255	Fine byte of White
19	Color Macro1	0	0–10 No Func - Custom 11–30 R:100% G:0-100% B:0 - Color (wheel slot 1) 31–50 R:100%-0 G:100% B:0 - Color (wheel slot 2) 51–70 R:0 G:100% B:0-100% - Color (wheel slot 3) 71–90 R:0 G:100%-0 B:100% - Color (wheel slot 4) 91–110 R:0-100% G:0 B:100% - Color (wheel slot 5) 111–130 R:100% G:0 B:100%-0 - Color (wheel slot 6) 131–150 R:100% G:0-100% B:0-100% - Color (wheel slot 7) 151–170 R:100%-0 G:0-100%-0 B:100% - Color (wheel slot 8) 171–200 RGBW:100% - Color (wheel slot 9) 201–205 White 1 - Color (wheel slot 10) 206–210 White 2 - Color (wheel slot 11) 211–215 White 3 - Color (wheel slot 12) 216–220 White 4 - Color (wheel slot 13) 221–225 White 5 - Color (wheel slot 14) 226–230 White 6 - Color (wheel slot 15) 231–235 White 7 - Color (wheel slot 16) 236–240 White 8 - Color (wheel slot 17) 241–245 White 9 - Color (wheel slot 18) 246–250 White 10 - Color (wheel slot 19) 251–255 White 11 - Color (wheel slot 20)
20	Shutter / Strobe	0	0–9 Open - Shutter Open 10–255 0-20Hz - Strobe
21	Effect	0	0–40 No Func - Custom 41–50 Auto 1 - Macro 51–60 Auto 2 - Macro 61–70 Auto 3 - Macro 71–80 Auto 4 - Macro 81–90 Auto 5 - Macro 91–100 Auto 6 - Macro 101–110 Auto 7 - Macro 111–120 Auto 8 - Macro 121–130 Auto 9 - Macro 131–140 Auto 10 - Macro 141–150 Custom 1 - Macro 151–160 Custom 2 - Macro 161–170 Custom 3 - Macro 171–180 Custom 4 - Macro 181–190 Custom 5 - Macro 191–200 Custom 6 - Macro 201–210 Custom 7 - Macro 211–220 Custom 8 - Macro 221–230 Custom 9 - Macro 231–255 Custom 10 - Macro
22	Effect Speed	0	0–0 Min 1–254 Min > Max 255–255 Max
23	Intensity MSpeed	0	0–9 Preset Dim Spd Fr Disp Menu - Speed 10–29 Linear Dimmer - Speed 30–69 Nonlinear Dim Curve 1 (Fastest) - Speed 70–129 Nonlinear Dim Curve 2 - Speed 130–189 Nonlinear Dim Curve 3 - Speed 190–255 Nonlinear Dim Curve 4 (Slowest) - Speed

Full (continued)

Ch	Function	Default	DMX values
24	Zoom	127	0–0 Narrow 1–254 Narrow > Wide 255–255 Wide
25	Zoom Mode	0	0–200 No Func - Custom 201–220 Zoom Reset - Reset 221–255 No Func - Custom