CKC Lighting

PixBar 1204



Manufacturer	**CKC Lighting**
Type	**PAR**
DMX modes	**5**
DMX footprint	**3, 4, 6, 8, 10 channels**
Beam angle	**34°**
Heads / cells	**2**
Size (W × H × D)	**486 × 80 × 55 mm**
GDTF fixture type	**EB68FCE6-F3EF-4C30-B78B-24E…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer · Pixel control

Safety-relevant functions

Strobe

DMX modes

3CH FX Mode	3 ch
4CH RGBW	4 ch
6CH RGBW+D+S	6 ch
8CH 2X RGBW	8 ch
10CH 2X RGBW+D	10 ch

3CH FX Mode

3 channels

Ch	Function	Default	DMX values
1	Color Wheel	0	0–9 Red (wheel slot 1) 10–19 Green (wheel slot 2) 20–29 Blue (wheel slot 3) 30–39 White (wheel slot 4) 40–49 Yellow (wheel slot 5) 50–59 Cyan (wheel slot 6) 60–69 Sky Blue (wheel slot 7) 70–79 Pink (wheel slot 8) 80–89 Light Green (wheel slot 9) 90–99 Magenta (wheel slot 10) 100–109 RGB (wheel slot 11) 110–119 Pale Cyan (wheel slot 12) 120–129 Light Yellow (wheel slot 13) 130–139 Pale Purple (wheel slot 14) 140–149 RGBW (wheel slot 15) 150–159 CFADE 160–169 Meteor 170–179 Fade 180–189 CHANGE 190–199 Flow1 200–209 Flow2 210–219 Flow3 220–229 Flow4 230–239 Flow5 240–255 Flow6
2	Shutter / Strobe	0	0–8 No function 9–254 min strobe 255–255 max strobe
3	Dimmer	0	0–62 0% 63–127 25% 128–191 50% 192–254 75% 255–255 100%

4CH RGBW

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	

6CH RGBW+D+S

6 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	
5	Dimmer	0	0–62 0% 63–127 25% 128–191 50% 192–254 75% 255–255 100%

6CH RGBW+D+S (continued)

Ch	Function	Default	DMX values
6	Shutter / Strobe	0	0–4 No function 5–254 min strobe 255–255 max strobe

8CH 2X RGBW

8 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	
5	Red	255	
6	Green	255	
7	Blue	255	
8	White	255	

10CH 2X RGBW+D

10 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	255	
5	Dimmer	0	0–62 0% 63–127 25% 128–191 50% 192–254 75% 255–255 100%
6	Red	255	
7	Green	255	
8	Blue	255	
9	White	255	
10	Dimmer	0	0–62 0% 63–127 25% 128–191 50% 192–254 75% 255–255 100%