CLF Lighting

XENA



Manufacturer	**CLF Lighting**
Type	**Moving head**
DMX modes	**1**
DMX footprint	**9 channels**
Beam angle	**25°**
Pan range	**360°**
Tilt range	**270°**
Size (W × H × D)	**238 × 260 × 238 mm**
GDTF fixture type	**2C05B46F-A3AF-4DD7-88EF-C8…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer

DMX modes

9ch Standard Mode — 9 ch

9ch Standard Mode

9 channels

Ch	Function	Default	DMX values
1	Shutter / Strobe	22	0–19 Shutter closed 20–24 Shutter open 25–64 Strobe 1 (Fast-Slow) 65–69 Shutter open 70–84 Opening pulse (Fast-Slow) 85–89 Shutter open 90–104 Closing pulse (Fast-Slow) 105–109 Shutter open 110–124 Random strobe (Fast-Slow) 125–129 Shutter open 130–144 Random opening pulse (Fast-Slow) 145–149 Shutter open 150–164 Random closing pulse (Fast-Slow) 165–169 Shutter open 170–184 Burst pulse (Fast-Slow) 185–189 Shutter open 190–204 Random burst pulse (Fast-Slow) 205–209 Shutter open 210–224 Sine wave (Fast-Slow) 225–229 Shutter open 230–244 Sine wave pulse (Fast-Slow) 245–255 Shutter open
2	Dimmer	0	0–254 Closed 255–255 Open
3	Red	255	
4	Green	255	
5	Blue	255	
6	White	255	
7	Color Effects1	0	0–9 No Function 10–174 Color wheel effect 175–179 Open 180–201 Color wheel rotation effect clockwise (fast-slow) 202–207 Stop 208–229 Color wheel rotation effect counter clockwise (fast... 230–234 Open 235–239 Random color Fast 240–244 Random color Medium 245–249 Random color Slow 250–255 Open
8	Color Macro1Rate	0	0–9 No Function 10–255 AUTO COLOR 1 THRU 8
9	Control1	0	