Dea Production

Strobe Bar192



Manufacturer	**Dea Production**
Type	**Strobe**
DMX modes	**5**
DMX footprint	**3, 4, 6, 13 channels**
Beam angle	**25-116°**
Size (W × H × D)	**1000 × 114 × 89 mm**
GDTF fixture type	**8BB19E35-BB50-4FF5-A076-9A…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Dimmer · Pixel control

DMX modes

112CH	3 ch
16CH	3 ch
192CH	4 ch
6CH	6 ch
13CH	13 ch

112CH

3 channels

Ch	Function	Default	DMX values
1	Red	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

16CH

3 channels

Ch	Function	Default	DMX values
1	Red	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

192CH

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

6CH

6 channels

Ch	Function	Default	DMX values
1	Red	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %

6CH (continued)

Ch	Function	Default	DMX values
2	Green	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Dimmer	0	0–62 0 % White 63–126 25 % White 127–190 50 % White 191–254 75 % White 255–255 100 % White
5	Dimmer	0	0–62 0 % Master 63–126 25 % Master 127–190 50 % Master 191–254 75 % Master 255–255 100 % Master
6	Dimmer Fine	0	Fine byte of Dimmer

13CH

13 channels

Ch	Function	Default	DMX values
1	Red	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
2	Green	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
3	Blue	255	0–62 0 % 63–126 25 % 127–190 50 % 191–254 75 % 255–255 100 %
4	Dimmer	0	0–62 0 % White 63–126 25 % White 127–190 50 % White 191–254 75 % White 255–255 100 % White

13CH (continued)

Ch	Function	Default	DMX values
5	Color Wheel	0	0–9 Off (wheel slot 1) 10–17 Color Macro 1 (wheel slot 2) 18–24 Color Macro 2 (wheel slot 3) 25–32 Color Macro 3 (wheel slot 4) 33–39 Color Macro 4 (wheel slot 5) 40–47 Color Macro 5 (wheel slot 6) 48–54 Color Macro 6 (wheel slot 7) 55–61 Color Macro 7 (wheel slot 8) 62–69 Color Macro 8 (wheel slot 9) 70–76 Color Macro 9 (wheel slot 10) 77–84 Color Macro 10 (wheel slot 11) 85–91 Color Macro 11 (wheel slot 12) 92–99 Color Macro 12 (wheel slot 13) 100–106 Color Macro 13 (wheel slot 14) 107–113 Color Macro 14 (wheel slot 15) 114–121 Color Macro 15 (wheel slot 16) 122–128 Color Macro 16 (wheel slot 17) 129–136 Color Macro 17 (wheel slot 18) 137–143 Color Macro 18 (wheel slot 19) 144–151 Color Macro 19 (wheel slot 20) 152–158 Color Macro 20 (wheel slot 21) 159–165 Color Macro 21 (wheel slot 22) 166–173 Color Macro 22 (wheel slot 23) 174–180 Color Macro 23 (wheel slot 24) 181–188 Color Macro 24 (wheel slot 25) 189–195 Color Macro 25 (wheel slot 26) 196–203 Color Macro 26 (wheel slot 27) 204–210 Color Macro 27 (wheel slot 28) 211–217 Color Macro 28 (wheel slot 29) 218–225 Color Macro 29 (wheel slot 30) 226–232 Color Macro 30 (wheel slot 31) 233–240 Color Macro 31 (wheel slot 32) 241–247 Color Macro 32 (wheel slot 33) 248–255 Color Macro 33 (wheel slot 34)
6	Dimmer	0	0–62 0 % Master 63–126 25 % Master 127–190 50 % Master 191–254 75 % Master 255–255 100 % Master
7	Dimmer Fine	0	Fine byte of Dimmer
8	Strobe Mode Strobe	0	0–2 Open 3–5 Strobe 6–50 Ramp up 51–100 Ramp down 101–150 Ramp up-down 151–200 Lighting 201–255 Random
9	Strobe Rate	0	0–126 Slow 127–254 Med 255–255 Fast
10	Strobe Duration	0	0–126 Slow 127–254 Med 255–255 Fast

13CH (continued)

Ch	Function	Default	DMX values
11	Color Macro1	0	0–5 Off 6–15 Macro 1 16–25 Macro 2 26–35 Macro 3 36–45 Macro 4 46–55 Macro 5 56–65 Macro 6 66–75 Macro 7 76–85 Macro 8 86–95 Macro 9 96–105 Macro 10 106–115 Macro 11 116–125 Macro 12 126–135 Macro 13 136–145 Macro 14 146–155 Macro 15 156–165 Macro 16 166–175 Macro 17 176–185 Macro 18 186–195 Macro 19 196–205 Macro 20 206–215 Macro 21 216–225 Macro 22 226–235 Macro 23 236–245 Macro 24 246–255 Macro 25
12	Color Macro1	0	0–5 No function 6–33 Macro1 34–60 Macro2 61–88 Macro3 89–116 Macro4 117–144 Macro5 145–172 Macro6 173–200 Macro7 201–228 Macro8 229–255 Macro9
13	Color Macro1Rate	0	