Dj Power

DJ Power WP-4



Manufacturer	**Dj Power**
Type	**Hazer**
DMX modes	**1**
DMX footprint	**4 channels**
Size (W × H × D)	**532 × 557 × 470 mm**
GDTF fixture type	**BBE2BBAC-9301-4AAD-8F5D-C…**

Controls

Fan · Haze or smoke output

Safety-relevant functions

Haze or smoke output

DMX modes

4-Channel Mode	4 ch

4-Channel Mode

4 channels

Ch	Function	Default	DMX values
1	Bubble Output Contro	0	0–10 No Bubble Output 11–255 Bubble Output 0-100%
2	Haze	0	0–10 No Haze 11–255 Haze 0-100%
3	Fan	0	0–10 No Fan 11–255 Fan 0-100%
4	Cleaning Mode Control	0	0–10 Cleaning Mode Off 11–255 Cleaning Mode On