Dj Power

H-20V IP co2 Fogger



Manufacturer	**Dj Power**
Type	**Hazer**
DMX modes	**1**
DMX footprint	**16 channels**
Beam angle	**18-25°**
Heads / cells	**2**
Size (W × H × D)	**405 × 185 × 338 mm**
GDTF fixture type	**2FD9F6C8-5678-439C-9469-C0…**

Controls

Haze or smoke output · Extra LED colours · Strobe · Dimmer · Pixel control

Safety-relevant functions

Haze or smoke output · Strobe · Built-in effect programmes

DMX modes

16CH — 16 ch

16CH

16 channels

Ch	Function	Default	DMX values
1	Haze	0	0–9 FOG OFF 10–255 FOG ON
2	Fans	255	0–128 FANS OFF 129–255 FANS ON
3	Red	255	0–8 NoFeature 9–254 Min 255–255 Max
4	Green	255	0–8 NoFeature 9–254 Min 255–255 Max
5	Blue	255	0–8 NoFeature 9–254 Min 255–255 Max
6	Color Add RY	9	0–8 NoFeature 9–254 Min 255–255 Max
7	Red	255	0–8 NoFeature 9–254 Min 255–255 Max
8	Green	255	0–8 NoFeature 9–254 Min 255–255 Max
9	Blue	255	0–8 NoFeature 9–254 Min 255–255 Max
10	Color Add RY	9	0–8 NoFeature 1 9–254 Min 255–255 Max
11	No Feature	0	
12	No Feature	0	
13	Effect	0	0–9 Off 10–255 Colour change (Slow to fast)
14	Shutter / Strobe	0	0–9 Shutter Open 10–255 Slow to fast strobe
15	Dimmer	0	
16	Control1	0	0–49 SAFETY ACTIVE 50–200 --- LIVE --- 201–255 SAFETY ACTIVE