Eagle Lite

IPSTORBE-1008



Manufacturer	**Eagle Lite**
Type	**Strobe**
DMX modes	**3**
DMX footprint	**2, 6, 11 channels**
Beam angle	**120°**
Size (W × H × D)	**452 × 100 × 100 mm**
GDTF fixture type	**E4EE7766-35E1-45BD-8C1D-F7…**

Controls

Effect speed · Strobe · Dimmer

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

Small Mode	2 ch
Simple mode	6 ch
EXT Mode	11 ch

Small Mode

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–9 Closed 10–71 0% Strobe 72–132 25% Strobe 133–193 50% strobe 194–254 75% Strobe 255–255 100% Strobe

Simple mode

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer	0	
3	Dimmer	0	
4	Dimmer	0	
5	Dimmer	0	
6	Dimmer	0	

EXT Mode

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer	0	
3	Dimmer	0	
4	Dimmer	0	
5	Dimmer	0	
6	Dimmer	0	
7	Dimmer	0	
8	Shutter / Strobe	9	0–9 Closed 10–71 0% Strobe 72–132 25% Strobe 133–193 50% strobe 194–254 75% Strobe 255–255 100% Strobe
9	Effect	0	0–9 No function 10–50 Auto show 1 51–100 Auto Show 2 101–150 Auto Show 3 151–200 Auto Show Loop 201–255 No function
10	Effect Speed	0	
11	Dimmer Curve	0	0–9 Dimmer curve based on menu settings 10–50 Dimmer curve 1 51–101 Dimmer curve 2 102–152 Dimmer curve 3 153–203 Dimmer curve 4 204–249 Dimmer curve 5 250–255 Dimmer curve 6