Elan Lighting

# city 24



| | |
|---|---|
| Manufacturer | **Elan Lighting** |
| Type | **Effect light** |
| DMX modes | **5** |
| DMX footprint | **2, 3, 6, 11, 19 channels** |
| Beam angle | **9.1°** |
| Size (W × H × D) | **545 × 285 × 218 mm** |
| GDTF fixture type | **ED5868E2-D371-41AF-AFBE-E6…** |

## Controls

Extra LED colours · Hue and saturation · RGB colour mixing · Colour temperature · Colour wheel · Effect speed · Dimmer

## Safety-relevant functions

Built-in effect programmes

## DMX modes

| | |
|---|---|
| Mode 2Ch | 2 ch |
| Mode 3 Ch | 3 ch |
| Mode 6Ch | 6 ch |
| Mode 11Ch | 11 ch |
| Mode 19Ch | 19 ch |

## Mode 2Ch

2 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Color Wheel | 0 | |
| 2 | C TO | 0 | |

## Mode 3 Ch

3 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | H SBHue | 0 | |
| 2 | H SBSaturation | 0 | |
| 3 | H SBBrightness | 0 | |

## Mode 6Ch

6 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Red | 0 | |
| 2 | Green | 0 | |
| 3 | Color Sub B | 0 | |
| 4 | White | 0 | |
| 5 | Color Add RY | 0 | |
| 6 | UV | 0 | |

## Mode 11Ch

11 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Dimmer | 0 | |
| 2 | Shutter1Strobe Random | 0 | |
| 3 | Red | 0 | |
| 4 | Green | 0 | |
| 5 | Blue | 0 | |
| 6 | White | 0 | |
| 7 | Color Add RY | 0 | |
| 8 | UV | 0 | |
| 9 | Dimmer Curve | 0 | |
| 10 | Effect | 0 | |
| 11 | Effect Speed | 0 | |

## Mode 19Ch

19 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Dimmer | 0 | |
| 2 | Dimmer Fine | 0 | Fine byte of Dimmer |
| 3 | Strobe Duration | 0 | |
| 4 | Red | 0 | |
| 5 | Red Fine | 0 | Fine byte of Red |
| 6 | Green | 0 | |
| 7 | Green Fine | 0 | Fine byte of Green |
| 8 | Blue | 0 | |

## Mode 19Ch (continued)

| Ch | Function | Default | DMX values |
|---|---|---|---|
| **9** | Blue Fine | 0 | Fine byte of Blue |
| **10** | White | 0 | |
| **11** | White Fine | 0 | Fine byte of White |
| **12** | Color Add RY | 0 | |
| **13** | Color Add RY Fine | 0 | Fine byte of Color Add RY |
| **14** | UV | 0 | |
| **15** | UV Fine | 0 | Fine byte of UV |
| **16** | Dimmer Mode | 0 | |
| **17** | Effect | 0 | |
| **18** | Effect Speed | 0 | |
| **19** | Control1 | 0 | |