Equinox

Helix XP Flower



Manufacturer	**Equinox**
Type	**Effect light**
DMX modes	**1**
DMX footprint	**8 channels**
Beam angle	**42°**
Size (W × H × D)	**80 × 80 × 25 mm**
GDTF fixture type	**87E1BB04-767A-4760-9F86-DF…**

Controls

Colour wheel · Strobe · Dimmer · Gobos · Gobo rotation

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

8ch Mode	8 ch

8ch Mode

8 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–0 Min 1–254 Min > Max 255–255 Max
2	Shutter / Strobe	32	0–31 Blackout 32–63 Open 64–64 Strobe Slow 65–94 Strobe S > F 95–95 Strobe Fast 96–127 No feature 1 128–128 Pulse Slow 129–158 Pulse S > F 159–159 Pulse Fast 160–191 No Feature 2 192–192 Random Slow 193–222 Random S > F 223–223 Random Fast 224–255 NoFeature 1
3	Color Wheel	0	0–15 Open (wheel slot 1) 16–29 Red (wheel slot 2) 30–43 Blue (wheel slot 3) 44–57 Magenta (wheel slot 4) 58–71 Yellow (wheel slot 5) 72–85 Green (wheel slot 6) 86–99 Orange (wheel slot 7) 100–113 Cyan (wheel slot 8) 114–120 Purple (wheel slot 9) 121–127 3200K (wheel slot 10) 128–128 ACW Fast 129–190 ACW F > S 191–191 ACW Slow 192–192 CW Slow 193–254 CW S > F 255–255 CW Fast
4	Gobo	0	0–16 Gobo 1 (wheel slot 1) 17–33 Gobo 2 (wheel slot 2) 34–50 Gobo 3 (wheel slot 3) 51–67 Gobo 4 (wheel slot 4) 68–84 Gobo 5 (wheel slot 5) 85–101 Gobo 6 (wheel slot 6) 102–118 Gobo 7 (wheel slot 7) 119–135 Gobo 8 (wheel slot 8) 136–136 ACW Fastest 137–194 ACW F > S 195–195 ACW Slowest 196–196 CW Slowest 197–254 CW S > F 255–255 CW Fastest
5	Gobo Rotation	0	0–0 Gobo Fully ACW 1–126 Gobo Manual Rotate 127–127 Gobo Fully CW 128–128 CW Fastest 129–190 CW F > S 191–191 CW Slowest 192–192 ACW Slowest 193–254 ACW S > F 255–255 ACW Fastest

8ch Mode (continued)

Ch	Function	Default	DMX values
6	Beam Effect Index Rotate Mode	0	0–0 Mirror Fully CW 1–126 Mirror Manual Rotate 127–127 Mirror Fully ACW 128–128 Mirror ACW Fastest 129–190 Mirror ACW F > S 191–191 Mirror ACW Slowest 192–192 Mirror CW Slowest 193–254 Mirror CW S > F 255–255 Mirror CW Fastest
7	Effect	0	0–12 Auto Programs Off 13–45 All Shows 46–80 Show 1 81–115 Show 2 116–150 Show 3 151–185 Show 4 186–220 Show 5 221–255 Show 6
8	Global MSpeed	0	0–0 Slowest 1–254 S > F 255–255 Fastest