Equinox

RGB Power Batten



Manufacturer	**Equinox**
Type	**LED bar**
DMX modes	**4**
DMX footprint	**2, 3, 4, 26 channels**
Beam angle	**25°**
Size (W × H × D)	**1075 × 65 × 85 mm**
GDTF fixture type	**B21210C0-70B8-4391-9273-7D…**

Controls

RGB colour mixing · Colour wheel · Effect speed · Dimmer

DMX modes

2 channel mode	2 ch
3 channel mode	3 ch
4 channel mode	4 ch
26 channel mode	26 ch

2 channel mode

2 channels

Ch	Function	Default	DMX values
1	Color Macro1	0	
2	Effect Speed	0	

3 channel mode

3 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	

4 channel mode

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Dimmer	0	0–254 Closed 255–255 Open

26 channel mode

26 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Reserved 4	0	
5	Reserved 5	0	
6	Reserved 6	0	
7	Reserved 7	0	
8	Reserved 8	0	
9	Reserved 9	0	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	Reserved 13	0	
14	Reserved 14	0	
15	Reserved 15	0	
16	Reserved 16	0	
17	Reserved 17	0	
18	Reserved 18	0	
19	Reserved 19	0	
20	Reserved 20	0	
21	Reserved 21	0	
22	Reserved 22	0	
23	Reserved 23	0	
24	Reserved 24	0	

26 channel mode (continued)

Ch	Function	Default	DMX values
25	Shutter1Strobe	0	
26	Dimmer	0	