Event Lighting

F160QW - Quad Colour Fresnel



Manufacturer	**Event Lighting**
Type	**Spot**
DMX modes	**2**
DMX footprint	**6, 11 channels**
Beam angle	**50°**
Size (W × H × D)	**180 × 127 × 45 mm**
GDTF fixture type	**B9E7743F-687D-46AD-A9C0-25…**

Controls

Extra LED colours · RGB colour mixing · Colour temperature · Dimmer

DMX modes

Standard mode 6Ch	6 ch
11 Ch Mode	11 ch

Standard mode 6Ch

6 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Color Add WW	0	
5	Dimmer	0	0–254 Closed 255–255 Open
6	Strobe Mode Strobe	119	0–15 NoFeature 1 16–118 Min Strobe 119–119 Max Strobe 120–127 NoFeature 2 128–182 Min Random 183–183 Max Random 184–191 NoFeature 3 192–246 Low Sensitivity 247–247 High Sensitivity 248–255 NoFeature 4

11 Ch Mode

11 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Red Fine	255	Fine byte of Red
3	Green	255	
4	Green Fine	255	Fine byte of Green
5	Blue	255	
6	Blue Fine	255	Fine byte of Blue
7	Color Add WW	0	
8	Color Add WW Fine	0	Fine byte of Color Add WW
9	Dimmer	0	0–254 Closed 255–255 Open
10	Strobe Mode Strobe	119	0–15 NoFeature 1 16–118 Min Strobe 119–119 Max Strobe 120–127 NoFeature 2 128–182 Min Random 183–183 Max Random 184–191 NoFeature 3 192–246 Low Sensitivity 247–247 High Sensitivity 248–255 NoFeature 4
11	C TC	0	0–9 Empty Channel Set 10–254 Warm White 255–255 Cool White