Expolite

Tour Blinder 400



Manufacturer	**Expolite**
Type	**Blinder**
DMX modes	**4**
DMX footprint	**1, 3, 4, 9 channels**
Beam angle	**60°**
Size (W × H × D)	**230 × 230 × 60 mm**
GDTF fixture type	**3A3F8346-C0F7-4423-8E31-734…**

Controls

Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

1 Ch	1 ch
3 Ch	3 ch
4 Ch	4 ch
9 Ch	9 ch

1 Ch

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	

3 Ch

3 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Shutter1Strobe	0	0–4 open 5–5 min strobe 6–254 slow to fast 255–255 max strobe

4 Ch

4 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer	0	
3	Dimmer	0	
4	Dimmer	0	

9 Ch

9 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Shutter1Strobe	0	0–4 open 5–5 min strobe 6–254 slow to fast 255–255 max strobe
4	Dimmer	0	
5	Dimmer	0	
6	Dimmer	0	
7	Dimmer	0	
8	Effect	0	0–35 No Function 36–255 Auto Mode
9	Dimmer Mode	0	0–10 Dimmer Mode 11–40 Mode 1 41–80 Mode 2 81–120 Mode 3 121–255 Dimmer Mode