Favolite

# Vader Pro 350



| | |
|---|---|
| Manufacturer | **Favolite** |
| Type | **Profile spot** |
| DMX modes | **1** |
| DMX footprint | **25 channels** |
| Beam angle | **3-46°** |
| Pan range | **540°** |
| Tilt range | **270°** |
| Size (W × H × D) | **337 × 306 × 128 mm** |
| GDTF fixture type | **55C593D4-1188-4844-B80C-1A…** |

## Controls

Focus · Frost · Iris · Prism · Prism rotation · Zoom · Extra LED colours · Colour temperature · Colour wheel · Dimmer · Gobos · Gobo rotation

## Safety-relevant functions

Fixture reset

## DMX modes

25Ch Standar — 25 ch

## 25Ch Standar

25 channels

| Ch | Function | Default | DMX values |
|---|---|---|---|
| 1 | Pan | 0 | |
| 2 | Pan Fine | 0 | Fine byte of Pan |
| 3 | Tilt | 127 | |
| 4 | Tilt Fine | 255 | Fine byte of Tilt |
| 5 | Color Wheel | 0 | 0–2 White (wheel slot 1)<br>3–5 Red (wheel slot 2)<br>6–9 Yellow (wheel slot 3)<br>10–12 Cyon (wheel slot 4)<br>13–15 Green (wheel slot 5)<br>16–24 Orange (wheel slot 6)<br>25–27 Purple (wheel slot 9)<br>28–30 Light Green (wheel slot 10)<br>31–33 Light Amber (wheel slot 11)<br>34–48 Deep Blue (wheel slot 12)<br>49–56 Purple (wheel slot 7)<br>57–255 Blue (wheel slot 8) |
| 6 | Color RGBCyan | 0 | |
| 7 | Color RGBMagenta | 0 | |
| 8 | Color RGBYellow | 0 | |
| 9 | C TO | 0 | |
| 10 | Gobo | 0 | 2–2 Gobo 1 (wheel slot 1)<br>3–4 Gobo 3 (wheel slot 3)<br>5–5 Gobo 4 (wheel slot 4)<br>6–7 Gobo 5 (wheel slot 5)<br>8–8 Gobo 6 (wheel slot 6)<br>9–10 Gobo 7 (wheel slot 7)<br>11–12 Gobo 8 (wheel slot 8)<br>13–13 Gobo 9 (wheel slot 9)<br>14–15 Gobo 10 (wheel slot 10)<br>16–16 Gobo 11 (wheel slot 11)<br>17–18 Gobo 12 (wheel slot 12)<br>19–20 Gobo 2 (wheel slot 2)<br>21–255 Gobo 14 (wheel slot 14) |
| 11 | Gobo Rotation | 0 | 3–5 Gobo 3 (wheel slot 3)<br>6–9 Gobo 4 (wheel slot 4)<br>10–12 Gobo 1 (wheel slot 1)<br>13–15 Gobo 7 (wheel slot 7)<br>16–18 Gobo 5 (wheel slot 5)<br>19–21 Gobo 6 (wheel slot 6)<br>22–255 Gobo 2 (wheel slot 2) |
| 12 | Gobo Rotation | 0 | |
| 13 | Dimmer | 0 | |
| 14 | Strobe Mode Strobe | 0 | |
| 15 | Dimmer Mode | 0 | |
| 16 | Prism | 0 | |
| 17 | Prism Rotation | 0 | |
| 18 | Zoom | 127 | |
| 19 | Focus | 0 | |
| 20 | Focus1Distance | 0 | |
| 21 | Focus1Distance | 0 | |
| 22 | Iris | 0 | |
| 23 | Frost1 | 0 | |
| 24 | Scan Speed | 0 | |

## 25Ch Standar (continued)

| Ch | Function | Default | DMX values |
|---|---|---|---|
| **25** | Control1 | 0 | |