Flash

DJ LED STROBE



Manufacturer	**Flash**
Type	**Strobe**
DMX modes	**4**
DMX footprint	**4, 11, 25, 32 channels**
Beam angle	**25°**
Size (W × H × D)	**300 × 150 × 200 mm**
GDTF fixture type	**865F5BC8-6D19-4808-85B0-5B…**

Controls

Extra LED colours · RGB colour mixing · Effect speed · Strobe · Dimmer · Pixel control

Safety-relevant functions

Strobe · Built-in effect programmes

DMX modes

4ch	4 ch
11ch	11 ch
32ch	25 ch
39ch	32 ch

4ch

4 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	White	0	

11ch

11 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	
3	Effect	0	
4	Effect Speed	0	
5	Red	255	
6	Green	255	
7	Blue	255	
8	Shutter / Strobe 2	0	
9	Effect 2	0	
10	Effect Speed 2	0	
11	White	0	

32ch

25 channels

Ch	Function	Default	DMX values
1	Red	255	
2	Green	255	
3	Blue	255	
4	Reserved 4	0	
5	Reserved 5	0	
6	Reserved 6	0	
7	Reserved 7	0	
8	Reserved 8	0	
9	Reserved 9	0	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	Reserved 13	0	
14	Reserved 14	0	
15	Reserved 15	0	
16	Reserved 16	0	
17	Reserved 17	0	
18	Reserved 18	0	
19	Reserved 19	0	
20	Reserved 20	0	
21	Reserved 21	0	
22	Reserved 22	0	
23	Reserved 23	0	

32ch (continued)

Ch	Function	Default	DMX values
24	Reserved 24	0	
25	White	0	

39ch

32 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Shutter / Strobe	0	
3	Effect	0	
4	Effect Speed	0	
5	Red	255	
6	Green	255	
7	Blue	255	
8	Reserved 8	0	
9	Reserved 9	0	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	Reserved 13	0	
14	Reserved 14	0	
15	Reserved 15	0	
16	Reserved 16	0	
17	Reserved 17	0	
18	Reserved 18	0	
19	Reserved 19	0	
20	Reserved 20	0	
21	Reserved 21	0	
22	Reserved 22	0	
23	Reserved 23	0	
24	Reserved 24	0	
25	Reserved 25	0	
26	Reserved 26	0	
27	Reserved 27	0	
28	Reserved 28	0	
29	Shutter / Strobe 2	0	
30	Effect 2	0	
31	Effect Speed 2	0	
32	White	0	