Fun Generation

LED Pot Strobe 100



Manufacturer	**Fun Generation**
Type	**Strobe**
DMX modes	**2**
DMX footprint	**1, 3 channels**
Beam angle	**25°**
Size (W × H × D)	**170 × 100 × 25 mm**
GDTF fixture type	**4D6A7EFE-7D7E-4AEF-88D2-F6…**

Controls

Dimmer

DMX modes

1ch	1 ch
3ch	3 ch

1ch

1 channel

Ch	Function	Default	DMX values
1	Dimmer	0	

3ch

3 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Dimmer Mode	0	0–0 DMX Control 1–127 Fade Animation (0%-100%) 128–255 Sound to Light (0%-100%)
3	Strobe Mode Strobe	0	0–1 No strobe 2–84 0 Hz 85–168 10 Hz 169–255 20 Hz