Fun_known

HALO PAR 64



Manufacturer	**Fun_known**
Type	**Moving head**
DMX modes	**1**
DMX footprint	**6 channels**
Beam angle	**25°**
Pan range	**540°**
Tilt range	**220°**
Size (W × H × D)	**312 × 188 × 244 mm**
GDTF fixture type	**A719875A-5221-47A7-AFAE-0B…**

Controls

Strobe · Dimmer

Safety-relevant functions

Fixture reset

DMX modes

Mode 1 — 6 ch

Mode 1

6 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–24 Closed 25–50 10% 51–63 20% 64–75 25% 76–101 30% 102–127 40% 128–152 50% 153–178 60% 179–190 70% 191–203 75% 204–229 80% 230–254 90% 255–255 Open
2	Shutter / Strobe	0	0–1 Open 2–254 Pulse · Slow 0.1–9.96 Hz 255–255 Pulse · Fast 10 Hz
3	Pan	128	
4	Tilt	128	
5	Pan Fine	0	Fine byte of Pan
6	Tilt Fine	0	Fine byte of Tilt