Ignition

co6 v2



Manufacturer	**Ignition**
Type	**PAR**
DMX modes	**1**
DMX footprint	**26 channels**
Beam angle	**25°**
Heads / cells	**3**
Size (W × H × D)	**385 × 100 × 145 mm**
GDTF fixture type	**5BD20E24-5C50-4EB3-A08E-DA…**

Controls

Dimmer · Pixel control

DMX modes

26 ch — 26 ch

26 ch

26 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Dimmer Fine	0	Fine byte of Dimmer
3	Shutter1Strobe	0	0–5 Open 6–10 Close 11–33 RandomPulse 34–56 Random Ramp Up 57–79 Random Ramp Down 80–102 Random Strobe 103–127 Strobe Break 128–250 Strobe 251–255 Open 1
4	Reserved 4	0	
5	Reserved 5	0	
6	Reserved 6	0	
7	Reserved 7	0	
8	Reserved 8	0	
9	Reserved 9	0	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	Reserved 13	0	
14	Reserved 14	0	
15	Red	0	
16	Green	0	
17	Blue	0	
18	White	0	
19	Red	0	
20	Green	0	
21	Blue	0	
22	White	0	
23	Red	0	
24	Green	0	
25	Blue	0	
26	White	0	