JB Systems

Striker



Manufacturer	**JB Systems**
Type	**Moving head**
DMX modes	**2**
DMX footprint	**4, 19 channels**
Beam angle	**25-36°**
Pan range	**540°**
Tilt range	**270°**
Size (W × H × D)	**240 × 450 × 220 mm**
GDTF fixture type	**5F71C8D9-B0D9-44C9-8383-4D…**

Controls

Focus · Extra LED colours · RGB colour mixing · Colour wheel · Strobe · Dimmer · Pan and tilt · Movement speed · Gobos

Safety-relevant functions

Fixture reset · Service functions · Strobe

DMX modes

5CH	4 ch
19CH	19 ch

5CH

4 channels

Ch	Function	Default	DMX values
1	Pan	0	
2	Tilt	0	
3	Focus	0	
4	Dimmer	0	

19CH

19 channels

Ch	Function	Default	DMX values
1	Pan	128	
2	Pan Fine	0	Fine byte of Pan
3	Tilt	128	
4	Tilt Fine	0	Fine byte of Tilt
5	Position MSpeed	0	
6	Color Macro1	0	0–23 Open (White) 24–47 Orange 48–71 Blue 72–95 Magenta 96–119 Yellow 120–143 Green 144–167 Blue (Dark) 168–191 Red 192–255 Rainbow (slow/fast/reverse)
7	Gobo	0	0–11 open (White) 12–23 Gobo1 24–35 Gobo2 36–47 Gobo3 48–59 Gobo4 60–71 Gobo5 72–83 Gobo6 84–95 Gobo7 96–111 Shaking 1 112–127 Shaking 2 128–143 Shaking 3 144–159 Shaking 4 160–175 Shaking 5 176–191 Shaking 6 192–255 Rainbow (Slow/Fast/Reverse)
8	Focus	0	
9	Dimmer	0	0–254 Closed 255–255 Open
10	Shutter / Strobe	255	0–4 Closed 5–250 Slow-Fast 251–255 Open
11	Dimmer W	0	0–254 Closed 255–255 Open
12	Shutter / Strobe 2	255	0–4 Closed 5–250 Slow-Fast 251–255 Open
13	Red	255	
14	Green	255	
15	Blue	255	
16	White	255	

19CH (continued)

Ch	Function	Default	DMX values
17	Color Effects1	0	0–7 Manual 8–47 Auto 1 48–87 Auto 2 88–127 Auto 3 128–167 Auto 4 168–207 Auto 5 208–247 Auto 6 248–255 Color/Gobo Sound Control
18	Position Effect	0	0–7 Manual 8–32 Prog 1 33–58 Prog 2 59–84 Prog 3 85–110 Prog 4 111–136 Prog 5 137–162 Prog 6 163–188 Prog 7 189–214 Prog 8 215–240 Prog 9 241–255 P/T Sound Control
19	Fixture Calibration Reset	0	