Lightsense

JW-PF300



Manufacturer	**Lightsense**
Type	**Profile spot**
DMX modes	**1**
DMX footprint	**2 channels**
Beam angle	**25°**
Size (W × H × D)	**250 × 450 × 250 mm**
GDTF fixture type	**BD1D1971-7A5D-4B19-980B-1…**

Controls

Dimmer

DMX modes

Default 2 ch

Default

2 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Strobe Duration	0	0–127 Strobe from fast to slow 128–159 Closing pluse in sequences 160–191 Opening pluse in sequences 192–255 Random strobe speed frome fast to slow