Lotus Light

ST 100 PiXEL



Manufacturer	**Lotus Light**
Type	**Strobe**
DMX modes	**2**
DMX footprint	**4, 16 channels**
Beam angle	**16°**
Heads / cells	**2**
Size (W × H × D)	**900 × 70 × 135 mm**
GDTF fixture type	**8577BF78-C6BB-4643-8174-6D…**

Controls

Extra LED colours · RGB colour mixing · Colour wheel · Effect speed · Strobe · Dimmer · Pixel control

Safety-relevant functions

Built-in effect programmes

DMX modes

Basic 4CH	4 ch
16 Standart	16 ch

Basic 4CH

4 channels

Ch	Function	Default	DMX values
1	Red	0	
2	Green	0	
3	Blue	0	
4	White	0	

16 Standart

16 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–5 No Function 6–255 Min > Max
2	Shutter / Strobe	0	0–9 Open - Shutter Open 10–254 Slow 255–255 High
3	Red	255	
4	Green	255	
5	Blue	255	
6	Effect	0	0–10 No Function 11–25 Effect 1 26–40 Effect 2 41–55 Effect 3 56–70 Effect 4 71–85 Effect 5 86–100 Effect 6 101–115 Effect 7 116–130 Effect 8 131–145 Effect 9 146–160 Effect 10 161–255 Effect 11
7	Effect Speed	0	0–127 Forward Flow F>S 128–255 Backward Flow S>F
8	Shutter / Strobe 2	0	0–19 No Function 20–254 W Strobe · Slow 255–255 W Strobe · Fast
9	White	255	
10	Effect 2	0	0–10 No Function 11–25 Effect 1 26–40 Effect 2 41–55 Effect 3 56–70 Effect 4 71–85 Effect 5 86–100 Effect 6 101–115 Effect 7 116–130 Effect 8 131–145 Effect 9 146–160 Effect 10 161–255 Effect 11
11	Effect Speed 2	0	0–127 Forward Flow F>S 128–255 Backward Flow S>F
12	Shutter / Strobe 3	0	0–254 Slow 255–255 High

16 Standart (continued)

Ch	Function	Default	DMX values
13	Effect 3	0	0–10 No Function 11–25 Effect 1 26–40 Effect 2 41–55 Effect 3 56–70 Effect 4 71–85 Effect 5 86–100 Effect 6 101–115 Effect 7 116–130 Effect 8 131–145 Effect 9 146–160 Effect 10 161–255 Effect 11
14	Effect Speed 3	0	0–127 Forward Flow F>S 128–255 Backward Flow S>F
15	Color Wheel	0	
16	Color Add RY	0	