LPL

Ribalta Strobo 3000



Manufacturer	**LPL**
Type	**PAR**
DMX modes	**2**
DMX footprint	**6, 14 channels**
Beam angle	**3-18°**
Heads / cells	**2**
Size (W × H × D)	**985 × 190 × 100 mm**
GDTF fixture type	**2F4D2A27-A21E-4EEC-BDAE-35…**

Controls

Extra LED colours · Colour wheel · Strobe · Dimmer · Pixel control

DMX modes

96CH	6 ch
14 CH	14 ch

96CH

6 channels

Ch	Function	Default	DMX values
1	Dimmer	255	
2	Shutter / Strobe	0	0–9 Open 10–90 STROBE SLOW TO FAST 91–169 PULSE EFFECT SLOW TO FAST 170–255 RANDOM STROBE SLOW TO FAST
3	White	255	
4	Red	255	
5	Green	255	
6	Blue	255	

14 CH

14 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–9 Open 10–90 STROBE SLOW TO FAST 91–169 PULSE EFFECT SLOW TO FAST 170–255 RANDOM STROBE SLOW TO FAST
3	Dimmer	255	
4	Reserved 4	0	
5	Reserved 5	0	
6	Reserved 6	0	
7	Red	255	
8	Green	255	
9	Blue	255	
10	Reserved 10	0	
11	Reserved 11	0	
12	Reserved 12	0	
13	White	255	
14	Color Macro1	0	