Magmatic

Magma Prime Fazer



Manufacturer	**Magmatic**
Type	**Hazer**
DMX modes	**3**
DMX footprint	**1, 3, 5 channels**
Size (W × H × D)	**338 × 400 × 160 mm**
GDTF fixture type	**E2EDD04B-1364-426B-8906-1B...**

Controls

Haze or smoke output

Safety-relevant functions

Haze or smoke output

DMX modes

Mode 1	1 ch
Mode3	3 ch
Mode 5	5 ch

Mode 1

1 channel

Ch	Function	Default	DMX values
1	Haze	0	0–254 Haze Min 255–255 Haze Max

Mode3

3 channels

Ch	Function	Default	DMX values
1	Haze	0	0–5 HazeOff 6–255 HazeOn
2	Haze	0	0–254 Haze Min 255–255 Haze Max
3	Blower1	0	0–254 Fan Min 255–255 Fan Max

Mode 5

5 channels

Ch	Function	Default	DMX values
1	Haze	0	0–5 HazeOff 6–255 HazeOn
2	Haze	0	0–254 Haze Min 255–255 Haze Max
3	Blower1	0	0–254 Fan Min 255–255 Fan Max
4	Haze	0	0–5 No Duration 6–254 1s 255–255 250s
5	Haze	0	0–5 No Interval 6–254 10s 255–255 2500s