MARK

BLINDER 400



Manufacturer	**MARK**
Type	**Blinder**
DMX modes	**2**
DMX footprint	**12 channels**
Beam angle	**60°**
Size (W × H × D)	**430 × 430 × 130 mm**
GDTF fixture type	**32FC0AA7-342D-4F22-A3E4-1E…**

Controls

Extra LED colours · Effect speed · Strobe · Dimmer

Safety-relevant functions

Built-in effect programmes

DMX modes

12CH A	12 ch
12CH B	12 ch

12CH A

12 channels

Ch	Function	Default	DMX values
1	Dimmer	0	0–254 Closed 255–255 Open
2	Color Add WW	255	
3	Color Add CW	255	
4	Color Add WW	255	
5	Color Add CW	255	
6	Color Add WW	255	
7	Color Add CW	255	
8	Color Add WW	255	
9	Color Add CW	255	
10	Shutter / Strobe	0	0–0 Open 1–255 Strobe S-F
11	Effect	0	0–50 No Function 51–100 Static Patterns 101–150 Jump White Change 151–200 Gradual White Change 201–250 Pulse White Change 251–255 Sound Mode
12	Effect Speed	0	

12CH B

12 channels

Ch	Function	Default	DMX values
1	Dimmer	0	
2	Shutter / Strobe	0	0–0 Open 1–255 Strobe S-F
3	Effect	0	0–50 No Function 51–100 Static Patterns 101–150 Jump White Change 151–200 Gradual White Change 201–250 Pulse White Change 251–255 Sound Mode
4	Effect Speed	0	
5	Color Add WW	255	
6	Color Add CW	255	
7	Color Add WW	255	
8	Color Add CW	255	
9	Color Add WW	255	
10	Color Add CW	255	
11	Color Add WW	255	
12	Color Add CW	255	